



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





# Electrician's / HVAC TRMS Multimeter

## MM6000

*Designed by Electricians  
for Electricians*



### ***True RMS & Low Impedance***

- Large backlit display.
- Analog bar graph.



Made in USA of US  
and imported parts.

PROFESSIONAL SERIES MULTIMETERS

# KLEIN<sup>®</sup> TOOLS

# PROFESSIONAL SERIES MULTIMETERS

## Electrician's / HVAC TRMS Multimeter

MEASUREMENT	MM6000
AC Current	10A
DC Current	10A
AC Voltage	1000V
DC Voltage	1000V
Resistance	50MΩ
Capacitance	6000 μF
Temperature	-58 ~ 1832°F
Frequency / Duty Cycle	399.9 kHz
Diode Test	●
Continuity	●
Lead Warning	●
Auto Hold	●
CAT Rating	CAT IV 600V
Basic DC Accuracy	±0.2%
Listing	
Dimensions:	7.00" H x 3.5" W x 1.875" D (178 mm H x 88.9 mm W x 47.6 mm D)
Weight:	14.0 oz. (397 g)
UPC:	0-9264469157-7
Included Accessories:	test leads, batteries, thermocouple, carrying case

**MM 6000**

**True RMS  
Low Impedance**

**Brighter Display**  
than most competitive units

**Bar Graph**  
measures fast moving readings

**Low Impedance**  
reduces ghost voltage

**μA Setting**  
for checking flame sensors

**True RMS**  
accurate readings for all signals

**10A AC/DC Current**

**Rubber Molding**  
for drop protection

Double Insulated

**Temperature**

**Lead Storage**  
protects leads

**1000V Voltage**  
reading

Safest rating available



### Accessories Available:

- Magnetic hanger
- Replacement test lead set
- Carrying case
- Replacement fuses
- Thermocouple



Made in USA of US and imported parts.



Measure Flame Sensors



Analog Bar Graph



Alligator Clips Attach to Bare Wire



Lead Storage

**⚠ WARNING:** Read, understand, and follow all instructions, cautions and warnings attached to and/or packed with all test and measurement devices before each use.

**KLEIN TOOLS**

See our complete line of test and measurement products at

[www.kleintools.com](http://www.kleintools.com)



© 2013 Klein Tools, Inc.  
Lincolnshire, IL. 60069-1418  
Printed in U.S.A. 96203