## imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



## MR9225 series



0.6 3.622 ±0.020 (92.0 ±0.5) 1 ±0.020 (25.4 ±0.50) 3.248 ±0.012 (82.5 ±0.3) 2- 0.157 ±0.012 (2- 4.0 ±0.3) Air Flow 0.197 ±0.039  $(5.0 \pm 1.0)$ 0 20 40 60 80 100 120 140 10.236 ±0.039 (92 x 92 x 25 mm) AIR VOLUME (CFM) Rotation (260 ±5) 8- Ø0.169 ±0.012 3.62 x 3.62 x 0.98 inches (8- Ø4.3 ±0.3) Features: soft start, polarity protection, auto-restart

Operating Voltage: 24 VDC		Model No.	Rated Voltage	Current A	Speed	Air Volume		Max. Static Pressure (H20)		Sound Noise	Weight
Construction:	UL94V-0 plastic impeller and frame	Wouer No.	VDC	24	RPM	M³/Min.	CFM	ММ	INCH	dbA	g
Bearing option:	ball bearing or sleeve	MR9225L	24	0.11	3,000	1.91	68	5.91	0.23	40.9	120
		MR9225M	24	0.19	3,600	2.28	81	8.42	0.33	45.1	120
Air Flow:	air exhaust over struts	MR9225H	24	0.25	4,000	2.53	90	10.35	0.40	48.0	120
Options:	tachometer output or locked rotor alarm signal; PWM speed	MR9225E	24	0.31	4,400	2.77	99	12.46	0.49	50.8	120
		MR9225X	24	0.42	4,800	3.02	107	14.78	0.58	53.0	120
	control										



**Cooling Simplified**