

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

TAA-Compliant OmniVS 230V 1500VA 940W Line-Interactive UPS, Extended Run, Tower, USB port, C13 Outlets

MODEL NUMBER: OMNIX1500XLTAA





Description

Tripp Lite's OMNIX1500XLTAA is compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases. This line interactive UPS system offers voltage regulation, surge suppression and long lasting, expandable battery support for personal computers, internetworking equipment and other sensitive electronics. Internal UPS circuits support entry level PC systems for up to 75 minutes during power failures so that connected equipment can be shut down without data loss. Automatic Voltage Regulation (AVR) circuits regulate brownouts as low as 151 and overvoltages up to 282 volts back to usable 230V levels without using battery power. Offers complete desktop power protection in an attractive black tower configuration. Includes 8 IEC320-C13 outlets with battery support and AC surge suppression. USB port enables optional unattended system shutdown without data loss in the case of extended power failure, USB cable included. PowerAlert software available via free download from www.tripplite.com. Built-in single line RJ jacks protect modem, fax machine, Ethernet, cordless phone or other peripheral with a standard dialup/DSL phone connection. Built-in audible alarm and 4 front panel LEDs indicate line power status, battery power status, battery low/replace status and voltage boost operation. 1500VA power handling ability supports entry-level PCs, network workstations, point-of-sale equipment, small business phone systems, audio/video equipment and home theater systems. Offers 4.5 minutes battery runtime with a full load of 1500VA and 13 minutes with a half load of 750VA. Supports hot-swappable battery replacement via built-in access panel. Extended runtime available with optional BP24V15RT2U or BP24V28-2U external battery packs.

Features

- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases
- OMNIX1500XLTAA Uninterruptible Power Supply offers voltage regulation, surge suppression and long lasting battery support
- Supports entry level PCs up to 75 minutes during blackouts to enable shutdown without data loss,
 runtime is further expandable by connecting an external battery pack
- Regulates brownouts as low as 151 and overvoltages to 282V back to usable 230V nominal levels without using battery power
- 8 IEC320 C13 outlets with complete AC surge suppression

Highlights

- Federal Trade Agreements Act / TAA Compliant for GSA
 Schedule purchase
- 1500VA / 1.5kVA tower 230V
 line interactive extended-run
 UPS
- Corrects brownouts and overvoltages from 151 to 282V
- USB port, TEL/DSL/ethernet protection, External battery pack options
- C14 input and 8 C13 outlets

Package Includes

- OMNIX1500XLTAA TAA
 Compliant line interactive UPS
- 2 C13 to C14 interconnection cables
- USB and phone line cables
- Owner's manual with warranty information



- C14 inlet accepts user-supplied AC power cord with country-specific plug
- USB port and cable enables unattended shutdown in the case of extended power failure
- PowerAlert software available via free download from www.tripplite.com
- Dataline surge suppression protects standard dialup/DSL or Ethernet line connection
- Audible alarm and 4 front panel LEDs offer complete UPS and line power status information
- 1500VA power handling ability supports a variety of sensitive electronic equipment
- 4.5 minutes full load runtime (1500VA), 13 minutes half load runtime (750VA)
- Runtime is further expandable with the addition of external battery packs
- Supports hot swappable battery replacement via built-in access panel
- Attractive full color retail packaging

Specifications

OVERVIEW		
UPC Code	037332153272	
ОИТРИТ		
Output Volt Amp Capacity (VA)	1500	
Output kVA Capacity (kVA)	1.5	
Output Watt Capacity (Watts)	940	
Nominal Output Voltage(s) Supported	230V	
Frequency Compatibility	50 / 60 Hz	
Output Voltage Regulation (Line Mode)	-18%, +8%	
Output Voltage Regulation (Battery Mode)	+/- 5%	
Output Receptacles	(8) C13	
Included Output Power Cables	Includes 2 C13 to C14 output power cables	
Output AC Waveform (AC Mode)	Sine wave	
Output AC Waveform (Battery Mode)	PWM sine wave	
INPUT		
Rated input current (Maximum Load)	5A	
Nominal Input Voltage(s) Supported	230V AC	
UPS Input Connection Type	C14 inlet	
UPS Input Connection Description	Attached 15cm line cord with C14 inlet. The C14 inlet accepts user-supplied AC power cord with country-specific plug.	





UPS Input Cord Length (ft.)	0.5
UPS Input Cord Length (m)	0.2
Input Phase	Single-Phase
BATTERY	
Full Load Runtime (min.)	4.5 min. (940w)
Half Load Runtime (min.)	13 min. (470w)
Expandable Battery Runtime	Extended runtime supported via optional external battery packs
External Battery Pack Compatibility	BP24V15RT2U (limit 1); BP24V28-2U (limit 1); BP24V28-2U">BP24V28-2U (limit 1); BP24V70-3U">BP24V70-3U (multi-pack compatible)
DC System Voltage (VDC)	24
Battery Recharge Rate (Included Batteries)	Less than 4.5 hours from 10% to 90%
Internal UPS Replacement Battery Cartridge	RBC51 (quantity 2)
Battery Access	Battery access door
Battery Replacement Description	Hot-swappable, user replaceable batteries
Expandable Runtime	Yes
Expandable Runtime VOLTAGE REGULATION	Yes
·	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282
VOLTAGE REGULATION	
VOLTAGE REGULATION Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282 Input voltages between 245 and 282 are reduced by 12%
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282 Input voltages between 245 and 282 are reduced by 12% Input voltages between 177 and 199 are boosted by 14% Input voltages between 151 and 176 are boosted by 30%
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282 Input voltages between 245 and 282 are reduced by 12% Input voltages between 177 and 199 are boosted by 14% Input voltages between 151 and 176 are boosted by 30%
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282 Input voltages between 245 and 282 are reduced by 12% Input voltages between 177 and 199 are boosted by 14% Input voltages between 151 and 176 are boosted by 30%
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282 Input voltages between 245 and 282 are reduced by 12% Input voltages between 177 and 199 are boosted by 14% Input voltages between 151 and 176 are boosted by 30% ITROLS 2 Switches control off/on power status and alarm-cancel/self-test operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Alarm Cancel Operation	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282 Input voltages between 245 and 282 are reduced by 12% Input voltages between 177 and 199 are boosted by 14% Input voltages between 151 and 176 are boosted by 30% ITROLS 2 Switches control off/on power status and alarm-cancel/self-test operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Alarm Cancel Operation Audible Alarm	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282 Input voltages between 245 and 282 are reduced by 12% Input voltages between 177 and 199 are boosted by 14% Input voltages between 151 and 176 are boosted by 30% ITROLS 2 Switches control off/on power status and alarm-cancel/self-test operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible alarm indicates power-failure and low-battery conditions
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Alarm Cancel Operation Audible Alarm LED Indicators	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282 Input voltages between 245 and 282 are reduced by 12% Input voltages between 177 and 199 are boosted by 14% Input voltages between 151 and 176 are boosted by 30% ITROLS 2 Switches control off/on power status and alarm-cancel/self-test operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible alarm indicates power-failure and low-battery conditions
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Alarm Cancel Operation Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282 Input voltages between 245 and 282 are reduced by 12% Input voltages between 177 and 199 are boosted by 14% Input voltages between 151 and 176 are boosted by 30% ITROLS 2 Switches control off/on power status and alarm-cancel/self-test operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible alarm indicates power-failure and low-battery conditions 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status
VOLTAGE REGULATION Voltage Regulation Description Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Alarm Cancel Operation Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 151 to 282 Input voltages between 245 and 282 are reduced by 12% Input voltages between 177 and 199 are boosted by 14% Input voltages between 151 and 176 are boosted by 30% ITROLS 2 Switches control off/on power status and alarm-cancel/self-test operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible alarm indicates power-failure and low-battery conditions 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status



PHYSICAL		
Installation Form Factors Supported with Included Accessories	Tower	
Installation Form Factors Supported with Optional Accessories	Wallmount (UPSWM - tower mounting kit)	
Primary Form Factor	Tower	
UPS Power Module Dimensions (hwd, in.)	11.8 x 7.2 x 7.5	
UPS Power Module Dimensions (hwd, cm)	29.97 x 18.29 x 19.05	
UPS Power Module Weight (lbs.)	32	
UPS Power Module Weight (kg)	14.51	
Shipping Dimensions (hwd / in.)	15.500 x 11.000 x 11.250	
Shipping Dimensions (hwd / cm)	39.37 x 27.94 x 28.58	
Shipping Weight (lbs.)	35.0000	
Shipping Weight (kg)	15.88	
UPS Housing Material	Polycarbonate	
Primary UPS Height (mm)	300	
Primary UPS Width (mm)	183	
Primary UPS Depth (mm)	191	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	98.8	
Battery Mode BTU / Hr. (Full Load)	654.6	
AC Mode Efficiency Rating (100% Load)	97%	
COMMUNICATIONS		
Communications Interface	USB	
PowerAlert Software	Free download from www.tripplite.com	
Communications Cable	USB interface cable included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	
LINE / BATTERY TRANSFER		
Transfer Time	2-4 milliseconds	



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234

Low Voltage Transfer to Battery Power (Setpoint)	151		
High Voltage Transfer to Battery Power (Setpoint)	282		
SPECIAL FEATURES			
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported		
High Availability UPS Features	Hot swappable batteries		
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS		
CERTIFICATIONS			
UPS Certifications	Tested to UL1778 (USA); CE; Tested to GOST (Russia); Tested to SASO (Saudi Arabia); Tested to IRAM (Argentina); ROHS (Restriction of Hazardous Substances); TAA Compliant		
UPS Certification Details	CE 62040		
WARRANTY			
Product Warranty Period (Worldwide)	2-year limited warranty		

© 2018 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies