

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









Small Power Choke Coil PCMC(B) series, PW.PS series



Low DCR, small size with high current capability, high efficiency and low loss.


DIA / DO T

Small electronics equipment for Applications communication, information, imaging, audio etc.

RoHS compliant



SPECIFICATIONS



PCMC(B) Type							
Dimension (mm)	PCMC(B)042T	PCMC053T					
L	4.5max.	5.2max.					
W	4.0±0.3	4.7±0.2					
Т	2.0max.	3.0max.					
Α	1.0±0.1	1.5±0.1					
A1	0.8 ± 0.3	1.0±0.3					
В	2,2±0.2	1.8±0.2					
B1	B1 1.5±0.3						

PW.PS I	ype				
Dimension	P	W	PS	031	D0044D
(mm)	021T Type	25201B Type	031T Type	031B Type	PS041B
L	1.9±0.2	1.95±0.1	2.9±	0.2	$3.8\!\pm\!0.2$
W	1.9 ± 0.2	2.45±0.1	2.9±	0.2	$3.8\!\pm\!0.2$
Р	0.4	±0.2	0.75	±0.2	1.0 ± 0.2
Т	1.0+0.1	12+01	10+01	12+01	12+01

Electrical

Jour		PW ty	ре		
PW021T-***MS	L0(μH)	Rdc($Rdc(m\Omega)$		Saturation current
PWUZII- IVIS	Inductance	Typical	MAX.	(A)	(A)
R50	0.5	85	100	1.50	2.40
1R0	1.0	120	150	1.20	1.80
2R2	2.2	300	350	0.85	1.20
3R3	3.3	430	500	0.75	0.98
4R7	4.7	600	700	0.65	0.80
6R8	6.8	780	900	0.55	0.73
100	10.0	1200	1400	0.45	0.61

PW25201BT-***MS	L0(μH)	Rdc(mΩ) F		Rated current	Saturation current
FW23201D1- W3	Inductance	Typical	MAX.	(A)	(A)
R47	0.47	47	56	2.20	3.70
1R0	1.0	73	88	1.80	2.70
1R5	1.5	105	126	1.50	2.10
2R2	2.2	129	155	1.30	1.70
3R3	3.3	227	272	1.00	1.30
4R7	4.7	338	406	0.80	1.15

PCMC(B) type

PCMC042T-***MN	L0(μH)	$Rdc(m\Omega)$		Rated current	Saturation current
POMOU421- IVIN	Inductance	Typical	MAX.	(A)	(A)
R10	0.10	4.5	5.0	11	30
R22	0.22	7.3	8.0	9	17
R47	0.47	14.0	15.5	6	11.5
1R0	1.00	32.0	36.0	3.8	8.5

PCMB042T-***MS	L0(μH)	$Rdc(m\Omega)$		Rated current	Saturation current
PUNDU421- INS	Inductance	Typical	MAX.	(A)	(A)
R10	0.10	3.5	4.0	12	22
R22	0.22	6.0	6.6	9	13
R47	0.47	12.5	12.0	7	9.5
1R0	1.00	24.0	27.0	4.5	7.0
1R5	1.50	38.0	46.0	4.0	6.0
2R2	2.20	52.0	58.0	3.0	5.0

PCMC053T-***MN	L0(μH)	$Rdc(m\Omega)$		Rated current	Saturation current
PCIVICUSS 1- IVIIN	Inductance	Typical	MAX.	(A)	(A)
R68	0.68	11.0	12.0	8.5	14.0
1R0	1.0	13.0	14.0	7.0	11.0
1R2	1.2	15.0	16.0	6.5	11.0
1R5	1.5	18.0	20.0	6.0	10.0
2R2	2.2	29.0	35.0	5.5	9.0
3R3	3.3	32.0	38.0	5.0	7.0

	1 O type				
PS031B-***MS	L0(μH)	Rdc($m\Omega)$	Rated current	Saturation current
F3031B- 1013	Inductance	Typical	MAX.	(A)	(A)
2R2	2.2	75	90	1.40	1.10
4R7	4.7	120	140	1.20	0.77
6R8	6.8	160	190	1.00	0.67
100	10.0	260	300	0.90	0.54

PS031T-***MS	L0(μH)	$Rdc(m\Omega)$		Rated current	Saturation current
F30311- 1013	Inductance	Typical	MAX.	(A)	(A)
2R2	2.2	90	105	1.30	1.10
3R3	3.3	130	150	1.20	0.90
4R7	4.7	170	200	1.00	0.75
6R8	6.8	200	230	0.90	0.65
100	10.0	300	340	0.80	0.52

PS041B-***MS	L0(μH)	$Rdc(m\Omega)$		Rated current	Saturation current
P5041B- IVI5	Inductance	Typical	MAX.	(A)	(A)
2R2	2.2	80	95	1.30	1.70
3R3	3.3	100	120	1.10	1.40
4R7	4.7	120	145	1.00	1.15
6R8	6.8	180	216	0.84	1.00

: Current that will increase temperature by 40°C Rated current Saturating current : The current that decreases inductance by 30%

for PS and PW. 20% for PCMC (B)

Packaging : 2,000 piece reel for PW, PS031T(B)

1000 piece reel for PCMC042T, PCMC053T



PART NUMBER

