



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





PM55A Digital Multimeter

The compact precision DMM with AutoTect™ and Voltect™

The ultimate shirt-pocket sized meter. Only 3/8" thick and less than 3 oz in weight with full functionality offering ac and dc voltage to 600 V, AC and DC current to 2000 μ A, resistance to 6 Megohm, capacitance to 2000 μ F, frequency to 30 kHz, diode test and continuity w/beeper. It also offers Voltect™, a built-in, non-contact voltage detector for AC voltages.

Another key feature is AutoTect™, which automatically selects between AC voltage, DC voltage or resistance measurement based on the test point to which the leads are

connected. Fully autoranging, this meter offers nine different measurement functions plus features that are usually found in much more expensive and larger meters. The digital display is oversized with large digits and unit icons in the display. In spite of its size, this meter is fully safety rated to CAT III 300 V, CAT II 600 V and is UL approved.

No other meter this small offers such performance and high safety ratings. Includes a silicone protective holster, deluxe carrying case, attached test leads, battery and manual.

No hassle warranty

No waiting.

No shipping charges.



Our commitment to high-quality products and customer service is demonstrated by our industry exclusive "No Hassle" warranty. In the unlikely event that an Amprobe Test Tool requires warranty service, any of our local dealers are authorized to replace it, on the spot.

(note: \$500 MSLP limit)

- AutoTect™ feature directs the meter to know if it is measuring AC volts, DC volts or resistance with no user interface
- The AutoTect™ feature has lower input impedance which zeros out ghost voltages
- Measures AC/DC current, capacitance, frequency, continuity with beeper plus includes Voltect™, a built-in, non-contact voltage detector
- Large oversize digital display
- Protective silicon holster included, attached test leads, battery, deluxe carry case and manual
- One-year, no-hassle warranty



PM55A Digital Multimeter

Data Sheet

General Specifications

Display and update rate	3-5/6 digits 6000 counts; Updates 5 per second nominal
Operating temperature	0 °C - 40 °C
Relative humidity	Max. 80 % R.H. up to 31 °C, decreasing linearly to 50 % R.H. at 40 °C
Altitude	Operating below 2000 m
Storage temperature	-20 °C ~ 60 °C, < 80 % R.H. (with battery removed)
Temperature coefficient	Nominal 0.15 x (specified accuracy)/ °C @ (0 °C ~ 18 °C or 28 °C ~ 40 °C), or otherwise specified
Sensing	Average sensing
Overload protection	600 V DC and V AC RMS
Low battery	Below approx. 2.4 V
Power supply	3 V standard button battery x 1 (IEC-CR2032; ANSI-NEDA-5004LC)
Power consumption (typical)	6 mA for voltage functions on Auto-V W position & 2 mA for other functions
Automatic Power Off (APO) timing	Idle for 3 minutes
APO consumption (typical)	2.2 µA
Dimension	L 113 mm x W 53 mm x H 10.2 mm (4.4 x 2.1 x 0.4 in)
Weight	Approx. 78 gm (3 oz)
Special features	AutoTect™ (Automatic V & Ω selection) and VoltTect™ (Electric Field Detection)
Agency approvals	CE, cULus
Safety	Meets IEC61010-1, UL61010B-1, CAN/CSA-C22.2 No. 1010.1-92, CAT II 600 V and CAT III 300 V, Pollution Degree 2, Class 2
E.M.C.	Meets EN61326

Specifications

Function	Range	Accuracy
RF field @ 3 V/m Specified accuracy + 45 d (capacitance not specified)		
DC Voltage		
	6.000 V	± (0.5 % + 3 dgt)
	60.00 V	± (1.0 % + 5 dgt)
	600 V (AutoTect™ Lo-Z)	2.0 %
	600 V (Hi-Z only)	1.5 % + 5 dgt
NMRR > 30 dB @ 50 Hz/60 Hz		
CMRR > 100 dB @ DC, 50 Hz/60 Hz; Rs=1 kΩ		
Input impedance AutoTect™ Lo-Z V DC: 833 kΩ (4.2 kW when displaying AUTO), 90 pF nom.		
V DC AutoTect™ threshold >		+1.2 V DC or < -0.6 V DC nominal (Hi-Z V DC only)
AC Voltage (50 Hz - 60 Hz)		
	6.000 V, 60.00 V, 600 V	± (1.5 % + 5 dgt)
CMRR > 60 dB @ DC to 60 Hz, Rs=1 kW		
Input impedance AutoTect™ Lo-Z V AC: 160 kΩ, 160 pF nominal		
Hi-Z ACV 5 MW, 90 pF nominal		
ACV AutoTect™ threshold > 1.5 V ac (50 Hz/60 Hz) nominal		

Specifications

Function	Range	Accuracy	
Capacitance			
	100.0 nF, 1000 nF, 10.0 μ F, 100.0 μ F, 2000 μ F ^{1 3}	\pm (3.5 % + 6 dgt) ²	
¹ Accuracy below 50 nF is not specified ⁴ Specified with battery voltage above 2.8 V (half full battery).			
² Accuracies with film capacitor or better Accuracy decreases gradually to 12% at low battery warning			
³ Updates > 1 minute on large values voltage of approx. 2.4 V.			
Resistance			
Range Accuracy			
	600.0 Ω	\pm (2.0% + 6 dgt) ²	
	6.000 k Ω	\pm (1.2% + 6 dgt) ²	
	60.00 k Ω , 600.0 k Ω	\pm (1.0% + 4 dgt)	
	6.000 M Ω	\pm (2.0% + 4 dgt)	
Open circuit voltage 0.4 V DC typical			
¹ AutoTect™ is for 6.000 k Ω ~ 6.000 M Ω ranges			
² Add 40 dgt to specified accuracy while reading is below 20 % of range			
Frequency			
	10.00 Hz - 30.00 kHz ^{1, 2}	\pm (0.5 % + 4 dgt) < 20 V Sine-rms	
	10.00 Hz - 999.9 Hz	\pm (0.5 % + 4 dgt) < 600 V Sine-rms	
¹ Sensitivity (Sine-rms): Hz in Auto-V (position: > 3 V			
² Line-level Hz in V position: @6.000 V AC range: > 3 V; @60.00 V AC range: > 6 V; @600.0 V AC range: > 60 V			
DC μA Current			
	Range	Accuracy	Burden voltage
	400.0 μ A	\pm (1.5 % + 3 dgt)	6 mV/ μ A
	2000 μ A	\pm (1.2 % + 3 dgt)	6 mV/ μ A
AC μA Current			
	Range	Accuracy	Burden voltage
	400.0 μ A	\pm (2.0 % + 3 dgt)	6 mV/ μ A
	2000 μ A	\pm (1.5 % + 3 dgt)	6 mV/ μ A
VolTect™			
Typical voltage Bar graph indication			
15 V to 55 V	--		
30 V to 85 V	---		
55 V to 145 V	----		
85 V to 190 V	-----		
above 120 V	-----		
Indication Bar graph segments & audible beep tones proportional to field strength			
Detection frequency 50/60 Hz			
Detection antenna Top left corner of the meter			
Audible Continuity Tester (600 Ω range)			
Open circuit voltage 0.4 V DC typical			
Audible threshold 50 Ω to 300 Ω			
Diode Test			
Diode test current 0.48 mA			
Open circuit voltage < 1.6 V DC			

PM55A Digital Multimeter

Data Sheet

Included Accessories

H-PMA protective holster, VC3A zippered carrying case, battery installed and user's manual.

Amprobe® Test Tools

website: www.Amprobe.com
email: info@amprobe.com
Everett, WA 98203
tel: 877-AMPROBE

Amprobe® Test Tools Europe

In den Engematten 14
79286 Glottertal, Germany
Tel.: +49 (0) 7684 8009 - 0