



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Quality Products. Service Excellence.

## Horizontal Finger Cable Manager *RB-HFM Series*

### Features



- Metal components constructed in 16-gauge steel.
- Three (3) inch length fingers constructed in black plastic.
- Snap-on, hinged door.
- Includes cutouts at rear for cable pass-through.
- Fits standard EIA-310-D compliant mounting rails.
- Metal components finished in textured black powder paint.
- Requires mounting hardware.
- RoHS and REACH compliant.

Part of the Rack Basics® line of economy rack solutions.

### Accessories



- Mounting Hardware
- Hook and Loop Roll

**RACK BASICS®**



Part No.	Overall Dimensions			Usable Mounting Dimensions	
	Height	Width	Depth	Rack Units	Height
RB-HFM1	1.72	19.00	4.37	1U	1.75
RB-HFM2	3.22	19.00	4.37	2U	3.50

### Estimated Cable Fill Capacities

Rack Units	Description	Recommended Cable Fill (50% Fill Ratio)			Maximum Cable Fill (100% Fill Ratio)		
		Cat 5e	Cat 6	Cat 6a	Cat 5e	Cat 6	Cat 6a
1U	Channel Opening	32	20	14	63	40	28
	Finger Opening	27	18	12	55	35	24
	Rear Pass Through	31	20	14	62	40	28
2U	Channel Opening	77	49	34	154	99	69
	Finger Opening	27	18	12	55	35	24
	Rear Pass Through	60	39	27	121	77	54

Data subject to change without notice

