imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Optoschmitt Detector Totem-Pole Output

FEATURES


- Side-looking plastic package
- 55° (nominal) acceptance angle
- TTL/LSTTL/CMOS compatible
- Totem- pole output
- Buffer (SDP8004) or inverting (SDP8014) logic available
- High noise immunity output
- Mechanically and spectrally matched to SEP8506 and SEP8706 infrared emitting diodes

DESCRIPTION

The SDP8004/8014 series consists of a high speed IC molded in a side- looking black plastic package to minimize the effect of visible ambient light. The detector incorporates a Schmitt trigger which provides pulse shaping and hysteresis for noise immunity. The totem- pole output is well- suited for applications which require fast transition times. The output can drive 10 TTL loads. Output rise and fall times are independent of rate of change of incident light. Detector sensitivity has been internally temperature compensated. For additional output configuration options refer to SDP8304/8314 and SDP8604/8614.

Device Polarity:


Buffer - Output is HI when incident light intensity is above the turn- on threshold level. Inverter - Output is LO when incident light intensity is above the turn- on threshold level.



OUTLINE DIMENSIONS in inches (mm)

Tolerance

3 plc decimals ±0.005(0.12) 2 plc decimals ±0.020(0.51)



DIM_026.ds4

Honeywell

Honeywell reserves the right to make changes in order to improve design and supply the best products possible.

184

Optoschmitt Detector Totem-Pole Output

ELECTRICAL CHARACTERISTICS (-40°C to +85°C unless otherwise noted)						
PARAMETER	SYMBOL	MIN	TYP	МАХ	UNITS	TEST CONDITIONS
Operating Supply Voltage	Vcc	4.5		7.0	V	T _A =25°C
Turn-on Threshold Irradiance (2) SDP8004-301, SDP8014-301	Eet(+)	0.06		0.37	mW/cm ²	Vcc=5 V T _A =25°C
Hysteresis (3)	HYST	33		67	%	
Supply Current	lcc			15.0	mA	Vcc=5.5 V Ee=0 Or 3.0 mW/cm²
High Level Output Voltage SDP8004 SDP8014	Vон	2.4 2.4			V	V _{CC} =4.5 V, I _{OH} =0.8 mA Ee=3.0 mW/cm² Ee=0
Low Level Output Voltage SDP8004 SDP8014	Vol			0.4 0.4	V	V _{CC} =5.5 V, I _{OL} =12.8 mA Ee=0 Ee=3.0 mW/cm²
Short Circuit Output Current SDP8004 SDP8014	los	-20 -20		-100 -100	mA	V _{cc} =5.5 V, Output=GND Ee=3.0 mW/cm ² Ee=0
Operate Point Temperature Coefficient	Ортс		-0.76		%/°C	Emitter @ Constant Temperature
Output Rise Time, Output Fall Time	t _r , t _f		70		ns	V _{CC} =5 V, T _A =25°C E _E =0 or 3.0 mW/cm ² f=10.0 kHz, D.C.=50% R _L =8 TTL Loads
Propagation Delay, Low-High, High-Low	tрլн, tрнг		2.5	5.0	μs	V _{cc} =5 V, T _A =25°C E _e =0.5 mW/cm ² f=10.0 kHz, D.C.=50% R _L =8 TTL Loads
Clock Frequency				100	kHz	RL=390 Ω, CL=50 pF

Notes

1. It is recommended that a bypass capacitor, 0.1 µF typical, be added between V_{CC} and GND near the device in order to stabilize The recommendee that a bypass capacitor, 0.1 µF typical, be added between vcc and GND hear the device in order to stabilize power supply line.
The radiation source is an IRED with a peak wavelength of 935 nm.
Hysteresis is defined as the difference between the operating and release threshold intensities, expressed as a percentage of the operate threshold intensity.


ABSOLUTE MAXIMUM RATINGS

(25°C Free-Air Temperature unless otherwise noted)

Supply Voltage Duration of Output Short to Vcc or Ground High Level Output Current Irradiance Operating Temperature Range Storage Temperature Range

Soldering Temperature (5 sec) Notes

1. Derate linearly from 25°C to 5.5 V at 85°C.




SCHEMATIC SDP8004 BUFFER, TOTEM-POLE

Honeywell reserves the right to make changes in order to improve design and supply the best products possible.


Honeywell


O Vo


Optoschmitt Detector Totem-Pole Output




SWITCHING WAVEFORM FOR BUFFERS












cir 011.cd









Honeywell

Honeywell reserves the right to make changes in order to improve design and supply the best products possible.


186

Optoschmitt Detector Totem-Pole Output





All Performance Curves Show Typical Values



Honeywell reserves the right to make changes in order to improve design and supply the best products possible.

Honeywell