



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





SER2USB - Cable



Adapter to connect printers and multifunction printers with an **USB** connection to the **COM** interface of PCs, measuring devices, laboratory and diagnostic devices, control panels, medical devices as well as all other products with a serial interface.

Hardware description



↓
Printer

↑
serial interface

Supported systems

All systems. No drivers or software are required.

Technical data

Power supply

Input: 100-240V / 50/60Hz

Output: 5Volt / about 100 mA
Cable: about 1.8m

USB interface

USB USB1.0 Low-Speed
USB1.1 Low/ Full-Speed
USB2.0 Low / Full-Speed

Class: Printer
Class: HUB

Plug: USB - B
Cable: about 1.8m

Speed: Low-Speed 1.5 MBit/sec
Full-Speed 12 MBit/sec

Serial interface

Speed: 2400 – 115200 Baud

Protocol: None,RTS/CTS
XON/XOFF

Parity: None,Odd,Even

Databits: 7,8

Stopbits 1,2

Jack: 9-pole SUB-D

Supported Features

Only printing.

Scanning, PC-Fax, and Software -
Toolboxes are not supported

GDI - Printer (without own
emulation) are not supported.

