



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





## SOLAR-500 Solar Analyzer

Professional analyzer for testing, maintenance, troubleshooting and efficiency of solar panels. The analyzer is used in the installation of solar panels to determine the proper inverter size, optimum power output position of panels and identifies broken or worn-out cells.

- I-V Curve test for solar cell
- Maximum Solar Power (Pmax) search by auto-scan (60V, 6A)
- Maximum Voltage (Vmaxp) at Pmax
- Maximum Current (Imaxp) at Pmax
- Voltage at open circuit (Vopen)
- Current at short circuit (Ishort)
- I-V curve with cursor
- Calculation of panel efficiency (%)
- Manual single point test

### No hassle warranty

*No waiting.*

*No shipping  
charges.*



Our commitment to high-quality products and customer service is demonstrated by our industry exclusive "No Hassle" warranty. In the unlikely event that an Amprobe Test Tool requires warranty service, any of our local dealers are authorized to replace it, on the spot.

(note: \$500 MSLP limit)



## SOLAR-500 Solar Analyzer

## Data Sheet

### Specifications

<b>DC Voltage</b>	
Range	0~6V / 6~10V / 10~60V
Resolution	0.001V / 0.001V / 0.01V
Accuracy	$\pm 1\% \pm (1\% \text{ of } V_{\text{open}} \pm 9 \text{ mV}) / \pm 1\% \pm (1\% \text{ of } V_{\text{open}} \pm 0.09 \text{ V}) / \pm 1\% \pm (1\% \text{ of } V_{\text{open}} \pm 0.09 \text{ V})$
<b>DC Current</b>	
Range	0~0.6A / 0.6~1A / 1~6A
Resolution	0.1mA / 0.1mA / 1mA
Accuracy	$\pm 1\% \pm (1\% \text{ of } I_{\text{short}} \pm 0.9 \text{ mA}) / \pm 1\% \pm (1\% \text{ of } I_{\text{short}} \pm 9 \text{ mA}) / \pm 1\% \pm (1\% \text{ of } I_{\text{short}} \pm 9 \text{ mA})$
<b>General Specifications</b>	
Battery Type	1.2V AA rechargeable battery x 8 (2500mAh)
AC Adaptor	AC 110V or 220V input, DC 12V/3A output
Dimension	257(L) x 155(W) x 57(H) mm (10.1 x 6.1 x 2.2 in)
Weight	1160 g (2.6 lb) (Batteries included)
Operation Environment	0°C to 50°C (32°F to 122°F), 85% RH
Temperature Coefficient	0.1% of full scale / °C (< 18°C or > 28°C)
Storage Environment	-20°C to 60°C (-4°F to 140°F), 75% RH
Accessories	Users manual x 1, Software Manual x 1, 1.2V AA rechargeable batteries x 8, AC adaptor x 1, RS232C (to USB Bridge) cable x 1, Software CD x 1, Kelvin Clips (6A max) x 1 set

### Amprobe® Test Tools

website: [www.Amprobe.com](http://www.Amprobe.com)  
email: [info@amprobe.com](mailto:info@amprobe.com)  
Everett, WA 98203  
Tel: 877-AMPROBE

### Amprobe® Test Tools Europe

In den Engematten 14  
79286 Glottertal, Germany  
Tel.: +49 (0) 7684 8009 - 0