

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!




Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



BOURNS®

**TISP3240F3, TISP3260F3,
TISP3290F3, TISP3320F3, TISP3380F3**

HIGH-VOLTAGE DUAL BIDIRECTIONAL THYRISTOR OVERVOLTAGE PROTECTORS

TISP3xxxF3 (HV) Overvoltage Protector Series

**Ion-Implanted Breakdown Region
Precise and Stable Voltage
Low Voltage Overshoot under Surge**

DEVICE	V _{DRM} V	V _(BO) V
'3240F3	180	240
'3260F3	200	260
'3290F3	220	290
'3320F3	240	320
'3380F3	270	380

**Planar Passivated Junctions
Low Off-State Current <10 μ A**

Rated for International Surge Wave Shapes

Waveshape	Standard	I _{TSP} A
2/10 μ s	GR-1089-CORE	175
8/20 μ s	IEC 61000-4-5	120
10/160 μ s	FCC Part 68	60
10/700 μ s	ITU-T K.20/21 FCC Part 68	50
10/560 μ s	FCC Part 68	45
10/1000 μ s	GR-1089-CORE	35

 UL Recognized Component

Description


These high-voltage dual bidirectional thyristor protectors are designed to protect ground backed ringing central office, access and customer premise equipment against overvoltages caused by lightning and a.c. power disturbances. Offered in five voltage variants to meet battery and protection requirements, they are guaranteed to suppress and withstand the listed international lightning surges in both polarities. Overvoltages are initially clipped by breakdown clamping until the voltage rises to the breakdown level, which causes the device to switch. The high crowbar holding current prevents d.c. latchup as the current subsides.

How To Order

Device	Package	Carrier	Order As
TISP3xxxF3	D, Small-outline	Tape And Reeled	TISP3xxxF3DR
	P, Plastic Dip	Tube	TISP3xxxF3P
	SL, Single-in-line	Tube	TISP3xxxF3SL


Insert xxx value corresponding to protection voltages of 240 through to 380

D Package (Top View)




NC - No internal connection

P Package (Top View)




Specified T terminal ratings require connection of pins 1 and 8.
Specified R terminal ratings require connection of pins 4 and 5.

SL Package (Top View)



MD1XAB

Device Symbol



SD3XAA

Terminals T, R and G correspond to the alternative line designators of A, B and C

TISP3xxxF3 (HV) Overvoltage Protector Series

BOURNS®

Description (continued)

These monolithic protection devices are fabricated in ion implanted planar structures to ensure precise and matched breakdown control and are virtually transparent to the system in normal operation.

Absolute Maximum Ratings, $T_A = 25^\circ\text{C}$ (Unless Otherwise Noted)

Rating	Symbol	Value	Unit
Repetitive peak off-state voltage, $0^\circ\text{C} < T_A < 70^\circ\text{C}$	V_{DRM}	'3240F3	± 180
		'3260F3	± 200
		'3290F3	± 220
		'3320F3	± 240
		'3380F3	± 270
Non-repetitive peak on-state pulse current (see Notes 1 and 2)	I _{PPSM}	350	
1/2 (Gas tube differential transient, 1/2 voltage wave shape)		175	
2/10 (Telcordia GR-1089-CORE, 2/10 voltage wave shape)		90	
1/20 (ITU-T K.22, 1.2/50 voltage wave shape, 25 Ω resistor)		120	
8/20 (IEC 61000-4-5, combination wave generator, 1.2/50 voltage wave shape)		60	
10/160 (FCC Part 68, 10/160 voltage wave shape)		55	A
4/250 (ITU-T K.20/21, 10/700 voltage wave shape, simultaneous)		38	
0.2/310 (CNET I 31-24, 0.5/700 voltage wave shape)		50	
5/310 (ITU-T K.20/21, 10/700 voltage wave shape, single)		50	
5/320 (FCC Part 68, 9/720 voltage wave shape, single)		45	
10/560 (FCC Part 68, 10/560 voltage wave shape)		35	
10/1000 (Telcordia GR-1089-CORE, 10/1000 voltage wave shape)			
Non-repetitive peak on-state current, $0^\circ\text{C} < T_A < 70^\circ\text{C}$ (see Notes 1 and 3)	I _{TSM}	4.3	
50 Hz, 1 s		5.7	
		7.1	A
Initial rate of rise of on-state current, Linear current ramp, Maximum ramp value < 38 A	d _I /dt	250	A/ μs
Junction temperature	T _J	-65 to +150	°C
Storage temperature range	T _{stg}	-65 to +150	°C

NOTES: 1. Further details on surge wave shapes are contained in the Applications Information section.
 2. Initially, the TISP® device must be in thermal equilibrium with $0^\circ\text{C} < T_J < 70^\circ\text{C}$. The surge may be repeated after the TISP® device returns to its initial conditions.
 3. Above 70°C , derate linearly to zero at 150°C lead temperature.

Electrical Characteristics for R and T Terminal Pair, $T_A = 25^\circ\text{C}$ (Unless Otherwise Noted)

Parameter	Test Conditions	Min	Typ	Max	Unit
I _{DRM} Repetitive peak off-state current	$V_D = \pm 2V_{\text{DRM}}$, $0^\circ\text{C} < T_A < 70^\circ\text{C}$			± 10	μA
I _D Off-state current	$V_D = \pm 50\text{ V}$			± 10	μA
C _{off} Off-state capacitance	$f = 100\text{ kHz}$, $V_d = 100\text{ mV}$, $V_D = 0$, Third terminal voltage = -50 V to +50 V (see Notes 4 and 5)	D Package P Package SL Package	0.05 0.065 0.03	0.15 0.2 0.1	pF

NOTES: 4. These capacitance measurements employ a three terminal capacitance bridge incorporating a guard circuit. The third terminal is connected to the guard terminal of the bridge.
 5. Further details on capacitance are given in the Applications Information section.

TISP3xxxF3 (HV) Overvoltage Protector Series

BOURNS®

Electrical Characteristics for T and G or R and G Terminals, $T_A = 25^\circ\text{C}$ (Unless Otherwise Noted)

Parameter	Test Conditions	Min	Typ	Max	Unit
I_{DRM} Repetitive peak off-state current	$V_D = \pm V_{DRM}$, $0^\circ\text{C} < T_A < 70^\circ\text{C}$			± 10	μA
$V_{(BO)}$ Breakover voltage	$dv/dt = \pm 250 \text{ V/ms}$, $R_{\text{SOURCE}} = 300 \Omega$	'3240F3 '3260F3 '3290F3 '3320F3 '3380F3		± 240 ± 260 ± 290 ± 320 ± 380	V
$V_{(BO)}$ Impulse breakover voltage	$dv/dt \leq \pm 1000 \text{ V}/\mu\text{s}$, Linear voltage ramp, Maximum ramp value = $\pm 500 \text{ V}$ $R_{\text{SOURCE}} = 50 \Omega$	'3240F3 '3260F3 '3290F3 '3320F3 '3380F3	± 267 ± 287 ± 317 ± 347 ± 407		V
$I_{(BO)}$ Breakover current	$dv/dt = \pm 250 \text{ V/ms}$, $R_{\text{SOURCE}} = 300 \Omega$		± 0.1	± 0.6	A
V_T On-state voltage	$I_T = \pm 5 \text{ A}$, $t_W = 100 \mu\text{s}$			± 3	V
I_H Holding current	$I_T = \pm 5 \text{ A}$, $di/dt = -/+30 \text{ mA/ms}$		± 0.15		A
dv/dt Critical rate of rise of off-state voltage	Linear voltage ramp, Maximum ramp value < $0.85V_{DRM}$		± 5		$\text{kV}/\mu\text{s}$
I_D Off-state current	$V_D = \pm 50 \text{ V}$			± 10	μA
C_{off} Off-state capacitance	$f = 1 \text{ MHz}$, $V_d = 0.1 \text{ V r.m.s.}$, $V_D = 0$ $f = 1 \text{ MHz}$, $V_d = 0.1 \text{ V r.m.s.}$, $V_D = -5 \text{ V}$ $f = 1 \text{ MHz}$, $V_d = 0.1 \text{ V r.m.s.}$, $V_D = -50 \text{ V}$ (see Notes 5 and 6)		57 26 11	95 45 20	pF

NOTES: 6 These capacitance measurements employ a three terminal capacitance bridge incorporating a guard circuit. The third terminal is connected to the guard terminal of the bridge.
7. Further details on capacitance are given in the Applications Information section.

Thermal Characteristics

Parameter	Test Conditions	Min	Typ	Max	Unit
$R_{\theta JA}$ Junction to free air thermal resistance	$P_{\text{tot}} = 0.8 \text{ W}$, $T_A = 25^\circ\text{C}$ 5 cm^2 , FR4 PCB	D Package		160	$^\circ\text{C}/\text{W}$
		P Package		100	
		SL Package		135	

Parameter Measurement Information




Figure 1. Voltage-Current Characteristics for any Terminal Pair

TISP3xxxF3 (HV) Overvoltage Protector Series

BOURNS®

Typical Characteristics - R and G or T and G Terminals




Figure 2.




Figure 3.




Figure 4.




Figure 5.

Typical Characteristics - R and G or T and G Terminals




Figure 6.




Figure 7.




Figure 8.




Figure 9.

Typical Characteristics - R and G or T and G Terminals




Figure 10.

TISP3xxxF3 (HV) Overvoltage Protector Series

BOURNS®

Typical Characteristics - R and T Terminals




Figure 11.




Figure 12.




Figure 13.




Figure 14.

Thermal Information

MAXIMUM NON-RECURRING 50 Hz CURRENT

VS

CURRENT DURATION

TI3HAA




Figure 15.

THERMAL RESPONSE

TI3MAA




Figure 16.

APPLICATIONS INFORMATION

Electrical Characteristics

The electrical characteristics of a TISP® device are strongly dependent on junction temperature, T_J . Hence, a characteristic value will depend on the junction temperature at the instant of measurement. The values given in this data sheet were measured on commercial testers, which generally minimize the temperature rise caused by testing. Application values may be calculated from the parameters' temperature coefficient, the power dissipated and the thermal response curve, Z_θ (see M. J. Maytum, "Transient Suppressor Dynamic Parameters." TI Technical Journal, vol. 6, No. 4, pp.63-70, July-August 1989).

Lightning Surge

Wave Shape Notation

Most lightning tests, used for equipment verification, specify a unidirectional sawtooth waveform which has an exponential rise and an exponential decay. Wave shapes are classified in terms of peak amplitude (voltage or current), rise time and a decay time to 50% of the maximum amplitude. The notation used for the wave shape is *amplitude, rise time/decay time*. A 50 A, 5/310 μ s wave shape would have a peak current value of 50 A, a rise time of 5 μ s and a decay time of 310 μ s. The TISP® surge current graph comprehends the wave shapes of commonly used surges.

Generators

There are three categories of surge generator type, single wave shape, combination wave shape and circuit defined. Single wave shape generators have essentially the same wave shape for the open circuit voltage and short circuit current (e.g. 10/1000 μ s open circuit voltage and short circuit current). Combination generators have two wave shapes, one for the open circuit voltage and the other for the short circuit current (e.g. 1.2/50 μ s open circuit voltage and 8/20 μ s short circuit current). Circuit specified generators usually equate to a combination generator, although typically only the open circuit voltage waveshape is referenced (e.g. a 10/700 μ s open circuit voltage generator typically produces a 5/310 μ s short circuit current). If the combination or circuit defined generators operate into a finite resistance, the wave shape produced is intermediate between the open circuit and short circuit values.

Current Rating

When the TISP® device switches into the on-state it has a very low impedance. As a result, although the surge wave shape may be defined in terms of open circuit voltage, it is the current wave shape that must be used to assess the required TISP® surge capability. As an example, the ITU-T K.21 1.5 kV, 10/700 μ s open circuit voltage surge is changed to a 38 A, 5/310 μ s current waveshape when driving into a short circuit. Thus, the TISP® surge current capability, when directly connected to the generator, will be found for the ITU-T K.21 waveform at 310 μ s on the surge graph and not 700 μ s. Some common short circuit equivalents are tabulated below:

Standard	Open Circuit Voltage	Short Circuit Current
ITU-T K.21	1.5 kV, 10/700 μ s	37.5 A, 5/310 μ s
ITU-T K.20	1 kV, 10/700 μ s	25 A, 5/310 μ s
IEC 61000-4-5, combination wave generator	1.0 kV, 1.2/50 μ s	500 A, 8/20 μ s
Telcordia GR-1089-CORE	1.0 kV, 10/1000 μ s	100 A, 10/1000 μ s
Telcordia GR-1089-CORE	2.5 kV, 2/10 μ s	500 A, 2/10 μ s
FCC Part 68, Type A	1.5 kV, <10/>160 μ s	200 A, <10/>160 μ s
FCC Part 68, Type A	800 V, <10/>560 μ s	100 A, <10/>160 μ s
FCC Part 68, Type B	1.5 kV, 9/720 μ s	37.5 A, 5/320 μ s

Any series resistance in the protected equipment will reduce the peak circuit current to less than the generators' short circuit value. A 1 kV open circuit voltage, 100 A short circuit current generator has an effective output impedance of 10 Ω (1000/100). If the equipment has a series resistance of 25 Ω , then the surge current requirement of the TISP® device becomes 29 A (1000/35) and not 100 A.

APPLICATIONS INFORMATION

Protection Voltage

The protection voltage, ($V_{(BO)}$), increases under lightning surge conditions due to thyristor regeneration. This increase is dependent on the rate of current rise, di/dt , when the TISP® device is clamping the voltage in its breakdown region. The $V_{(BO)}$ value under surge conditions can be estimated by multiplying the 50 Hz rate $V_{(BO)}$ (250 V/ms) value by the normalized increase at the surge's di/dt (Figure 7). An estimate of the di/dt can be made from the surge generator voltage rate of rise, dv/dt , and the circuit resistance.

As an example, the ITU-T K.21 1.5 kV, 10/700 μ s surge has an average dv/dt of 150 V/ μ s, but, as the rise is exponential, the initial dv/dt is higher, being in the region of 450 V/ μ s. The instantaneous generator output resistance is 25 Ω . If the equipment has an additional series resistance of 20 Ω , the total series resistance becomes 45 Ω . The maximum di/dt then can be estimated as 450/45 = 10 A/ μ s. In practice, the measured di/dt and protection voltage increase will be lower due to inductive effects and the finite slope resistance of the TISP® breakdown region.

Capacitance**Off-state Capacitance**

The off-state capacitance of a TISP® device is sensitive to junction temperature, T_J , and the bias voltage, comprising of the d.c. voltage, V_D , and the a.c. voltage, V_d . All the capacitance values in this data sheet are measured with an a.c. voltage of 100 mV. The typical 25 °C variation of capacitance value with a.c. bias is shown in Figure 17. When $V_D \gg V_d$, the capacitance value is independent on the value of V_d . The capacitance is essentially constant over the range of normal telecommunication frequencies.




Figure 17.

APPLICATIONS INFORMATION

Longitudinal Balance

Figure 18 shows a three terminal TISP® device with its equivalent “delta” capacitance. Each capacitance, C_{TG} , C_{RG} and C_{TR} , is the true terminal pair capacitance measured with a three terminal or guarded capacitance bridge. If wire R is biased at a larger potential than wire T, then $C_{TG} > C_{RG}$. Capacitance C_{TG} is equivalent to a capacitance of C_{RG} in parallel with the capacitive difference of $(C_{TG} - C_{RG})$. The line capacitive unbalance is due to $(C_{TG} - C_{RG})$ and the capacitance shunting the line is $C_{TR} + C_{RG}/2$.

All capacitance measurements in this data sheet are three terminal guarded to allow the designer to accurately assess capacitive unbalance effects. Simple two terminal capacitance meters (unguarded third terminal) give false readings as the shunt capacitance via the third terminal is included.





Figure 18.

MECHANICAL DATA

D008 Plastic Small-outline Package

This small-outline package consists of a circuit mounted on a lead frame and encapsulated within a plastic compound. The compound will withstand soldering temperature with no deformation, and circuit performance characteristics will remain stable when operated in high humidity conditions. Leads require no additional cleaning or processing when used in soldered assembly.



NOTES: A. Leads are within 0.25 (0.010) radius of true position at maximum material condition.
 B. Body dimensions do not include mold flash or protrusion.
 C. Mold flash or protrusion shall not exceed 0.15 (0.006).
 D. Lead tips to be planar within ± 0.051 (0.002).


MDXXAAC

MARCH 1994 - REVISED OCTOBER 2000
 Specifications are subject to change without notice.

MECHANICAL DATA

D008 Tape Dimensions

D008 Package (8-pin Small Outline) Single-Sprocket Tape



DIMENSIONS ARE: METRIC
(INCHES)

NOTES: A. Taped devices are supplied on a reel of the following dimensions:-

MDXXATB

Reel diameter: $\frac{330 +0.0/-4.0}{(12.992 +0.0/-157)}$

Reel hub diameter: $\frac{100 \pm 2.0}{(3.937 \pm .079)}$


Reel axial hole: $\frac{13.0 \pm 0.2}{(.512 \pm .008)}$

B. 2500 devices are on a reel.

MECHANICAL DATA

D008 Plastic Dual-in-Line Package

This dual-in-line package consists of a circuit mounted on a lead frame and encapsulated within a plastic compound. The compound will withstand soldering temperature with no deformation, and circuit performance characteristics will remain stable when operated in high humidity conditions. The package is intended for insertion in mounting-hole rows on 7.62 (0.300) centers. Once the leads are compressed and inserted, sufficient tension is provided to secure the package in the board during soldering. Leads require no additional cleaning or processing when used in soldered assembly.




NOTES: A. Each pin centerline is located within 0.25 (0.010) of its true longitudinal position.
 B. Dimensions fall within JEDEC MS001 - R-PDIP-T, 0.300" Dual-In-Line Plastic Family.

MDXXCF

MECHANICAL DATA

SL003 3-pin Plastic Single-In-Line Package

This single-in-line package consists of a circuit mounted on a lead frame and encapsulated within a plastic compound. The compound will withstand soldering temperature with no deformation, and circuit performance characteristics will remain stable when operated in high humidity conditions. Leads require no additional cleaning or processing when used in soldered assembly.



NOTES: A. Each pin centerline is located within 0.25 (0.010) of its true longitudinal position.
 B. Body molding flash of up to 0.15 (0.006) may occur in the package lead plane.

MDXXCE