

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China








TS441165





Wiring Diagram



V = Voltage S1 = Initiate Switch L = Load

R_T is used when external adjustment is ordered.

Description

The TS441165 is an analog delay-on-make timer with a normally closed solid-state output. Unlike an interval timer, the load is energized prior to and during the time delay period. It can be used as a faster starting interval time delay when S1 is closed upon application of input voltage.

Operation (Delay-on-Make NC)

Upon application of input voltage, the load is energized immediately. When the initiate switch is closed, the time delay begins. At the end of the time delay, the load de-energizes.

Reset: When the initiate switch is reopened, the load again energizes and the time delay is reset. Removing input voltage resets the time delay and output.

Features & Benefits

FEATURES	BENEFITS			
Analog circuitry	Repeat Accuracy + / - 2%			
Compact, low cost design	Allows flexiblility for OEM applications			
1A steady, 10A inrush solid-state output	Provides 100 million operations in typical conditions.			
Load energized prior to and during time delay	Faster operation			
Totally solid state and encapsulated	No moving parts to arc and wear out over time and encapsulated to protect against shock, vibration, and humidity			
Normally closed output	Can be used as a faster starting interval time delay			

Accessories



P1004-XX, P1004-XX-X Versa-Pot

Panel mountable, industrial potentiometer recommended for remote time delay adjustment.



P1023-6 Mounting bracket

The 90° orientation of mounting slots makes installation/removal of modules quick and easy.



P0700-7 Versa-Knob

Designed for 0.25 in (6.35 mm) shaft of Versa-Pot. Semi-gloss industrial black finish.



P1015-64 (AWG 14/16) **Female Quick Connect**

These 0.25 in. (6.35 mm) female terminals are constructed with an insulator barrel to provide strain relief.



P1015-18 Quick Connect to Screw Adapter

Screw adapter terminal designed for use with all modules with 0.25 in. (6.35 mm) male guick connect terminals.



TS441165

Accessories



C103PM (AL) DIN Rail

35 mm aluminum DIN rail available in a 36 in. (91.4 cm) length.



P1023-20 DIN Rail Adapter

Allows module to be mounted on a 35 mm DIN type rail with two #10 screws.



VTP(X)(X) Plug-on Adjustment Module

Mounts on modules with in-line adjustment terminals. Rated at 0.25W at 55°C. Available in resistance values from $5K\Omega$ to $5M\Omega$.

Selection Table for VTP Plug-on Adjustment Accessory


Time Delay	VTP P/N
1 - 0.05-3s	VTP4B
2 - 0.5-60s	VTP4F
3 - 2-180s	VTP4J
4 - 5-600s	VTP5N

Selection Guide

R _T Selection Chart					
Des	R-				
	1,,1				
1	2	3	4	Megohm	
0.05	0.5	2	5	0.0	
0.5	10	30	60	0.5	
1.0	20	60	120	1.0	
1.5	30	90	180	1.5	
2.0	40	120	240	2.0	
2.5	50	150	300	2.5	
3.0	60	180	360	3.0	
			420	3.5	
			480	4.0	
			540	4.5	
			600	5.0	

^{*} When selecting an external R_T add at least 20% for tolerance of unit and the R_T.

Function Diagram



V = VoltageS1 =Initiate Switch L = LoadTD =Time Delay R = Reset = Undefined Time

Specifications

Time Delay

Type Analog circuitry Range 165s Adjustment Fixed

Repeat Accuracy ±2% or 20ms, whichever is greater; under

fixed conditions

Tolerance

(Factory Calibration) ≤ ±10%

Time Delay vs Temp.

& Voltage $\leq \pm 10\%$ **Recycle Time** ≤ 150ms

Input 120VAC Voltage **Tolerance** ±20% **AC Line Frequency** 50/60 Hz

Output

Type Solid state

NC, closed during timing **Form**

Maximum Load Current 1A steady state, 10A inrush at 60°C **Voltage Drop** ≈ 2.5V @ 1A

Protection

Mechanical

Circuitry Encapsulated

Dielectric Breakdown ≥ 2000V RMS terminals to mounting surface

Insulation Resistance \geq 100 M Ω

Surface mount with one #10 (M5 x 0.8) screw Mounting

Dimensions H 50.8 mm (2.0"); **W** 50.8 mm (2.0");

D 30.7 mm (1.21")

Termination 0.25 in. (6.35 mm) male quick connect terminals **Environmental**

Operating/Storage **Temperature** -40° to 75° C / -40° to 85° C Humidity 95% relative, non-condensing

Weight $\approx 2.4 \text{ oz } (68 \text{ g})$