



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Contents

Device	Part number	Quantity
Cable assembly RPC-N 75 Ω plug / RPC-N 75 Ω plug	L20-001-600	2

Assembly parts

Technical data sheet cable assembly:
RPC- N 75 Ω plug / RPC-N 75 Ω plug

L20-001-XXX

Electrical data

Impedance	75 Ω
Frequency	DC to 4 GHz
Return loss ¹	≥ 28 dB, DC to 3 GHz
	≥ 23 dB, 3 to 4 GHz
Insertion loss ¹	≤ 0.70 dB at 4 GHz
Phase deviation:	
After 90° bending	≤ 2.5°, DC to 4 GHz
Straight after 3x90° bending	≤ 1.5°, DC to 4 GHz
Amplitude stability	≤ 0.03 dB, DC to 4 GHz
Return loss stability	≥ 42 dB, DC to 4 GHz

Individual testing and documentation:

Measurement plot with all 4 S-Parameters (S11; S22; S21; S12) is included with the cable assembly and on the backside the care and handling instruction is printed. Measurement adaptors used are mentioned in the commentary field.

¹ Return Loss and Insertion Loss includes the measurement adaptor

Mechanical data

Minimum bend radius:	50 mm
----------------------	-------

Environmental data

Temperature range	-40°C to +80°C
RoHS	compliant

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date	Rev.	Engineering change number	Name	Date
Martin Moder	07/12/15	Herbert Babinger	08/12/15	e00	15-1612	M.Ruf	08/12/15
Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany www.rosenberger.de					Tel. : +49 8684 18-0 Email : info@rosenberger.de		Page 2 / 2