



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Pen Vibration Meter

✓ **Measures RMS Acceleration and Velocity**
with metric and imperial units of measure

Features:

- Ranges — Acceleration (RMS): 656ft/s²; 20.39g; 200m/s², Velocity (RMS): 7.87in/s; 2.00cm/s; 200mm/s
- Wide frequency range of 10Hz to 1kHz
- Resolution to 1ft/s²; 0.01g; 0.1m/s² and 0.02in/s; 0.01cm/s; 0.1mm/s
- Basic accuracy of $\pm(5\% + 2 \text{ digits})$
- Zero adjustment
- Data Hold freezes the reading in the display
- Water and dust resistant to IP65
- Low battery indicator
- Dimensions: Meter: 6.9 x 1.6 x 1.3" (175 x 40 x 32mm); Sensing Head: 0.4" dia x 1.9" (9mm dia x 30mm) Weight: 0.53lbs (240g)
- Complete with test pin tip, magnetic base, 4 x AAA batteries, and pouch case

Applications:

- Motors, bearings
- Fans
- Pumps
- Rotating machinery
- Plant maintenance



Magnetic base included



Ordering Information:

VB400Pen Vibration Meter

