

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China

PNP SILICON PLANAR MEDIUM POWER HIGH VOLTAGE TRANSISTORS


ISSUE 1 – JULY 94

FEATURES

- * 300 Volt V_{CEO}
- * 0.5 Amp continuous current
- * $P_{tot} = 1$ Watt

ZTX556

ZTX557



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	ZTX556		ZTX557		UNIT
Collector-Base Voltage	V_{CBO}		-200		-300	V
Collector-Emitter Voltage	V_{CEO}		-200		-300	V
Emitter-Base Voltage	V_{EBO}			-5		V
Peak Pulse Current	I_{CM}			-1		A
Continuous Collector Current	I_C			-0.5		A
Power Dissipation	P_{tot}			1.0		W
Operating and Storage Temperature Range	$T_j; T_{stg}$			-55 to +200		°C

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ C$ unless otherwise stated).

PARAMETER	SYMBOL	ZTX556		ZTX557		UNIT	CONDITIONS.
		MIN.	MAX	MIN.	MAX		
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-200		-300		V	$I_C = -100\mu A$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-200		-300		V	$I_C = -10mA^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-5		-5		V	$I_E = -100\mu A$
Collector Cut-Off Current	I_{CBO}		-0.1		-0.1	μA	$V_{CB} = -160V$ $V_{CB} = -200V$
Emitter Cut-Off Current	I_{EBO}		-0.1		-0.1	μA	$V_{EB} = -4V$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		-0.3		-0.3	V	$I_C = -50mA$, $I_B = -5mA^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$		-1		-1	V	$I_C = -50mA$, $I_B = -5mA^*$
Base-Emitter Turn-on Voltage	$V_{BE(on)}$		-1		-1	V	$I_C = -50mA$, $V_{CE} = -10V^*$
Static Forward Current Transfer Ratio	h_{FE}	50 50	300	50 50	300		$I_C = -10mA$, $V_{CE} = -10V^*$ $I_C = -50mA$, $V_{CE} = -10V^*$
Transition Frequency	f_T	75		75		MHz	$I_C = -50mA$, $V_{CE} = -10V$ $f = 100MHz$

ZTX556
ZTX557

TYPICAL CHARACTERISTICS

