# imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Technical Data Sheet		Rosenberg	Rosenberger		
4.3-10	Panel Jack	64K409-200B1			
(36)	M20x1 M20x1	Z Z Z Z Z Z Z Z Z Z Z Z Z Z Z Z Z Z Z			
	Pg2 01 01 01 01 01 01 01 01 01 01				
All dimension Interface According to	ons are in mm; tolerances according t	o ISO 2768 m-H 61169-54			
Document Panel pierci		4b			
Material at Connector Center con Outer conta Body Dielectric Gasket	parts Mat tact CuE act Bra: Bra: PTF	ss Silver, 3-6 μm ss White bronze(e.g. Optalloy®)			
Rosenberger H P.O.Box 1260 /ww.rosenberg	ochfrequenztechnik GmbH & Co. KG D-84526 Tittmoning Germany <u>er.de</u>	Tel. : +49 8684 18-0 Email : <u>info@rosenberger.de</u>	Page 1 / 2		

Dieses Dokument ist urheberrechtlich geschützt • This document is protected by copyright • Rosenberger Hochfrequenztechnik GmbH & Co. KG

RF\_35/05.10/6.1

#### **Technical Data Sheet**

#### 4.3-10

### Panel Jack

# Rosenberger

### 64K409-200B1

Electrical data	
Impedance Frequency	50 Ω DC to 12 GHz
Return loss	$\geq$ 36 dB @ DC to 4 GHz
	$\geq$ 32 dB @ 4 GHz to 6 GHz
Insertion loss	$\leq$ 0.05 x $\sqrt{f[GHz]}$ dB
Insulation resistance	$\geq$ 5 G $\Omega$
Center contact resistance	≤ 1.0 mΩ
Outer contact resistance Test voltage	≤ 1.0 mΩ 2500 V rms
Working voltage	500 V rms
RF-leakage	$\geq$ 110 dB @ DC to 6 GHz for tool tightened plugs
	$\geq$ 90 dB @ DC to 3 GHz for tool-less plugs
Power handling (at 90 °C, altitude 3000m)	≥ 70 dB @ 3 to 6 GHz for tool-less plugs 500 W @ 2.0 GHz
Intermodulation (3 <sup>rd</sup> order)	$\geq$ 160 dBc (2 x 46 dBm) @ 0.4 – 4.0 GHz
· · ·	≥ 166 dBc (2 x 43 dBm) @ 0.4 – 4.0 GHz
- RL value only valid for the interface -	_
Mechanical data	
Mating cycles Center contact captivation: axial	≥ 100 > 30 N
radial	> 5 Ncm
Center contact retention force	1.5 - 20 N
Outer contact retention force Engagement force	4 - 35 N typ. 100 N
Disengagement force	typ. 80N
Recommended torque	5 Nm
Environmental data	
Temperature range	-55 °C to +90 °C operating temperature
Thermal shock Corrosion resistance	IEC 61169-1 9.4.4 ISO 21207 method B
Vibration	IEC 61169-1 9.3.3 and IEC 60068-2-64
Shock	IEC 61169-1 9.3.14
Degree of protection (mated pair) RoHS	IEC 60529, IP68 1h / 25m compliant
Tooling	N/A
Suitable cables	
	N/A
Weight	
Standard	47.3 g/pc

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date		Rev.	Engineering change number	Name	Date
M. Wimmer	11.09.2014	F_Fraunhofer	01.03.17		a00	17-s078	C_Schmidinger	01.03.17
Rosenberger Hochfrequenztechnik GmbH & Co. KG						Tel. : +49 8684 18-0 Email : <u>info@rosenberger.de</u>		
P.O.Box 1260 D-84526 Tittmoning Germany www.rosenberger.de								