



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832


Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Shiftout Module (SKU:DFR0072)



Contents

- [1 Introduction](#)
- [2 Pin out](#)
 - [2.1 Connection Details](#)
- [3 Code](#)

Introduction


At sometime or another you may run out of pins on your Arduino board and need to extend it with shift registers. With this shift out module which is based on 74HC595. The datasheet refers to the 74HC595 as an "8-bit serial-in, serial or parallel-out shift register with output latches; 3-state." In other words, you can use it to control 8 outputs at a time while only taking up a few pins on your microcontroller. You can link multiple registers together to extend your output even more. It can also be applied to 51, AVR, PIC and other microcontroller.

Note:This module can be multiplied linked, but too much modules linked may affect the working efficiency. Twenty may be better

Pin out

Output

1:D3(clockPin)
2:VCC
3:D8(latch Pin)
4:
5:D9(dataout)
6:GND



Input

1:D3(clockPin)
2:VCC
3:D8(latch Pin)
4:
5:D9(dataPin)
6:GND

Shiftout Module

Connection Details

- **Input:**
 - D3 connect to Arduino Digital 3
 - D8 connect to Arduino Digital 8
 - D9 connect to Arduino Digital 9
 - VCC connect to Arduino 5V
 - GND connect to Arduino GND
- **Output:**
 - D3 connect to the modules' input D3
 - D8 connect to the modules' input D8
 - D9 connect to the modules' input D9
 - VCC connect to the modules' VCC
 - GND connect to the modules' GND

Code

```
//Pin connected to latch pin (ST_CP) of 74HC595
const int latchPin = 8;
//Pin connected to clock pin (SH_CP) of 74HC595
const int clockPin = 3;
/////Pin connected to Data in (DS) of 74HC595
const int dataPin = 9;
byte Tab[]={0xc0,0xf9,0xa4,0xb0,0x99,0x92,0x82,0xf8,0x80,0x90,0xff};
void setup() {
    //set pins to output because they are addressed in the main loop
    pinMode(latchPin, OUTPUT);
```

```
pinMode(dataPin, OUTPUT);
  pinMode(clockPin, OUTPUT);
  Serial.begin(9600);
  Serial.println("reset");
}
void loop() {
  if (Serial.available() > 0) {
    // ASCII '0' through '9' characters are
    // represented by the values 48 through 57.
    // so if the user types a number from 0 through 9 in ASCII,
    // you can subtract 48 to get the actual value:
    int bitToSet = Serial.read() - 48;
    // write to the shift register with the correct bit set high:
    digitalWrite(latchPin, LOW);
    // shift the bits out:
    shiftOut(dataPin, clockPin, MSBFIRST, Tab[bitToSet]);
    // turn on the output so the LEDs can light up:
    digitalWrite(latchPin, HIGH);
  }
}
```