



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Shift out LED kit (SKU:DFR0089)

Contents

- [1 Introduction](#)
- [2 Specification](#)
- [3 Pin Usage](#)
- [4 Sample Code](#)

Introduction



This shiftout LED Kit includes a very simple and small LED display module. It makes it possible for you to directly connect many 7-segment led modules in a chain. So you could diy a simple timer or a clock display , and many other devices that require the use of 7 segment LEDs.

Specification

- supply power:5V
- Interface: SPI
- Common Anode
- Digital Bits: 1
- number of connecting:over 16
- Directly connected with the interface shield
- Compatible with the SPI LED Module 8 Digital (Arduino Compatible)
- size:41x30x25mm

Pin Usage

Shiftout register:Digital pins 3, 8, and 9

Sample Code

```
//Pin connected to latch pin (ST_CP) of 74HC595
const int latchPin = 8;
//Pin connected to clock pin (SH_CP) of 74HC595
const int clockPin = 3;
////Pin connected to Data in (DS) of 74HC595
const int dataPin = 9;
byte Tab[]={
    0xc0,0xf9,0xa4,0xb0,0x99,0x92,0x82,0xf8,0x80,0x90,0xff};
void setup() {
    //set pins to output because they are addressed in the main loop
    pinMode(latchPin, OUTPUT);
    pinMode(dataPin, OUTPUT);
    pinMode(clockPin, OUTPUT);
    Serial.begin(9600);
    Serial.println("reset");
    for(int i = 0;i < 10; i++){
        digitalWrite(latchPin, LOW);
        shiftOut(dataPin, clockPin, MSBFIRST, Tab[i]);
        digitalWrite(latchPin, HIGH);
        delay(500);
    }
}
void loop() {
    if (Serial.available() > 0) {
        // ASCII '0' through '9' characters are
        // represented by the values 48 through 57.
        // so if the user types a number from 0 through 9 in ASCII,
        // you can subtract 48 to get the actual value:
        int bitToSet = Serial.read() - 48;
        // write to the shift register with the correct bit set high:
        digitalWrite(latchPin, LOW);
        // shift the bits out:
        shiftOut(dataPin, clockPin, MSBFIRST, Tab[bitToSet]);
    }
}
```

```
// turn on the output so the LEDs can light up:  
digitalWrite(latchPin, HIGH);  
}  
}
```