

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







100mA / 50V Digital transistors (with built-in resistors)

DTC143EM / DTC143EE / DTC143EUA / DTC143EKA / DTC143ESA

Applications

Inverter, Interface, Driver


Features

- 1) Built-in bias resistors enable the configuration of an inverter circuit without connecting external input resistors (see equivalent circuit).
- 2) The bias resistors consist of thin-film resistors with complete isolation to allow negative biasing of the input. They also have the advantage of almost completely eliminating parasitic effects.
- 3) Only the on/off conditions need to be set for operation, making the device design easy.

Structure

NPN epitaxial planar silicon transistor (Resistor built-in type)


●External dimensions (Unit:mm)



Packaging specifications

	Package	VMT3	EMT3	UMT3	SMT3	SPT
	Packaging type	Taping	Taping	Taping	Taping	Taping
Part No.	Code	T2L	TL	T106	T146	TP
	Basic ordering unit (pieces)	8000	3000	3000 3000		5000
DTC143EM		0				_
DTC143EE		-	0	-	-	-
DTC143EUA		-	-	0		-
DTC143EKA	4	-	_	_	0	_
DTC143ESA	4	-	_	-	-	0

●Equivalent circuit



 $R_1=R_2=4.7k\Omega$

● Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits					
rarameter		DTC143EM	DTC143EE	DTC143EUA	DTC143EKA	DTC143ESA	Unit
Supply voltage	Vcc	50					V
Input voltage	VIN	−10 to +30					V
Output current	lo	100					mA
Output current	IC(Max.)	100					
Power dissipation	Po	150		200		300	mW
Junction temperature	Tj	150					
Storage temperature Tstg -55 to +150							°C

●Electrical characteristics (Ta=25°C)

		•				
Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
lancit valtana	VI(off)	-	-	0.5	V	Vcc=5V, Io=100μA
Input voltage	V _{I(on)}	3	-	-	\ \	Vo=0.3V, Io=20mA
Output voltage	V _{O(on)}	-	0.1	0.3	٧	lo/l=10mA/0.5mA
Input current	lı	-	-	1.8	mA	Vi=5V
Output current	IO(off)	-	-	0.5	μΑ	Vcc=50V, Vi=0V
DC current gain	Gı	30	-	-	-	Vo=5V, Io=10mA
Input resistance	R ₁	3.29	4.7	6.11	kΩ	-
Resistance ratio	R2/R1	0.8	1	1.2	-	-
Transition frequency	f⊤ *	-	250	_	MHz	Vce=10V, Ie= -5mA, f=100MHz

^{*} Characteristics of built-in transistor

Electrical characteristic curves




Fig.1 Input voltage vs. output current (ON characteristics)




Fig.2 Output current vs. input voltage (OFF characteristics)




Fig.3 DC current gain vs. output current




Fig.4 Output voltage vs. output current

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any
 means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the
 product described in this document are for reference only. Upon actual use, therefore, please request
 that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or
 otherwise dispose of the same, no express or implied right or license to practice or commercially
 exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.

