imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Is Now Part of



ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at <u>www.onsemi.com</u>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor dates sheds, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor dates sheds and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use on similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor and its officers, employees, subsidiaries, affliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out or i, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconduc



January 2015

PowerTrench[®] Power Stage Asymmetric Dual N-Channel MOSFET

Features

Q1: N-Channel

- Max $r_{DS(on)}$ = 8 m Ω at V_{GS} = 10 V, I_D = 13 A
- Max $r_{DS(on)}$ = 11 m Ω at V_{GS} = 4.5 V, I_D = 11 A

Q2: N-Channel


- Max $r_{DS(on)} = 2.8 \text{ m}\Omega$ at $V_{GS} = 10 \text{ V}$, $I_D = 23 \text{ A}$
- Max $r_{DS(on)}$ = 3.5 m Ω at V_{GS} = 4.5 V, I_D = 21 A
- Low inductance packaging shortens rise/fall times, resulting in lower switching losses
- MOSFET integration enables optimum layout for lower circuit inductance and reduced switch node ringing
- RoHS Compliant

General Description

This device includes two specialized N-Channel MOSFETs in a dual PQFN package. The switch node has been internally connected to enable easy placement and routing of synchronous buck converters. The control MOSFET (Q1) and synchronous SyncFETTM (Q2) have been designed to provide optimal power efficiency.

Applications

- Computing
- Communications
- General Purpose Point of Load
- Notebook VCORE



MOSFET Maximum Ratings T_A = 25 °C unless otherwise noted

Symbol	Parameter		Q1	Q2	Units	
V _{DS}	Drain to Source Voltage		30	30	V	
V _{DSt}	Drain to Source Transient Voltage (tTransient < 100 ns)		33	33	V	
V _{GS}	Gate to Source Voltage	(Note 3)	±20	±20	V	
	Drain Current -Continuous (Package limited)	T _C = 25 °C	30	40		
	-Continuous (Silicon limited)	T _C = 25 °C	60	130	A	
D	-Continuous	T _A = 25 °C	13 ^{1a}	23 ^{1b}		
	-Pulsed		40	100		
E _{AS}	Single Pulse Avalanche Energy		40 ⁴	60 ⁵	mJ	
D	Power Dissipation for Single Operation	T _A = 25 °C	2.2 ^{1a}	2.5 ^{1b}	w	
P _D	Power Dissipation for Single Operation	T _A = 25 °C	1.0 ^{1c}	1.0 ^{1d}	vv	
T _J , T _{STG}	Operating and Storage Junction Temperature Range		-55 to	+150	°C	

Thermal Characteristics

R_{\thetaJA}	Thermal Resistance, Junction to Ambient	57 ^{1a}	50 ^{1b}	
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient	125 ^{1c}	120 ^{1d}	°C/W
$R_{\theta JC}$	Thermal Resistance, Junction to Case	3.5	2	

Package Marking and Ordering Information

Device Marking	Device	Package	Reel Size	Tape Width	Quantity
22CA N7CC	FDMS3604S	Power 56	13 "	12 mm	3000 units

FDMS3604S
PowerTrench [®]
Power Stage

Symbol	Parameter	Test Conditions	Туре	Min	Тур	Max	Units
Off Chara	cteristics						
BV _{DSS}	Drain to Source Breakdown Voltage	$I_D = 250 \ \mu A, \ V_{GS} = 0 \ V$ $I_D = 1 \ m A, \ V_{GS} = 0 \ V$	Q1 Q2	30 30			V
$\frac{\Delta BV_{DSS}}{\Delta T_J}$	Breakdown Voltage Temperature Coefficient	$I_D = 250 \ \mu$ A, referenced to 25 °C $I_D = 10 \ m$ A, referenced to 25 °C	Q1 Q2		15 12		mV/°C
I _{DSS}	Zero Gate Voltage Drain Current	$V_{DS} = 24 \text{ V}, V_{GS} = 0 \text{ V}$	Q1 Q2			1 500	μA μA
I _{GSS}	Gate to Source Leakage Current, Forwad	V _{GS} = 20 V, V _{DS} = 0 V				100 100	nA nA
On Chara	cteristics						
V _{GS(th)}	Gate to Source Threshold Voltage	$\label{eq:VGS} \begin{array}{l} V_{GS} = V_{DS}, \ I_D = 250 \ \mu A \\ V_{GS} = V_{DS}, \ I_D = 1 \ m A \end{array}$	Q1 Q2	1.1 1.1	2 1.8	2.7 3	V
$\frac{\Delta V_{GS(th)}}{\Delta T_J}$	Gate to Source Threshold Voltage Temperature Coefficient	$I_D = 250 \ \mu$ A, referenced to 25 °C $I_D = 10 \ m$ A, referenced to 25 °C	Q1 Q2		-6 -5		mV/°C
DS(on)	Drain to Source On Resistance		Q1		5.8 8.5 7.8	8 11 10.8	mΩ
'DS(on)		$ \begin{array}{l} V_{GS} = 10 \ \text{V}, \ \text{I}_{D} = 23 \ \text{A} \\ V_{GS} = 4.5 \ \text{V}, \ \text{I}_{D} = 21 \ \text{A} \\ V_{GS} = 10 \ \text{V}, \ \text{I}_{D} = 23 \ \text{A} \ , \ \text{T}_{J} = 125 \ ^{\circ}\text{C} \end{array} $	Q2		2.2 3.0 2.6	2.8 3.5 4	
9 _{FS}	Forward Transconductance	$V_{DS} = 5 V$, $I_D = 13 A$ $V_{DS} = 5 V$, $I_D = 23 A$	Q1 Q2		61 130		S
Dynamic	Characteristics						
C _{iss}	Input Capacitance	Q1: V _{DS} = 15 V, V _{GS} = 0 V, f = 1 MHZ	Q1 Q2		1340 3240	1785 4310	pF
C _{oss}	Output Capacitance	Q2:	Q1 Q2		485 1230	645 1635	pF
C _{rss}	Reverse Transfer Capacitance	V _{DS} = 15 V, V _{GS} = 0 V, f = 1 MHZ	Q1 Q2		53 103	80 155	pF
R _g	Gate Resistance		Q1 Q2	0.2 0.2	0.6 0.8	2 3	Ω
Switching	g Characteristics						
t _{d(on)}	Turn-On Delay Time		Q1 Q2		8.2 13	16 23	ns
t _r	Rise Time	Q1: $V_{DD} = 15 \text{ V}, \text{ I}_{D} = 13 \text{ A}, \text{ R}_{GEN} = 6 \Omega$	Q1 Q2		2.5 4.8	10 10	ns
t _{d(off)}	Turn-Off Delay Time	Q2: V _{DD} = 15 V, I _D = 23 A, R _{GEN} = 6 Ω	Q1 Q2		20 31	32 50	ns
t _f	Fall Time		Q1 Q2		2.2 3.4	10 10	ns
Qg	Total Gate Charge	$V_{GS} = 0$ V to 10 V Q1	Q1 Q2		21 47	29 66	nC
Qg	Total Gate Charge	$V_{GS} = 0$ V to 4.5 V $V_{DD} = 15$ V, I _D = 13 A	Q1 Q2		10 22	14 31	nC
Q _{gs}	Gate to Source Gate Charge	Q2 V _{DD} = 15 V,	Q1 Q2		3.9 9		nC
		• DD - 13 V,		1			-

Gate to Drain "Miller" Charge

 Q_{gd}

 $V_{DD} = 15 V,$ $I_{D} = 23 A$

Q1


Q2

3.1

5.5


nC

Symbol	Parameter	Test Conditions		Гуре	Min	Тур	Max	Units			
Drain-Source Diode Characteristics											
V _{SD}	Source to Drain Diode Forward Voltage		,	Q1 Q2		0.8 0.8	1.2 1.2	V			
t _{rr}	Reverse Recovery Time	Q1 I _F = 13 A, di/dt = 100 A/µs		Q1 Q2		25 32	40 51	ns			
Q _{rr}	Reverse Recovery Charge	Q2 Ι _F = 23 A, di/dt = 300 A/μs		Q1 Q2		9 39	18 62	nC			




2: Pulse Test: Pulse Width < 300 µs, Duty cycle < 2.0%.

- 3: As an N-ch device, the negative Vgs rating is for low duty cycle pulse ocurrence only. No continuous rating is implied.
- 4: E_{AS} of 40 mJ is based on starting T_J = 25 °C; N-ch: L = 1 mH, I_{AS} = 9 A, V_{DD} = 27 V, V_{GS} = 10 V. 100% test at L= 0.3 mH, I_{AS} = 14 A.
- 5: E_{AS} of 60 mJ is based on starting T_J = 25 °C; N-ch: L = 1 mH, I_{AS} = 11 A, V_{DD} = 27 V, V_{GS} = 10 V. 100% test at L= 0.3 mH, I_{AS} = 18 A.



FDMS3604S Rev.C5


www.fairchildsemi.com




©2011 Fairchild Semiconductor Corporation FDMS3604S Rev.C5

www.fairchildsemi.com


FDMS3604S PowerTrench[®] Power Stage






FDMS3604S Rev.C5

FDMS3604S PowerTrench[®] Power Stage



FDMS3604S Rev.C5

www.fairchildsemi.com



FDMS3604S PowerTrench[®] Power Stage

Typical Characteristics (continued)

SyncFET[™] Schottky body diode Characteristics

25

Fairchild's SyncFETTM process embeds a Schottky diode in parallel with PowerTrench MOSFET. This diode exhibits similar characteristics to a discrete external Schottky diode in parallel with a MOSFET. Figure 27 shows the reverse recovery characteristic of the FDMS3604S.

20 didt = 300 A/µs 15 CURRENT (A) 10 5 0 -5 0 50 100 150 200 TIME (ns) Figure 27. FDMS3604S SyncFET[™] body diode reverse recovery characteristic

Schottky barrier diodes exhibit significant leakage at high temperature and high reverse voltage. This will increase the power in the device.





Figure 28. SyncFETTM body diode reverse leakage versus drain-source voltage

Application Information

1. Switch Node Ringing Suppression

Fairchild's Power Stage products incorporate a proprietary design* that minimizes the peak overshoot, ringing voltage on the switch node (PHASE) without the need of any external snubbing components in a buck converter. As shown in the figure 29, the Power Stage solution rings significantly less than competitor solutions under the same set of test conditions.








Figure 30. Shows the Power Stage in a buck converter topology

2. Recommended PCB Layout Guidelines

As a PCB designer, it is necessary to address critical issues in layout to minimize losses and optimize the performance of the power train. Power Stage is a high power density solution and all high current flow paths, such as VIN (D1), PHASE (S1/D2) and GND (S2), should be short and wide for better and stable current flow, heat radiation and system performance. A recommended layout procedure is discussed below to maximize the electrical and thermal performance of the part.







Following is a guideline, not a requirement which the PCB designer should consider:

1. Input ceramic bypass capacitors C1 and C2 must be placed close to the D1 and S2 pins of Power Stage to help reduce parasitic inductance and High Frequency conduction loss induced by switching operation. C1 and C2 show the bypass capacitors placed close to the part between D1 and S2. Input capacitors should be connected in parallel close to the part. Multiple input caps can be connected depending upon the application.

2. The PHASE copper trace serves two purposes; In addition to being the current path from the Power Stage package to the output inductor (L), it also serves as heat sink for the lower FET in the Power Stage package. The trace should be short and wide enough to present a low resistance path for the high current flow between the Power Stage and the inductor. This is done to minimize conduction losses and limit temperature rise. Please note that the PHASE node is a high voltage and high frequency switching node with high noise potential. Care should be taken to minimize coupling to adjacent traces. The reference layout in figure 31 shows a good balance between the thermal and electrical performance of Power Stage.


3. Output inductor location should be as close as possible to the Power Stage device for lower power loss due to copper trace resistance. A shorter and wider PHASE trace to the inductor reduces the conduction loss. Preferably the Power Stage should be directly in line (as shown in figure 31) with the inductor for space savings and compactness.

4. The PowerTrench[®] Technology MOSFETs used in the Power Stage are effective at minimizing phase node ringing. It allows the part to operate well within the breakdown voltage limits. This eliminates the need to have an external snubber circuit in most cases. If the designer chooses to use an RC snubber, it should be placed close to the part between the PHASE pad and S2 pins to dampen the high-frequency ringing.

5. The driver IC should be placed close to the Power Stage part with the shortest possible paths for the High Side gate and Low Side gates through a wide trace connection. This eliminates the effect of parasitic inductance and resistance between the driver and the MOSFET and turns the devices on and off as efficiently as possible. At higher-frequency operation this impedance can limit the gate current trying to charge the MOSFET input capacitance. This will result in slower rise and fall times and additional switching losses. Power Stage has both the gate pins on the same side of the package which allows for back mounting of the driver IC to the board. This provides a very compact path for the drive signals and improves efficiency of the part.


6. S2 pins should be connected to the GND plane with multiple vias for a low impedance grounding. Poor grounding can create a noise transient offset voltage level between S2 and driver ground. This could lead to faulty operation of the gate driver and MOSFET.


7. Use multiple vias on each copper area to interconnect top, inner and bottom layers to help smooth current flow and heat conduction. Vias should be relatively large, around 8 mils to 10 mils, and of reasonable inductance. Critical high frequency components such as ceramic bypass caps should be located close to the part and on the same side of the PCB. If not feasible, they should be connected from the backside via a network of low inductance vias.




SEE


DETAIL A








SIDE VIEW



(SCALE: 2X)



ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor has against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death ass

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910

Japan Customer Focus Center Phone: 81-3-5817-1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

© Semiconductor Components Industries, LLC