# mail

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



#### 2. Soldering the headers

Before using your click<sup>™</sup> board, make sure to solder 1x8 male headers to both left and right side of the board. Two 1x8 male headers are included with the board in the package.



1



Turn the board upward again. Make sure to align the headers so that they are perpendicular to the board, then solder the pins carefully.



RFid click<sup>™</sup> with its **CR95HF** IC is a RFid module with integrated transceiver for contactless applications. The board contains dedicated internal frame controller and analog front end (AFE) for RF communications. It supports ISO/IEC 14443 type A and B, ISO/IEC 15693 and ISO/IEC 18092 protocols (tags) as well as the detection, reading and writing of NFC forum type 1, 2, 3 and 4 tags.



**RFid click**<sup>™</sup>



bottom side is facing you upwards. Place shorter pins of the header into the appropriate soldering pads.

Turn the board upside down so that



### 3. Plugging the board in

Once you have soldered the headers your board is ready to be placed into desired mikroBUS<sup>™</sup> socket. Make sure to align the cut in the lower-right part of the board with the markings on the silkscreen at the mikroBUS<sup>™</sup> socket. If all of the pins are aligned correctly, push the board all the way into the socket.



#### 1. Introduction



RFid click<sup>™</sup> is an accessory board in mikroBUS<sup>TM</sup> form factor. It's a compact and easy solution for adding RFid to your design. It features CR95HF 13.56 MHz contactless transceiver as well as trace antenna. RFid click<sup>™</sup> communicates with the target board microcontroller via mikroBUS<sup>TH</sup> UART (TX, RX), SPI (MISO, MOSI, SCK, CS) INT, RST, PWM and AN lines. The board is designed to use 3.3V power supply only. LED diode (GREEN) indicates the presence of power supply.

#### 5. RFid click<sup>™</sup> Board Schematic



#### 6. SMD jumpers



Two SMD jumpers are provided on the board. In case you want to use UART interface, it is necessary to solder SMD jumpers in

**B** position. Otherwise if you want to use SPI interface, jumpers should be left in its default position (**A**). In that case interrupt pins (IN and OUT) are usable.

#### 7. Code Examples

Once you have done all the necessary preparations, it's time to get your click<sup>m</sup> board up and running. We have provided the examples for mikroC<sup>m</sup>, mikroBasic<sup>m</sup> and mikroPascal<sup>m</sup> compilers on our **Libstock** website. Just download them and you are ready to start.



#### 8. Support

MikroElektronika offers **Free Tech Support** (www.mikroe.com/esupport) until the end of product lifetime, so if something goes wrong, we are ready and willing to help!



MikroElektronika assumes no responsibility or liability for any errors or inaccuracies that may appear in the present document. Specification and information contained in the present schematic are subject to change at any time without notice. Copyright © 2013 MikroElektronika. All rights reserved.