



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China




Fiber Opt click

From MikroElektronika Documentation

Fiber Opt click is a compact and easy solution for adding fiber-optic communication to your design. It features IF-D91 fiber-optic photodiode, IF-E97 fiber-optic LED diode as well as two operational amplifiers. Provided plastic optic connectors feature an internal micro-lens and a precision-molded PBT housing to ensure efficient optical coupling with plastic fiber cable. Data rates of up to 512 Kbps can be achieved. Fiber Opt click communicates with the target MCU via UART interface or directly through the GPIO pins. UART position is set by default. Board is designed to use either 3.3V or 5V power supply.

Features and usage notes



Schematic also available in PDF (http://cdn-docs.mikroe.com/images/7/70/Fiber_Opt_Click_Sche

The combination of a fiber-optic photodiode and a fiber-optic diode constitutes a system for sending and receiving data. The configuration of components makes Fiber Opt click suitable for both analog and digital data links.

Quoting from the manufacturer's data sheet, "the IF-E97 is a high-optical-output, visible red LED housed in a "connector-less" style plastic fiber optic package. The output spectrum is produced by a GaAlAs die which peaks at 660 nm, one of the optimal transmission windows of PMMA plastic optical fiber. The device package features an internal micro-lens and a precision-molded PBT housing to ensure efficient optical coupling with standard 1000 µm core plastic fiber cable."

The optical response of the corresponding IF-D91 is from 450 to 1100 nm.

You can either transmit data using UART, or, if you switch the position of the onboard UART/GPIO jumper, you can send a PWM signal through the optical cable.

Another onboard jumper is for setting the power supply at either 3.3V or 5V.

Programming

This simple code snippe demonstrates how to set up Fiber Opt click to transmit ADC values.

```

1 void main()
2 {
3     char txt[20];
4     unsigned int adc_value = 0;
5
6     UART1_Init(19200); // Initialize UART module at 19200 bps
7     Delay_ms(100);    // Wait for UART module to stabilize
8
9     // Every 2 seconds transmit the ADC value over Fiber Optic
10    while(1)
11    {
12        adc_value = adc_read();
13        IntToStr( txt, adc_value );
14        UART1_Write_Text( Ltrim( txt ) );
15        Delay_ms( 2000 );
16    }
17 }
18 }

```

A more elaborate example that demonstrates the use of Fiber Opt click with MikroElektronika hardware, written for mikroC, mikroBasic and mikroPascal for PIC, is available on Libstock (<http://libstock.mikroe.com/projects/view/728/fiber-opt-click-example>).

We also recommend the learn.mikroe.com article Going the distance with fiber optics (<https://learn.mikroe.com/going-distance-fiber-optics/>) for those who are looking for a deeper understanding on how this click board works.

Resources

- IF-D91 fiber-optic photodiode Manufacturer's data sheet (<http://i-fiberoptics.com/pdf/ifd91.pdf>)
- MikroElektronika Fiber Opt click on learn.mikroe.com (<https://learn.mikroe.com/going-distance-fiber-optics/>)
- IF-E97 fiber-optic LED diode (<http://i-fiberoptics.com/pdf/ife97.pdf>)

Fiber Opt click



Fiber Opt click

IC/Module	IF-D91 fiber-optic photodiode (http://i-fiberoptics.com/pdf/ifd91.pdf)
	IF-E97 fiber-optic LED diode (http://i-fiberoptics.com/pdf/ife97.pdf)
Interface	RX, TX, INT, PWM
Power supply	3.3V, 5V
Website	www.mikroe.com/click/fiber-opt (http://www.mikroe.com/click/fiber-opt)

- MikroElektronika Fiber Opt click on learn.mikroe.com (<https://learn.mikroe.com/going-distance-fiber-optics/>)

- mikroBUS standard specifications (<http://download.mikroe.com/documents/standards/mikrobus/mikrobus-standard-specification-v200.pdf>)

Retrieved from "http://docs.mikroe.com/index.php?title=Fiber_Opt_click&oldid=271"

- This page was last modified on 11 May 2016, at 20:07.
- Content is available under Creative Commons Attribution unless otherwise noted.