

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









VCO Product Specification

Model: VCO-120TC **Rev:** - **Date:** 7/22/2002

Customer: SIRENZA MICRODEVICES, INC.

Operating Temperature Range: (-55 ° to 100 ° C)

| Parameter | Min | Тур | Max | Units | х | Remark |
|---------------------------------------|-------|-------------|-------|---------|---|--------|
| Frequency Range - | 600 | | 1200 | MHz | Х | |
| uning Voltage: | | | | | | |
| 600 MHz | 0 | 1.5 | | Vdc | Х | |
| 1200 MHz | | 17.2 | 20 | Vdc | Х | |
| uning Sensitivity: | | | | | | |
| 600 MHz | 25.8 | 34.4 | 43 | MHz/V | Х | |
| 750 MHz | 29.6 | 39.4 | 49.3 | MHz/V | Х | |
| 900 MHz | 49.7 | 66.3 | 82.9 | MHz/V | Х | |
| 1050 MHz | 32.1 | 42.8 | 53.4 | MHz/V | Х | |
| 1200 MHz | 14.4 | 19.2 | 24 | MHz/V | Х | |
| Output Power - | 10 | 13 | 16 | dBm | Х | |
| Output Phase Noise: | | | | | | |
| 10 kHz | | -90 | -84 | dBc/Hz | Х | |
| 100 kHz | | -113 | -107 | dBc/Hz | Х | |
| 1000 kHz | | -135 | -129 | dBc/Hz | Х | |
| ower Supply - | 14.75 | 15 | 15.25 | Volts | Х | |
| upply Current - | | 15.5 | 17 | mA | Х | |
| larmonic Suppression: | | | | | | |
| 2nd Harmonic | | -15 | -10 | dBc | Х | |
| 3rd Harmonic | | -12 | -10 | dBc | Х | |
| Spurious (Non-Harmonic) - | | | -80 | dBc | | |
| requency Pushing - 14.75 to 5.25 V | | 0.5 | 1 | MHz p-p | | |
| requency Pulling - 20 dB RL | | 16 | 22 | MHz p-p | | |
| utput Impedance - | | 50 | | Ω | | |
| lodulation: | | | | | | |
| Bandwidth | 10000 | 15000 | | kHz | | |
| Input Impedance | | 0.05 | | kΩ | | |
| | | | | • | | • |

Package Information

| Package Type: | TO-8 (Cir) | Drawing Number: | A8678 |
|---------------|-----------------------------|-------------------|-------|
| Dimensions: | 0.504 x 0.504 x 0.27 inches | Drawing Revision: | Р |

Comments

 \boldsymbol{X} Indicates parameter to be tested 100% in production

Performance tests and ratings for Sirenza Microdevices' products were performed internally by Sirenza and measured using specific computer systems and/or components and reflect the approximate performance of the the products as measured by those tests. Any difference in circuit implementation, test software, or test equipment may affect actual performance. The information provided herein is believed to be reliable at press time and Sirenza Microdevices assumes no responsibility for the use of this information. All such use shall be entirely at the user's own risk. Prices and specifications for Sirenza Microdevices' products are subject to change without notice. Buyers should consult Sirenza Microdevices' standard terms and conditions of sale for Sirenza's limited warranty with regard to its products. These products may be patented or include patented technology. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Sirenza Microdevices does not authorize or warrant any product for use in life-support devices and/or systems.

Page 1 of 1