imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





WIDE BANDWIDTH, HIGH LINEARITY LOW NOISE AMPLIFIER

Package Style: QFN, 16-Pin, 3mmx3mm






Features

- Low Noise and High Intercept Point
- Adjustable Bias for Enhanced IP3
- Single 2.5V to 6.0V Power Supply
- 400 MHz to 3800 MHz Operation
- QFN16, 3mmx3mm Package

Applications

- GSM/EDGE, CDMA, PCS, UMTS LNA/Linear Driver
- WLAN LNA/Linear Driver
- WiMAX LNA/Linear Driver
- 900MHz LNA/Linear Driver
- General Purpose Amplification



Functional Block Diagram

Product Description

The RF3861 is a low noise amplifier with a high output IP3. The amplifier is self-biased from a single voltage supply with 50 Ω input and output ports. The useful frequency range is from 400MHz to 3800MHz. A 1dB noise figure and 36dBm OIP3 performance is achieved with a 5V $V_{DD},$ 90mA. Current can be increased to raise OIP3 while having minimal effect on noise figure. The IC is featured in a standard QFN, 16-pin, 3mmx3mm package.

Ordering Information

RF3861 V RF3861PCK-410 F

Wide Bandwidth, High Linearity Low Noise Amplifier Fully Assembled Evaluation Board with 5 Sample Parts 1.5 GHz to 2.7 GHz

Optimum Technology Matching® Applied

🗌 GaAs HBT	□ SiGe BiCMOS	🗹 GaAs pHEMT	🗌 GaN HEMT
GaAs MESFET	🗌 Si BiCMOS	Si CMOS	RF MEMS
InGaP HBT	SiGe HBT	🗌 Si BJT	

RF MIGRO EVICESS, RFMDS, Optimum Technology MatchingS, Enabling Wireless Connectivity¹⁰, PowerStaff, POLARIS¹⁰⁴ TOTAL RADIO¹⁴ and UltimateBlue¹⁴ are trademarks of RFMD, LLC, BLUETOOTH is a trademark mark the Bundent SIG, bun, LLS 4, and lingsed for use the RFMI and trademarks and resident trademarks are the normal are the normal work of the residence of the RFM.

7628 Thorndike Road, Greensboro, NC 27409-9421. For sales or technical support, contact RFMD at (+1) 336-678-5570 or sales-support@rfmd.com.




rfmd.com

Absolute Maximum Ratings

Parameter	Rating	Unit
Supply Voltage	6V	V _{DC}
Input RF Level	+10	dBm
Current Drain, I _{DD}	150	mA
Operating Ambient Temperature	-40 to +85	°C
Storage Temperature	-40 to +150	°C

Note 1: Max continuous RF IN is +10dBm. The max transient RF IN is +20dBm.



Exceeding any one or a combination of the Absolute Maximum Rating conditions may cause permanent damage to the device. Extended application of Absolute Maximum Rating conditions to the device may reduce device reliability. Specified typical performance or functional operation of the device under Absolute Maximum Rating conditions is not implied.

RoHS status based on EU Directive 2002/95/EC (at time of this document revision).

The information in this publication is believed to be accurate and reliable. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents, or other rights of third parties, resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.


Devementer		Specification		Unit	Condition	
Parameter	Min.	Тур.	Max.	Unit	Condition	
High Band						
Frequency	3.3	3.5	3.8	GHz	V _{DD} =5V	
Current		90	110	mA		
Gain		10		dB	At 3.5GHz	
Noise Figure		1.1		dB	+25°C, V _{DD} =5V, I _{DD} =90mA, 3500MHz unless specified	
OIP3		37.0		dBm		
OP1dB		22.0		dBm		
S11		-12		dB	f ₁ =3500MHz, f ₂ =3501MHz	
S22		-18		dB		
Mid Band						
Frequency	1500		2700	MHz		
Current		90	110	mA	V _{DD} =5V	
Gain	13.5	14.5	16.5	dB	+25°C, V _{DD} =5V, I _{DD} =90mA, 2000MHz unless specified	
Noise Figure		1.0	1.2	dB		
OIP3	33.0	35.5		dBm	f ₁ =2000 MHz, f ₂ =2001 MHz	
OP1dB	21.0	22.5	25.0	dBm		
S11		-10		dB		
S22		-20		dB		
Low Band						
Frequency	700		1100	MHz		
Current		90	110	mA	V _{DD} =5V	
Gain		16		dB	+25°C, V _{DD} =5V, I _{DD} =90mA, 850MHz unless specified	
Noise Figure		1.2		dB		
OIP3		36.0		dBm	f ₁ =850MHz, f ₂ =851MHz	
OP1dB		22.5		dBm		
S11		-14		dB		
S22		-18		dB		
Thermal						
Theta _{JC}		51		°C/W		
Power Supply						
Device Operating Voltage	2.5	5.0	6.0	V		
Operating Current	65	90	110	mA	V _{DD} =5.0V, R2=open	



rfmd.com


Pin	Function	Description	Interface Schematic
1	NC	Not connected.	
2	NC	Not connected.	
3	RF IN	RF input pin. 50 Ω matched. This pin is DC-blocked.	
4	NC	Not connected.	
5	NC	Not connected.	
6	NC	Not connected.	
7	ACG	AC ground. Shunt cap may be added for tuning. Shunt resistor may be added to increase $I_{\text{DD}}/\text{IP3}.$	
8	NC	Not connected.	
9	NC	Not connected.	
10	NC	Not connected.	
11	RF OUT	RF output pin. 50 Ω matched. This pin is DC-blocked.	
12	NC	Not connected.	
13	NC	Not connected.	
14	NC	Not connected.	
15	VD	Bias voltage. 2.5V to 6.0V applied through bias inductor.	
16	NC	Not connected.	
Pkg Base	GND	Ground connection.	

Package Drawing





Application Schematic 400 MHz to 1300 MHz




FREQ	VCC	NF	GAIN	OIP3	OP1dB
MHz	Volts	dB	dB	dBm	dBm
400	5	1.7	15.23	35.45	21.27
600	5	1.4	15.81	37.33	21.84
800	5	1.2	16.49	36.56	22.05
1000	5	1.1	16.7	36.22	22.02
1300	5	1.1	15.28	36.88	22.19

Note: This schematic is equivalent to standard 700 MHz to 1100 MHz evaluation board. Specification in above table shows tested performance over extended frequency range. See Theory of Operation section for details.



Application Schematic 800 MHz to 2200 MHz




FREQ	VCC	NF	GAIN	OIP3	OP1dB
MHz	Volts	dB	dB	dBm	dBm
800	5	1.3	16	36	22
2200	5	0.9	13.9	36	22





Evaluation Board Schematic 700 MHz to 3800 MHz



Components	700-1100 MHz	1.5-2.7 GHz	3.3-3.8 GHz
C1 (pF)	10	10	10
C3 (pF)	100	100	100
C4 (pF)	10	DNP	DNP
L1 (nH)	39	3.9	2.2
L2 (nH)	18	4.7	4.7
R1 (ohm)	0	0	0
R2 (ohm)	DNP	DNP	DNP
L3 (nH)	DNP	DNP	DNP

R2 is DNP for standard 90 mA current draw. If R2 is added, the I_{DD} will increase. A 20 Ω R2 will raise the current to achieve higher linearity.






-40

3000.0


- 25 **a** 85

3000.0



5V Gain versus Temperature

5V Gain versus Temperature



0.8

0.6

0.4

3.2

3.3

3.4

3.5

Frequency (GHz)

3.6

3.7

7628 Thorndike Road, Greensboro, NC 27409-9421 · For sales or technical support, contact RFMD at (+1) 336-678-5570 or sales-support@rfmd.com.


3.8


3.9


RFMD IN

5V OIP3 versus Temperature


5V P1dB versus Temperature







RF3861 lcc vs R2 Vdd = 5.0 V R2 = 20 ohm for optimal OIP3





Theory of Operation

Low noise figure/high IP3 make RF3861 ideal for use as both receive LNA and transmit driver for cellular/DCS/PCS/UMTS and WiMax platforms, in addition to many other general purpose applications. Standard evaluation boards cover 700MHz to 1100MHz, 1500MHz to 2700MHz, and 3300MHz to 3800MHz. Viewing the data sheet evaluation board schematic, refer to below for purpose/function of external components:

- R1/L3 (0Ω/unpopulated on standard evaluation boards): These unused components were placed for convenience and flexibility when needed to optimize matching for an out of band application.
- L2/C3/C4: Placed to optimize input match, and enhance out of band low frequency stability.
- R2: Optionally placed to increase bias current and IP3. It has been found that 20Ω value is best case (see graph section of data sheet).
- L1/C1: Influence output return loss.

RF3861 has internal DC blocking capacitors at RFin/RFout. In addition, it has been shown impedance seen looking out at pins 7/15 influence response. As a result, two port s-parameters become non-applicable. In the event matching is desired for frequency bands outside of those provided with standard evaluation boards, the following approach can be used:

- Start with matching seen for standard evaluation board closest to desired band of operation.
- Optimize values at L2/C4/L1 to obtain response/performance.

The application schematic section of data sheet shows matching arrived at using above procedure, for 400 MHz to 1300 MHz and 800 MHz to 2200 MHz. These schematics, along with standard evaluation boards, cover 82% of the useable bandwidth from 400 MHz to 3800 MHz.

One interesting note concerning these application schematics, the 400MHz to 1300MHz example shows same component values as seen with 700MHz to 1100MHz evaluation board. So, it is, in actuality, the same board. The specification chart next to the schematic simply extends the frequency band by 500MHz. Input and output return losses are better than 10dB over the entire 900MHz bandwidth.

