imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





High Efficiency 4-Channel HB LED Driver with I²C Interface and Phase-Shifted PWM Dimming

The SC5014 is a 4-channel, highly integrated, high-effi-

ciency step-up (boost) HB LED driver designed to reduce

the thickness of mid-size LCD displays. It features a wide

input voltage range (4.5V to 27V), phase-shifted PWM

dimming, analog dimming, a flexible output configura-

tion, an I²C interface, and numerous protection features.

The SC5014 exhibits 2% to 4% higher efficiency when

using the same size inductors as existing LED drivers. But,

unlike existing devices, it can also operate with inductors

that are up to 10x smaller without sacrificing efficiency.

This part can also use very low-profile inductors (as small

as 2.2µH, 1mm height), which allows LED drivers to be

built directly into the LCD panel to enable ultra-thin

The boost controller, with programmable switching fre-

quency from 200kHz to 2.2MHz, maximizes efficiency by

dynamically minimizing the output voltage while main-

taining LED string current accuracy. It provides excellent

line and load response with no external compensation

components. An external resistor adjusts the current from

20-120mA per string. It also features PWM dimming reso-

lution of 9 or 10-bits (user selectable) over a dimming freguency from 100Hz to 20kHz, synchronized to the boost

oscillator. String-by-string phase shifting reduces the

demand on the input/output capacitance, decreases EMI,

and improves dimming linearity.

Description

displays.

POWER MANAGEMENT

Features

- Input Voltage 4.5V to 27V
- Output Voltage Up to 50V
- Step-up (Boost) Controller
 - Ultra-Fast Transient Response (<100µs)
 - Programmable Switching Frequency
- Linear Current Sinks
 - 4 Strings, up to 120mA/String
 - Current Matching ±1%
 - Current Accuracy ±2%
- PWM Dimming
 - String-by-String Phase Shifting
 - Input Dimming Frequency 100Hz-30kHz
 - User Selectable 9 or 10-Bits Dimming Resolution
- 5-Bits Analog Dimming
- I²C Interface
 - Fault Status Open/Short LED, UVLO, OTP
 - Device Control: PLL Setting
- Protection Features
 - Open/Shorted LED(s) and adjustable OVP
 - Over-Temperature and UVLO Shutdown Protection
- 4mm X 4mm 20-pin QFN Package

Applications

- Ultrabooks[™], All-in-One PCs, Monitors, Automotive-Display Backlighting
- Backlighting for Mid-Size Displays

Typical Application Circuit

