



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China


Standard Rectifier Module

3~ Rectifier
$V_{RRM} = 1400 \text{ V}$
$I_{DAV} = 27 \text{ A}$
$I_{FSM} = 550 \text{ A}$


3~ Rectifier Bridge

Part number

VUO36-14NO8



 E72873



Features / Advantages:

- Planar passivated chips
- Very low leakage current
- Very low forward voltage drop
- Improved thermal behaviour

Applications:

- Diode for main rectification
- For three phase bridge configurations
- Supplies for DC power equipment
- Input rectifiers for PWM inverter
- Battery DC power supplies
- Field supply for DC motors


Package: FO-B

- Industry standard outline
- RoHS compliant
- 1/4" fast-on terminals
- Easy to mount with one screw

Rectifier

Symbol	Definition	Conditions	Ratings			
			min.	typ.	max.	
V_{RSM}	max. non-repetitive reverse blocking voltage	$T_{VJ} = 25^\circ C$			1500	V
V_{RRM}	max. repetitive reverse blocking voltage	$T_{VJ} = 25^\circ C$			1400	V
I_R	reverse current	$V_R = 1400 V$ $V_R = 1400 V$	$T_{VJ} = 25^\circ C$ $T_{VJ} = 150^\circ C$		40 1.5	μA mA
V_F	forward voltage drop	$I_F = 15 A$ $I_F = 45 A$ $I_F = 15 A$ $I_F = 45 A$	$T_{VJ} = 25^\circ C$ $T_{VJ} = 125^\circ C$		1.04 1.23 0.93 1.18	V V
I_{DAV}	bridge output current	$T_C = 85^\circ C$ rectangular $d = \frac{1}{3}$	$T_{VJ} = 150^\circ C$		27	A
V_{F0} r_F	threshold voltage slope resistance } for power loss calculation only		$T_{VJ} = 150^\circ C$		0.76 9.1	V $m\Omega$
R_{thJC}	thermal resistance junction to case				7	K/W
R_{thCH}	thermal resistance case to heatsink				1	K/W
P_{tot}	total power dissipation		$T_C = 25^\circ C$		17	W
I_{FSM}	max. forward surge current	$t = 10 ms; (50 Hz)$, sine $t = 8,3 ms; (60 Hz)$, sine	$T_{VJ} = 45^\circ C$ $V_R = 0 V$		550 595	A
		$t = 10 ms; (50 Hz)$, sine $t = 8,3 ms; (60 Hz)$, sine	$T_{VJ} = 150^\circ C$ $V_R = 0 V$		470 505	A
I^2t	value for fusing	$t = 10 ms; (50 Hz)$, sine $t = 8,3 ms; (60 Hz)$, sine	$T_{VJ} = 45^\circ C$ $V_R = 0 V$		1.52 1.48	kA ² s
		$t = 10 ms; (50 Hz)$, sine $t = 8,3 ms; (60 Hz)$, sine	$T_{VJ} = 150^\circ C$ $V_R = 0 V$		1.11 1.06	kA ² s
C_J	junction capacitance	$V_R = 400 V; f = 1 MHz$	$T_{VJ} = 25^\circ C$		18	pF



Package FO-B			Ratings		
Symbol	Definition	Conditions	min.	typ.	max.
I_{RMS}	RMS current	per terminal			100 A
T_{stg}	storage temperature		-40		125 °C
T_{vJ}	virtual junction temperature		-40		150 °C
Weight				20	g
M_D	mounting torque		1.8		2.2 Nm
$d_{Spp/App}$	creepage distance on surface / striking distance through air		terminal to terminal	9.0	7.0 mm
$d_{Spb/Apb}$			terminal to backside	10.0	10.0 mm
V_{ISOL}	isolation voltage	t = 1 second t = 1 minute 50/60 Hz, RMS; $I_{ISOL} \leq 1$ mA	3000		V
			2500		V



Ordering	Part Number	Marking on Product	Delivery Mode	Quantity	Code No.
Standard	VUO36-14NO8	VUO36-14NO8	Box	50	465151

Equivalent Circuits for Simulation		* on die level	$T_{vJ} = 150$ °C
	Rectifier		
$V_{0\max}$	threshold voltage	0.76 V	
$R_{0\max}$	slope resistance *	7.9 mΩ	

Outlines FO-B



Rectifier




Fig. 1 Forward current vs. voltage drop per diode




Fig. 2 Surge overload current vs. time per diode



Fig. 3 I^2t vs. time per diode

Fig. 4 Power dissipation vs. forward current and ambient temperature per diode




Fig. 5 Max. forward current vs. case temperature per diode




Fig. 6 Transient thermal impedance junction to case vs. time per diode

Constants for Z_{thJC} calculation:

i	R_{th} (K/W)	t_i (s)
1	0.040	0.005
2	0.150	0.030
3	1.710	0.400
4	5.100	2.300