



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# XA-SK-AUDIO Slice Card Hardware Guide

---

REV A

Publication Date: 2012/10/23  
XMOS © 2012, All Rights Reserved.



## Table of Contents

<b>1</b>	<b>Slice Card Overview</b>	<b>3</b>
1.1	Pack Contents . . . . .	3
1.2	4 Channel Audio . . . . .	3
1.3	MIDI . . . . .	3
1.4	SPDIF Transmit . . . . .	3
<b>2</b>	<b>XA-SK-AUDIO Functional Pins</b>	<b>4</b>

# 1 Slice Card Overview

---

## IN THIS CHAPTER

- ▶ Pack Contents
  - ▶ 4 Channel Audio
  - ▶ MIDI
  - ▶ SPDIF Transmit
- 

### 1.1 Pack Contents

- ▶ One XA-SK-AUDIO Slice Card

### 1.2 4 Channel Audio

Four input and four output channels are provided on the Slice Card via an I2S interface to two CS4270 stereo audio codecs with a shared 2-wire bus for configuration. The xSOFTip I2S driver component drives all 4 channels in both directions at sample rates up to 192 KHz and takes care of codec configuration. Audio clock generation is provided via a CS2100-CP programmable PLL.

### 1.3 MIDI

MIDI In and MIDI out connectors are provided. A stand alone MIDI xSOFTip component to work with this Slice Card is under development.

### 1.4 SPDIF Transmit

An SPDIF digital audio output is provided on the board. A stand alone SPDIF transmit xSOFTip component to work with this Slice Card is under development.

## 2 XA-SK-AUDIO Functional Pins

This table shows the port mapping for each of the Slice Card Signal IO, and the Slicekit Slot connector pin it is located on.

Function	TRIANGLE	CIRCLE	PIN	Description
BCLK	1A	1A	B2	I2S Bit Clock
DAC_DATA0	1D	1D	B4	I2S DAC DATA Channel 0
MCLK	1E	1E	A3	I2S Master Clock
LRCLK	1H	1H	A4	I2S LR Clock
SPDIF_OUT	1K	1K	B10	SPDIF transmit
UART_RX	1I	1I	B15	I2S ADC DATA Channel 0
I2C_SCL	1L	1L	A15	I2S ADC DATA Channel 1
MIDI_IN	1J	1J	A8	From MIDI Connector
MCLK_FSEL	4E1	4E1	B7	MCLK Function Select
CODEC_RST_N	4E2	4E2	A6	Codec Reset
LED	4E3	4E3	A7	User LED output
SCL	4F0	4F0	B9	I2C clock for codec configuration
SDA	4F1	4F1	B11	I2C data for codec configuration
DAC_DATA1	8D0	1M	B12	I2S DAC DATA Channel 1
PLL_SYNC	1P	1P	B18	PLL
MIDI_OIUT	8D7	NC	A13	To MIDI connector



Copyright © 2012, All Rights Reserved.

Xmos Ltd. is the owner or licensee of this design, code, or Information (collectively, the "Information") and is providing it to you "AS IS" with no warranty of any kind, express or implied and shall have no liability in relation to its use. Xmos Ltd. makes no representation that the Information, or any particular implementation thereof, is or will be free from any claims of infringement and again, shall have no liability in relation to any such claims.

XMOS and the XMOS logo are registered trademarks of Xmos Ltd. in the United Kingdom and other countries, and may not be used without written permission. All other trademarks are property of their respective owners. Where those designations appear in this book, and XMOS was aware of a trademark claim, the designations have been printed with initial capital letters or in all capitals.