

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China








N RECEPTACLES

FOR .040" - .060" DIAMETER PINS (#03 CONTACT) FOR .059" - .063" DIAMETER PINS (#42 CONTACT)

0433/8433

X433-0-15-XX-03-XX-04-0


Press-fit in .106 mounting hole



Basic Part Number	Length A
0433-0	.120
8433-0	.330

0435/0436 043X-0-15-XX-03-XX-10-0

Solder mount in .102 min. mounting hole Also available on 24mm wide carrier tape: 950 parts per 13" reel Order as: 0435-0-57-XX-03-XX-10-0




Basic Part	Dia.	Length	
Number	C	K	
0435-0	.118	.050	
0436-0	.125	.070	

4064


4064-0-18-XX-03-XX-40-0

Surface mount Also available on 16mm wide carrier tape:



P.C.B. PAD






0342

0342-0-15-XX-42-XX-10-0

Hex press-fit in .090±.002 plated through-hole




- 0342 receptacle uses Mill-Max's new #42 Contact. This receptacle will accept the Ø.061 ±.002 power pins of 1/4 brick DC/DC converters.
- #42 contact can be ordered in standard receptacles that use #03 contact; or it can be specified as the spring element inside custom made receptacles.

0434

0434-0-15-XX-03-XX-10-0

Press-fit in .106 mounting hole



Mechanical Data #42 Contact:

Insertion/Extraction Force with a Ø.061 (nominal) pin:

First Cycle		2nd & Subsequent Cycles	
Insertion Force	Extraction Force	Insertion Force	Extraction Force
20N	6N	10N	6N

Compliancy Test (the "spring back" characteristic of the contact to accept Ø .059 small pin after insertion of a Ø.063 large pin):

Initial Cycle w	Initial Cycle with Ø.059 pin		Second Cycle with Ø.063 pin		ith Ø.059 pin
Ins. Force	Ext. Force	Ins. Force	Ext. Force	Ins. Force	Ext. Force
18N	6N	22N	7N	3N	2N

(Insertion/Extraction Forces are in Newtons and measured with polished steel gage pins having elliptical shaped tips).

SPECIFICATIONS:

Shell Material: Brass Alloy 360, 1/2 Hard

Contact Material: Beryllium Copper Alloy 172, HT

Dimensions: Inches

Tolerances On: Lengths: ±.005

Diameters: ±.002

±2° Angles:



BASIC PART #

SPECIFY SHELL FINISH:

- $\textbf{01} \ \ 200 \ \mu '' \ \text{TIN/LEAD OVER NICKEL}$
- ◆ **80** 200 μ" TIN OVER NICKEL (RoHS)
- 15 10 μ" GOLD OVER NICKEL (RoHS)

SPECIFY CONTACT FINISH:

- **01** 200 μ " TIN/LEAD OVER NICKEL
- 80 200 μ" TIN OVER NICKEL (RoHS)
- 27 30 μ" GOLD OVER NICKEL (RoHS)

SELECT CONTACT:

#03 or #42 CONTACT (DATA ON PAGE 259)

