

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China










# **SERIES 04 4PST**

#### **FEATURES**

- Joy Stick Action
- Position Locator On CRT Screens
- · Moves Cursor On Menu Display



# **DIMENSIONS** in inches (and millimeters)



### **SPECIFICATIONS**

## Rating Criteria


Rated: Make and break 250 mA at 115 Vac or 125 mA at 220 Vac resistive load for 500,000 operations Contact Resistance: 25 milliohms maximum on a new switch Insulation Resistance: 1,000 megohms at 100 Vdc Dielectric Strength: 500 Vac RMS minimum Operating Temperature: -40°C to +85°

Actuation Force: 13 oz. +/- 3 oz. Actuation travel: 0.095" +/- .020" Actuation lever stop strength: 20 lbs. min.

### **Materials and Finishes**

Base, Cover and Switch Actuator: Polyester (Black) Terminals: Brass, gold-plated over nickel Shorting Bar: Phosphor bronze, gold-plated over nickel Spring: Tinned music wire Keycap: ABS or equivalent Bat-Handle: ABS

#### **CIRCUITRY**



#### ORDERING INFORMATION

Description	Part No.
Basic Switch Switch with Arrowhead Keycap Switch with Bat-Handle	04A 04A-K01 04A-B01*

<sup>\*</sup>Shipped with bat handle permanently attached.

Available from your local Grayhill Distributor. For prices and discounts, contact a local Sales Office, an authorized local Distributor or Grayhill.