# imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





## Contents

Device	Part number	Quantity	Calibration Option <sup>a</sup>	
Open circuit plug	08S12L-000S3	1	FC	
Open circuit jack	08K12L-000S3	1	FC	
Short circuit plug	08S12S-000S3	1	FC	
Short circuit jack	08K12S-000S3	1	FC	
Calibration load plug	08S150-C10S3	1	FC	
Calibration load jack	08K150-C10S3	1	FC	
Calibration adaptor plug/plug	08S121-S20S3	1	FC	
Calibration adaptor jack/jack	08K121-K20S3	1	FC	
Combi wrench	03W008-000	1	-	
Torque wrench	03W021-000	1	FC	
Gauge jack (including gauge block)	08W00S-000	1	FC	
Gauge plug (including gauge block)	08W00K-000	1	FC	

See "Declaration of calibration options" for explanation. a.

Rosenberger Hochfrequenztechnik GmbH & Co. KG					
P.O.Box 1260	D-84526 Tittmoning	Germany			
www.rosenberger.de					

: +49 8684 18-0 Tel. Fax : +49 8684 18-499 Email : info@rosenberger.de

Page

1/3

## **Technical Data Sheet**

Calibration Kit Full Version

## Rosenberger

## 08CK001-150

### Documentation

**RPC-1.85** 

This kit is delivered with

USB-Stick

Standard Definitions as data files for Vector Network Anaylzer Families PNA (Keysight/Agilent) and ZVA (Rohde&Schwarz). Calibration Certificate as PDF-file.

• Standard Definitions Cards

Printed Standard Definitions that can be used on nearly all Vector Network Analyzers.

- **Kit Info Card** Handling precautions and information for installing Standard Definitions on a Vector Network Analyzer.
- Calibration Certificate

Details see "Declaration of calibration options"

• Operating Manual

### **Electrical specifications**

This specification covers electrical key values for the main calibration standards of the calibration kit. Specific datasheets are available for each component among the part number.

Calibration standard	Frequency	Parameter	Specification	
<b>Opens</b> <sup>b</sup> (plug and jack)	$\begin{array}{rrrr} DC & to & \leq 4 \; GHz \\ > 4 \; GHz & to & \leq 40 \; GHz \\ > 40 \; GHz & to & \leq 70 \; GHz \end{array}$	Error from Nominal Phase	≤ 2.0° ≤ 5.0° ≤ 8.0°	
<b>Shorts<sup>b</sup></b> (plug and jack)	$\begin{array}{rrrr} DC & to & \leq 4 \; GHz \\ > \; 4 \; GHz & to & \leq 40 \; GHz \\ > \; 40 \; GHz & to & \leq 70 \; GHz \end{array}$	Error from Nominal Phase	≤ 2.0° ≤ 5.0° ≤ 8.0°	
Calibration loads (plug and jack)	$\begin{array}{rrrr} DC & to & \leq 4 \; GHz \\ > \; 4 \; GHz & to & \leq 40 \; GHz \\ > \; 40 \; GHz & to & \leq 70 \; GHz \end{array}$	Return Loss	≥ 35 dB ≥ 26 dB ≥ 22 dB	
Calibration adaptors (plug/plug and jack/jack)	$\begin{array}{rrrr} DC & to & \leq 4 \; GHz \\ > \; 4 \; GHz & to & \leq 40 \; GHz \\ > \; 40 \; GHz & to & \leq 70 \; GHz \end{array}$	Return Loss	≥ 28 dB ≥ 20 dB ≥ 17 dB	

b. The specifications for opens and shorts are given as allowed deviation from nominal model as defined in calibration certificate included with your kit.

, Ц

RF\_35/05.10/6.1

Rosenberger Hochfrequenztechnik GmbH & Co. KG					
P.O.Box 1260	D-84526 Tittmoning	Germany			
www.rosenberger.de					

Tel. : +49 8684 18-0 Fax : +49 8684 18-499 Email : <u>info@rosenberger.de</u>

## **Technical Data Sheet**

RPC-1.85 Calibration Kit Full Version

## Rosenberger

## 08CK001-150

#### Declaration of calibration options

#### **Factory Calibration**

Standard delivery for this kit includes a Factory Calibration. All devices marked with "FC" in the Content table above are reported in a Calibration Certificate with their individual calibration results, traceable to national / international standards. Model based definitions of the calibration standards are reported in Agilent/Keysight, Rohde & Schwarz and Anritsu compatible VNA format.

#### **Accredited Calibration**

Not available.

For further, more detailed information see application note AN001 on the Rosenberger homepage.

#### Calibration interval

Recommendation

12 months

## Recommended accessories

- Rosenberger Test Port Adaptor
- Rosenberger VNA Test cable kit and Microwave Cable Assemblies

For further, more detailed information please visit our homepage <u>www.rosenberger.com</u>.

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date		Rev.	Engineering change number	Name	Date
Martin Moder	04.03.15	Herbert Babinger	08.04.15		a00	15-s152	Maik Knoll	08.04.15
Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany					Tel. : +49 8684 18-0 Fax : +49 8684 18-499		Page	
www.rosenberger.de				Email : info@rosenberger.de		3/3		