mail

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



. to Dif	erential P								
		ECL Translator							
5V supply. ntial pair shou f only one outp d both output	out is being used. If s can be left open	 Features Typical propagation delay of 300 ps <100 ps between outputs Max I_{CC} of 30 mA Fairchild MSOP-8 package is a drop-in replacement to ON TSSOP-8 Flow through pinout Meets or exceeds JEDEC specification EIA/JESD78 IC latch-up test Moisture Sensitivity Level 1 ESD Performance: Human Body Model > 2000V Machine Model > 200V 							
:									
ige Code		Package Description							
		ne Integrated Circuit (SOIC), JEDEC MS-012, 0.150" Narrow nall Outline Package (MSOP), JEDEC MO-187, 3.0mm Wide							
	y appending suffix letter "X"	to the ordering code. Logic Diagram							
-	$8 - V_{CC}$ $7 - D_0$ $6 - D_1$ $5 - GND$	$ \begin{array}{c} Q_0 \\ \overline{Q}_0 \\ \overline{Q}_0 \\ \hline D_0 \\ \hline D_1 \\ \hline D_1 \end{array} $							
PECL Dif TTL Inpu Positive S	ferential Outputs								
	if only one output ad both output rature compens Product Code ber Top Mark 3A KLT22 8D KT22 and Reel. Specify b agram Top View ns PECL Dif TTL Input	antial pair should be terminated in if only one output is being used. If ed both outputs can be left open rature compensated. age Product age Code ber Top Mark 3A KLT22 8-Lead Small Outlin 8D KT22 8-Lead Molded Small and Reel. Specify by appending suffix letter "X' agram 0 7 D0 6 D1 5 GND Top View NS Description PECL Differential Outputs TTL Inputs Positive Supply							

100ELT22 5V Dual TTL to Differential PECL Translator

Absolute Maximum Ratings(Note 1)

Supply Voltage (V_{CC}) Input Voltage (V_1) $V_1 \le V_{CC}$	0.0V to +7.0V 0.0V to + 7.0V
DC Output Current (I _{OUT})	
Continuous	50 mA
Surge	100 mA
Storage Temperature (T _{STG})	$-65^{\circ}C$ to $+ 150^{\circ}C$

Recommended Operating Conditions

Power Supply Operating TTL Input Voltage Free Air Operating Temperature (T_A) $V_{CC} = 4.2V \text{ to } 5.5V$ 0.0V to V_{CC} -40°C to +85°C

Note 1: The "Absolute Maximum Ratings" are those values beyond which the safety of the device cannot be guaranteed. The device should not be operated at these limits. The parametric values defined in the Electrical Characteristics tables are not guaranteed at the absolute maximum rating. The "Recommended Operating Conditions" table will define the conditions for actual device operation.

PECL DC Electrical Characteristics V_{CC} = 5.0V; GND = 0.0V (Note 2)

Symbol	Parameter	-40°C			25°C			85°C			Units
		Min	Тур	Max	Min	Тур	Max	Min	Тур	Max	onns
I _{CC}	Power Supply Current			30			30			30	mA
V _{OH}	Output HIGH Voltage (Note 3)	3915	3995	4120	3975	4045	4120	3975	4050	4120	mV
V _{OL}	Output LOW Voltage (Note 3)	3170	3305	3445	3190	3295	3380	3190	3295	3380	mV
Note 2: Output parameters vary 1 to 1 with V _{CC} . V _{CC} can vary +0.5V/-0.8V.											

Note 3: Outputs are terminated through a 50Ω Resistor to V_{CC} – 2.0V.

Note: Devices are designed to meet the DC specifications after thermal equilibrium has been established. Circuit is tested with air flow greater than

Note: Devices are designed to meet the DC specifications after thermal equilibrium has been established. Circuit is tested with air flow greater than 500LFPM maintained.

TTL DC Electrical Characteristics $V_{CC} = 5.0V$; GND = 0.0V (Note 4); $T_A = -40^{\circ}C$ to $+85^{\circ}C$

Symbol	Parameter	Min	Тур	Max	Units	Condition
IIH	Input HIGH Current			20		V _{IN} = 2.7V
				100	μA	$V_{IN} = V_{CC}$
IIL	Input LOW Current			-200	μA	$V_{IN} = 0.5V$
V _{IK}	Clamp Diode Voltage			-1.2	V	$I_{IN} = -18 \text{ mA}$
V _{IH}	Input HIGH Voltage	2.0			V	
VIL	Input LOW Voltage			0.8	V	

Note 4: V_{CC} can vary +0.5V/-0.8V.

AC Electrical Characteristics $V_{CC} = 5.0V$; GND = 0.0V (Note 5)

Symbol	Parameter	−40°C		25°C			85°C			Units	Figure	
		Min	Тур	Max	Min	Тур	Max	Min	Тур	Max	Units	Number
f _{MAX}	Maximum Input Frequency		TBD			TBD			TBD		MHz	
t _{JITTER}	Cycle-to-Cycle Jitter		TBD			TBD			TBD		ps	
t _{PLH} , t _{PHL}	Propagation Delay to Output (Note 6)	100		600	100		600	100		600	ps	Figure 1
t _r , t _f	Output Rise Time/Fall Times (20% to 80%)	200		500	200		500	200		500	ns	Figure 2
t _{skpp}	Part to Part Skew			500			500			500	ps	
t _{skew}	Within Device Skew (Note 7)			100			100			100	ps	

Note 5: V_{CC} can vary +0.5V/-0.8V.

Note 6: Specifications for standard TTL input signal (see Figure 1).

Note 7: Within-device skew is defined as identical transitions on similar paths through a device.





