## imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



## Cross Laser Diode – 5mW 650nm Red



## DESCRIPTION

You have some frickin' sharks at your lair, and you're thinking "it would be really great if I could attach some lasers to them" and then you see these little laser diode modules: what great timing! These encapsulated laser diodes are Class IIIa 5mW, with a 650nm red wavelength. They can be driven from 2.8V to 5.2V so they're great for your embedded electronics project.

This particular module has a lens attached that will turn the dot into a cross. This makes it particularly good for laser-vision guidance, targeting, and more! Simply connect power to the red and black wires and you will be lasing in no time.

The cross has a beam spread of approximately 60° in both directions. So from a distance of 5cm, the cross is 5cm tall and 5cm wide. The cross ends have a sharp cutoff so the shape is very clearly defined.

Please note: this is not a laser pointer. It's a diode with integrated driver. You still need a 3 to 5VDC power supply. These diodes are 5mW output, and have a safety label marked on them. For more information on laser safety and ratings check out the Wikipedia page





Weight: 11.85g Diameter: 10.11mm Length: 32.82mm Wire length: 100mm 650nm wavelength 2.8 - 5.2V DC voltage input 25mA max current draw Operating temperature -10°C to 40°C;