# imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# **Brad M12 LED Machine Lights**



By combining an LED Light, Mounting Bracket, and M12 Cordset in one package, the LED Machine Lights Kit simplifies light maintenance and streamlines machine lighting replacement

### Features and Benefits


#### Complete LED Machine Lighting Solutions

Package includes LED Light, Mounting Brackets, and M12 Cordsets and Connectors. Simplifies ordering by condensing an entire lighting system into one order number

M12 Connector Interface Eliminates costly and complicated hard-wiring. Simplifies maintenance and replacement. Delivers IP67 sealing protection for harsh environments



Brad M12 40mm LED Machine Light Kit



M12 Lighting Assembly Power Options: 5.0W 10.5W 16.0W 21.5W End Brackets Clip Brackets Molex M12 Cordsets 5m Single-Ended: 120065-9520 1m Double-Ended: 120066-8992 M12 Closure cap to seal off unused M12 connector

## Applications

#### Industrial

- Machine Lighting Area Lighting
- Workshops
- Factories
- Plant Floors



Brad M12 70mm LED Machine Light KIT



M12 Lighting Assembly Power Options: 12.0W 24.0W 30.0W 42.0W End Brackets Clip Brackets Molex M12 Cordsets 5m Single-Ended: 120065-9520 1m Double-Ended: 120066-8992

M12 Closure cap to seal off unused M12 connector



Brad M12 LUMA Wide-Area LED Machine Light Kit



Side-Panel M12 Interface Power Options: 25.0W 50.0W Pivoting Arm Mount Mounting Bracket Set Molex M12 Cordsets 5m Single-Ended: 120065-9520

# **Brad M12 LED Machine Lights**

# molex

### **Specifications**

#### **REFERENCE INFORMATION**

Use With: A-Coded M12 Cordset Designed In: mm Sealing Protection: 70mm : IP67 40mm: IP67 LUMA: IP68-1m and IPX9K (DIN 40050-9)

#### ELECTRICAL

Voltage (max.): 70mm : 20 to 28V DC 40mm: 20 to 28V DC LUMA: 22 to 26V DC Output: 70mm: 12, 24, 30, or 42W 40mm: 5, 10.5, 16 or 21.5W LUMA: 25 or 50W LED Life (min).: 60,000 Hours

#### MECHANICAL

Length: 70mm: 370mm, 650mm, 790mm, or 1069mm 40mm: 190, 365, 540 or 715mm LUMA: 420 or 770mm Outer Diameter: 70mm: 70mm 40mm: 40mm Width: LUMA: 170mm Vibration Resistance: From 10 to 55 Hz Amplitude: 0.35mm Shock Resistance (max.): 50g

#### PHYSICAL

Color Temperature: 70mm: 5000K 40mm: 5000K LUMA: 5800K Color Rendering: Ra > 80 Reflector Angle:  $90^{\circ}$ LUMA: Glare-Free Glass Thickness: 4mm Housing: Anodised Aluminum Ambient Temperature (max.): 70mm:  $+40^{\circ}$ C 40mm:  $+50^{\circ}$ C LUMA:  $+50^{\circ}$ C On/Off Switch: None

## **Ordering Information**

#### 40mm LED Machine Light KIT

Order No.	Engineering No.	Output	Length	Accessories	Operating Voltage
<u>130305</u> -0010	M12MXIS40-5W	5.0W	7.5"	End Brackets 5m and 1m Cordsets M12 Closure Cap	24VDC
<u>130305</u> -0020	M12MXIS40-10W	10.5W	14.4"		
<u>130305</u> -0030	M12MXIS40-16W	16.0W	21.3"		
<u>130305</u> -0040	M12MXIS40-21W	21.5W	28.2"		

#### 70mm LED Machine Light KIT

Order No.	Engineering No.	Output	Length	Accessories	Operating Voltage
<u>130305</u> -0110	M12MXIS70-12W	12W	14.6"	End Brackets 5m and 1m Cordsets M12 Closure Cap	24VDC
<u>130305</u> -0120	M12MXIS70-24W	24W	25.6"		
<u>130305</u> -0130	M12MXIS70-30W	30W	31.1"		
<u>130305</u> -0140	M12MXIS70-42W	42W	42.1"		

#### LUMA Wide-Area LED Machine Light KIT

Order No.	Engineering No.	Output	Dimensions	Accessories	Operating Voltage
<u>130305</u> -0210	M12MXISLUMA-25W	25W	420 x 170mm	Mounting Bracket Set 5m Cordset	24VDC
<u>130305</u> -0220	M12MXISLUMA-50W	50W	770 x 170mm		

### www.molex.com/link/m12ledlights.html

Molex is a registered trademark of Molex, LLC in the United States of America and may be registered in other countries; all other trademarks listed herein belong to their respective owners.