



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



## Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



# Test Equipment

## 0-25V/5A, Digital Output AC/DC Power Supply

The 1315D is specifically designed for educational usage, prototyping, and covers a wide range of circuit testing applications.

### 1315D AC/DC Power



Global Specialties Model 1315D is a rugged general purpose AC/DC power supply with variable outputs of 0-25 volts @ 5 amps with digital LED (Green) displays for motoring both voltage and current outputs. This unique power supply is a low-cost, space-saving solution for applications requiring both AC/DC voltages. The 1315D is specifically designed for educational usage, prototyping, and covers a wide range of circuit testing applications.

#### Features:

- 0-25 @ 5AMP Variable
- AC or DC Selection Switch
- Separate Circuit Breakers for AC & DC
- Output Voltage 3 Digit LED Display (Green)
- Output Current 3 Digit LED Display (Green)
- Power Switch on/off switch with LED indicator
- Separate Power Switch
- Heavy Duty Transformer
- Rugged Metal Case
- 115V @ 60Hz or 230VAC, 50Hz, Single Phase
- 3-Year Warranty

This simple AC/DC power source can be used to demonstrate the concept of alternating and non-alternating voltages. It can also be used for simple experiments using lamps, resistances, etc. The unit has been provided with voltmeter and ammeter for AC/DC voltage and current readings.



1315D

# Test Equipment

0-25V/5A, Digital Output AC/DC Power Supply

AC/DC  
Power  
Supply

Specifications	
<b>AC Voltage:</b>	
Output Voltage, No Load	0V to 30V (nom)
Output Voltage, Full Load	0V to 25V $\pm$ 2V
Output Current	5A max
Output Protection	5A Circuit Breaker
<b>DC Voltage:</b>	
No Load	0V to 40V
Full Load	0V to 25V $\pm$ 2V
Output Voltage	0V to 25V (nom)
Output Current	5A Max
Output Protection	6A Circuit Breaker
DPM V/A Selection	2Pole/2Way Push Switch
Output Voltage	3 Digit LED Display (Green)
Output Current	3 Digit LED Display (Green)
<b>General:</b>	
Input Power	115V/230VAC, 60Hz, single phase
Input Fuse	115/230V: 2A/3A, 250V Slow Blow
Dimensions (W x H x D) Approx.	235mm x 155mm x 295mm
Weight	Approx. 10.0 Kg

Specifications subject to change without notice. Go to [globalspecialties.com](http://globalspecialties.com) for the latest update.



WARRANTY



Innovative Training Solutions

[www.globalspecialties.com](http://www.globalspecialties.com)