

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









FKS Resistor ATO® Style

RoHS



Specifications

Insulating body: Out of thermoplastic (UL 94-V0, heat-resistant)

Connections: Blade contacts

Copper alloy, gal. Sn Edge-protected


Resistance: Metal coating resistance 1%, 0.4 W

Packaging:

Series	Pack
Serien	Size
163.7010.xxx2	1000

ATO-Style FKS-Coding Plug with 0.4 W metal coating resistor 1%. Available resistance 110 Ohms to 9,100 Ohms.

ATO-Style Kodierstecker mit metallisiertem Widerstand (0,4 W, 1%). Erhältlich mit Widerstandswerten von 110 Ohm bis 9.100 Ohm.



Part Number Artikel-Nr.	Resistance Widerstand	Housing Color Kennfarbe	Identification Letter Kennbuchstabe
163.7010.0102	110 Ω		А
163.7010.0152	240 Ω		В
163.7010.0202	430 Ω		С
163.7010.0252	680 Ω		D
163.7010.0302	1,000 Ω		Е
163.7010.0352	1,500 Ω		F
163.7010.0402	2,400 Ω		G
163.7010.0452	3,900 Ω		Н
163.7010.0502	9,100 Ω		1

Corresponding fuse holders see Section "Fuse Holders."