

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China














DESCRIPTION

The 1800 Series of inductors are particularly suited to use with a wide variety of switching regulators. Offering high current handling with a low mounting height, the devices are ideal where space is at a premium.

SELECTION	GUIDE					
Order Code	Inductance (1kHz, 0.1Vac)	DC Current ¹	DC Resistance	Q @ f kHz		SRF
	±10%	Max.	Max.			Nom.
	μН	Α	mΩ	Q	f	MHz
18472C	4.7	5.35	9.0	112	1000	36.4
18682C	6.8	4.15	12.0	78	500	23.6
18103C	10.0	3.45	15.0	64	500	19.0
18153C	15.0	3.00	18.0	55	500	15.9
18223C	22.0	2.42	25.0	59	500	11.8
18333C	33.0	2.00	40.0	48	500	11.5
18473C	47.0	1.65	55.0	55	500	8.5
18683C	68.0	1.35	70.0	31	100	6.6
18104C	100.0	1.20	100.0	40	100	7.4
18154C	150.0	1.10	165.0	47	100	4.4
18224C	220.0	0.90	230.0	46	100	3.5
18254C	250.0	0.80	255.0	50	100	3.7
18334C	330.0	0.73	335.0	58	100	3.0
18474C	470.0	0.60	465.0	56	100	2.2
18684C	680.0	0.53	630.0	55	100	2.0
18105C	1.0mH	0.44	1.0Ω	94	50	1.6
18155C	1.5mH	0.33	1.5Ω	107	50	1.3
18225C	2.2mH	0.30	2.2Ω	108	50	1.1
18335C	3.3mH	0.22	3.5Ω	143	50	0.8
18475C	4.7mH	0.20	4.6Ω	128	40	0.7
18685C	6.8mH	0.15	7.0Ω	144	40	0.6
18106C	10.0mH	0.13	12.0Ω	143	40	0.5

TYPICAL CORE/WIRE CHARACTERISTICS								
Inductance Temperature Coefficient	Resistance Temperature Coefficient	Curie Temperature $(T_{\rm c})$	Saturation Flux (B _{SAT})					
430ppm	4000ppm	190°C	325mT					

ABSOLUTE MAXIMUM RATINGS					
Operating free air temperature range	0°C to 70°C				
Storage temperature range	-55°C to 125°C				

SOLDERING INFORMATION ²					
Peak wave solder temperature	300°C for 10 seconds				
Pin finish	Bright tin				


All specifications typical at T,=25°C

- 1 Maximum DC current occurs when either the inductance falls to 90% of its nominal value or when its temperature rise reaches 30°C, whichever is sooner.
- 2 For further information, please visit www.murata-ps.com/rohs





Axial Lead Inductors



Murata Power Solutions, Inc.
11 Cabot Boulevard, Mansfield, MA 02048-1151 U.S.A. ISO 9001 and 14001 REGISTERED

Murata Power Solutions, Inc. makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The descriptions contained herein do not imply the granting of licenses to make, use, or sell equipment constructed in accordance therewith. Specifications are subject to change without notice.