

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









Features

- Compact size
- Low capacitance
- Performance stability over life
- High insulation resistance
- RoHS compliant*
- **Su**® UL Recognized

Applications

- MDC / PCI modems
- Splitters
- Telecom CPE
- Datacom

2051 Series Gas Discharge Tube Surge Protector

Bourns® 2051 Series micro surface mount, 2-electrode GDT surge protection device is designed to meet board level protection requirements with reduced space requirements. The 2051 Series is ideal for high-speed/high-bandwidth applications with a typical capacitance of 0.6 pF. The 2051 Series product dimensions are 2.7 x 3.2 x 4.5 mm.

Characteristics

Test Methods per ITU-T (CCITT) K.12 and IEEE C62.31

Characteristic		Model No.					
Characteristic	2051-09	2051-15	2051-20	2051-23	2051-30		
DC Sparkover @ 100 V/s	90 V ±30 %	150 V ±30 %	200 V ±25 %	230 V ±25 %	300 V ±25 %		
Impulse Sparkover (1)							
100V/μs	<500 V	<500 V	<500 V	<500 V	<600 V		
1000V/μs	<600 V	<600 V	<650 V	<650 V	<750 V		

Characteristic		Model No.					
Characteristic	2051-35	2051-40	2051-42	2051-47	2051-60		
DC Sparkover @ 100 V/s	350 V ±25 %	400 V ±25 %	420 V ±25 %	470 V ±25 %	600 V ±25 %		
Impulse Sparkover (1)							
100V/μs	<650 V	<750 V	<750 V	<800 V	<950 V		
1000V/μs	<800 V	<900 V	<900 V	<950 V	<1100 V		

⁽¹⁾ Impulse Sparkover voltage is defined as typical values of distribution.

Insulation Resistance (IR)	. 50 / 100 V _{dc}	>1G Ω
Glow Voltage	. 10 mA	.~ 70 V
	. 1 A	
Capacitance	. 1 MHz	.< 1 pF
Impulse Discharge Current	. 2000 A, 8/20 μs	.10 operations
	100 A, 8/20 µs	.300 operations
	10 A, 10/1000 μs	.100 operations
Alternating Discharge Current	. 2 A, 50 Hz, 1 sec	.10 operations
Operating & Storage Temperature		40 to +125 °C
5 , , , ,		

Notes:

- UL Recognized component, UL File E153537.
- · At delivery AQL 0.65 Level II, DIN ISO 2859.
- Bourns recommends reflowing surface mount devices per IPC/JEDEC J-STD-020 rev D.

BOURNS®

Asia-Pacific: Tel: +886-2 2562-4117 • Fax: +886-2 2562-4116

EMEA: Tel: +36 88 520 390 • Fax: +36 88 520 211

The Americas: Tel: +1-951 781-5500 • Fax: +1-951 781-5700

www.bourns.com


The device characteristics and parameters in this data sheet can and do vary in different applications and actual device performance may vary over time. Users should verify actual device performance in their specific applications.

^{*}RoHS Directive 2002/95/EC Jan. 27, 2003 including annex and RoHS Recast 2011/65/EU June 8, 2011. Specifications are subject to change without notice.

2051 Series Gas Discharge Tube Surge Protector

 $\frac{3.2 \pm 0.3}{(0.126 \pm 0.012)}$


BOURNS




Packaging Specifications

 $\frac{4.5 \pm 0.3}{(0.177 \pm 0.012)}$

The Model 2051-xx-SM ships standard reelpack (-RP), 2500 pieces per reel. Reel is 330 mm in diameter and 14 mm wide.







DIMENSIONS:

(INCHES)

Recommended Pad Layout



How to Order



RoHS Compliancy —

LF = RoHS Compliant Product