

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









### **Features**

- Size: 5 mm diameter, 7.2 mm length
- Surface mount design
- Symmetrical breakdown voltage (L-L, L-G)
- Low capacitance and insertion loss
- **91** UL Recognized
- RoHS compliant\*

### **Applications**

- Telecommunications equipment
- Industrial equipment/electronics
- Consumer electronics

## 2052 Series Light Duty 3-Electrode Symmetrical Gas Discharge Tube

#### **Characteristics**

Test Methods per ITU-T K.12 and IEC 61643-311.

Characteristic	Model No.							
	2052-23	2052-25	2052-35	2052-40	2052-42	2052-47	2052-60	2052-80
DC Sparkover ±20 % @ 100 V/s (L-L, L-G)	230 V	250 V	350 V	400 V	420 V	470 V	600 V	800 V
Impulse Sparkover (L-L, L-G) <sup>(1)</sup> 100 V/µs 1000 V/µs	< 600 V < 700 V	< 600 V < 700 V	< 650 V < 750 V	< 700 V < 800 V	< 700 V < 800 V	< 800 V < 900 V	< 900 V < 1000 V	< 1150 V < 1400 V

<sup>(1)</sup> Impulse Sparkover voltage is defined as typical values of distribution.

Insulation Resistance (IR) (2)	100/250 Vdc	>1 GΩ
Glow Voltage	10 mA	~70 V
Arc Voltage	1 A	~10 V
Glow-Arc Transition Current		<1 A
Maximum Capacitance	1 MHz	<2 pF
Maximum Impulse Discharge Current	10,000 A, 8/20 µs	1 operation
	5,000 A, 8/20 μs	10 operations
Nominal Alternating Discharge Current	5 A, 50 Hz, 1 sec	1 operation
	20 A, 9 cycles	1 operation
Impulse Life	200 A, 10/1000 µs	150 operations
DC Holdover Voltage (3)	>135 V	<150 ms
Operating Temperature		-30 to +85 °C
Storage Temperature		-40 to +115 °C

### Notes:

- UL Recognized component, UL File E153537.
- At delivery AQL 0.65 AQL Level II, DIN ISO 2859.
- The rated discharge current is the total current equally divided between each line to ground (ELTG).
- · Bourns recommends reflowing surface mount devices per IPC/JEDEC J-STD-020 rev D.

(2) DC Sparkover Voltage IR Measuring Voltage

145-400 V 100 V 420–800 V 250 V

(3) Network Applied.

### **BOURNS**®

Asia-Pacific: Tel: +886-2 2562-4117 • Fax: +886-2 2562-4116

EMEA: Tel: +36 88 520 390 • Fax: +36 88 520 211

**The Americas:** Tel: +1-951 781-5500 • Fax: +1-951 781-5700

www.bourns.com

Specifications are subject to change without notice.


The device characteristics and parameters in this data sheet can and do vary in different applications and actual device performance may vary over time. Users should verify actual device performance in their specific applications.

<sup>\*</sup>RoHS Directive 2002/95/EC Jan. 27, 2003 including annex and RoHS Recast 2011/65/EU June 8, 2011.


## 2052 Series Light Duty 3-Electrode Symmetrical Gas Discharge Tube

## **BOURNS**


#### **Product Dimensions**



#### **Recommended Pad Layout**





#### **How to Order**



### **Packaging Specifications**

Model 2052-xx-SM-RPLF (Reel Pack) contains 900 pieces per reel, 2,700 pieces per box. The reel is 330 mm in diameter and 18 mm wide.





REV. B 07/15