



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



CABLE-FCN40/.../...M/S7...

System cables for Simatic S7-300, 64-channel I/O boards

INTERFACE

Data sheet
103913_en_00

© PHOENIX CONTACT - 03/2009



1 Description

These system cables are plugged into Simatic S7-300 I/O boards, which are connected via Fujitsu connectors.

Two connection options are available:

CABLE-FCN40/1X50/...M/S7...

- Signal transfer of 32 channels
(two cables are required per board)

CABLE-FCN40/4X14/...M/S7...

- Splitting of 32 channels into 4 x 8 channels
(two cables are required per board)

The following I/O boards can be connected:

- 6ES7 322-1BP00-0AA0
- 6ES7 322-1BP50-0AA0
- 6ES7 321-1BP00-0AA0



Make sure you always use the latest documentation.
It can be downloaded at www.phoenixcontact.net/download.



This data sheet is valid for all products listed on the following page:

2 Ordering data

System cables

Description	Cable length	Type	Order No.	Pcs./Pkt.
Assembled round cable , 40-pos. Fujitsu strip on 50-pos. FLK strip (for connection to 6ES7 322-1BP00-0AA0 and 6ES7 322-1BP50-0AA0 output modules)	0.5 m	CABLE-FCN40/1X50/0,5M/S7-OUT	2321017	1
	1.0 m	CABLE-FCN40/1X50/1,0M/S7-OUT	2321020	1
	2.0 m	CABLE-FCN40/1X50/2,0M/S7-OUT	2321033	1
	3.0 m	CABLE-FCN40/1X50/3,0M/S7-OUT	2321046	1
	4.0 m	CABLE-FCN40/1X50/4,0M/S7-OUT	2321059	1
	6.0 m	CABLE-FCN40/1X50/6,0M/S7-OUT	2321062	1
	8.0 m	CABLE-FCN40/1X50/8,0M/S7-OUT	2321075	1
	10.0 m	CABLE-FCN40/1X50/10,0M/S7-OUT	2321088	1
Assembled round cable , 40-pos. Fujitsu strip on 50-pos. FLK strip (for connection to 6ES7 321-1BP00-0AA0 input module) Positive reading mode (sinking mode) of the module	0.5 m	CABLE-FCN40/1X50/0,5M/S7-IN	2321091	1
	1.0 m	CABLE-FCN40/1X50/1,0M/S7-IN	2321101	1
	2.0 m	CABLE-FCN40/1X50/2,0M/S7-IN	2321114	1
	3.0 m	CABLE-FCN40/1X50/3,0M/S7-IN	2321127	1
	4.0 m	CABLE-FCN40/1X50/4,0M/S7-IN	2321130	1
	6.0 m	CABLE-FCN40/1X50/6,0M/S7-IN	2321143	1
	8.0 m	CABLE-FCN40/1X50/8,0M/S7-IN	2321156	1
	10.0 m	CABLE-FCN40/1X50/10,0M/S7-IN	2321169	1
Assembled round cable , 40-pos. Fujitsu strip on four 14-pos. FLK strips (for connection to 6ES7 322-1BP00-0AA0 and 6ES7 322-1BP50-0AA0 output modules)	0.5 m	CABLE-FCN40/4X14/0,5M/S7-OUT	2321172	1
	1.0 m	CABLE-FCN40/4X14/1,0M/S7-OUT	2321185	1
	2.0 m	CABLE-FCN40/4X14/2,0M/S7-OUT	2321198	1
	3.0 m	CABLE-FCN40/4X14/3,0M/S7-OUT	2321208	1
	4.0 m	CABLE-FCN40/4X14/4,0M/S7-OUT	2321211	1
	6.0 m	CABLE-FCN40/4X14/6,0M/S7-OUT	2321224	1
	8.0 m	CABLE-FCN40/4X14/8,0M/S7-OUT	2321237	1
	10.0 m	CABLE-FCN40/4X14/10,0M/S7-OUT	2321240	1
Assembled round cable , 40-pos. Fujitsu strip on four 14-pos. FLK strips (for connection to 6ES7 321-1BP00-0AA0 input module) Positive reading mode (sinking mode) of the module	0.5 m	CABLE-FCN40/4X14/0,5M/S7-IN	2321253	1
	1.0 m	CABLE-FCN40/4X14/1,0M/S7-IN	2321266	1
	2.0 m	CABLE-FCN40/4X14/2,0M/S7-IN	2321279	1
	3.0 m	CABLE-FCN40/4X14/3,0M/S7-IN	2321282	1
	4.0 m	CABLE-FCN40/4X14/4,0M/S7-IN	2321295	1
	6.0 m	CABLE-FCN40/4X14/6,0M/S7-IN	2321305	1
	8.0 m	CABLE-FCN40/4X14/8,0M/S7-IN	2321318	1
	10.0 m	CABLE-FCN40/4X14/10,0M/S7-IN	2321321	1

3 Technical data

General data	CABLE-FCN40/1X50/...M/S7...	CABLE-FCN40/4X14/...M/S7...
Nominal voltage UN	< 50 V AC/60 V DC	
Maximum permissible current carrying capacity per path	1 A	
Maximum conductor resistance	0.16 Ω/m	
Ambient temperature range		
Operation	-20°C ... +50°C	
Storage/transport	-20°C ... +70°C	
Conductor cross-section	0.14 mm ² (26 AWG)	
Conductor structure	7 litz wires, Cu tin-plated	
Outside diameter	10 mm	6.3 mm
Assembly	IDC IEC 60352-4/DIN EN 60352-4	
Connector, control side	40-pos. Fujitsu FCN connection	
Connector, module side	50-pos. flat-ribbon cable connection	4 x 14-pos. flat-ribbon cable connection

4 Color code and pin assignment

CABLE-FCN40/1X50/...M/S7-OUT

Connector, control side	Connector, module side	Conductor color
A1	3	Black
B1	27	Brown
A2	4	Red
B2	28	Orange
A3	5	Yellow
B3	29	Green
A4	6	Blue
B4	30	Violet
A5	7	Gray
B5	31	White
A6	8	White-black
B6	32	White-brown
A7	9	White-red
B7	33	White-orange
A8	10	White-yellow
B8	34	White-green
A9	11(-)	White-blue
B9	35(-)	White-violet
A10	1(+)	White-gray
B10	25(+)	Brown-black
A11	15	Brown-red
B11	39	Brown-orange
A12	16	Brown-yellow
B12	40	Brown-green
A13	17	Brown-blue
B13	41	Brown-violet
A14	18	Brown-gray
B14	42	Brown-white
A15	19	Green-black
B15	43	Green-brown
A16	20	Green-red
B16	44	Green-orange
A17	21	Green-blue
B17	45	Green-violet
A18	22	Green-gray
B18	46	Green-white
A19	23(-)	Yellow-black
B19	47(-)	Yellow-brown
A20	13(+)	Yellow-red
B20	37(+)	Yellow-orange

CABLE-FCN40/1X50/...M/S7-IN

Connector, control side	Connector, module side	Conductor color
A1	3	Black
B1	27	Brown
A2	4	Red
B2	28	Orange
A3	5	Yellow
B3	29	Green
A4	6	Blue
B4	30	Violet
A5	7	Gray
B5	31	White
A6	8	White-black
B6	32	White-brown
A7	9	White-red
B7	33	White-orange
A8	10	White-yellow
B8	34	White-green
A9	11(-)	White-blue
B9	35(-)	White-violet
A10	15	White-gray
B10	39	Brown-black
A11	16	Brown-red
B11	40	Brown-orange
A12	17	Brown-yellow
B12	41	Brown-green
A13	18	Brown-blue
B13	42	Brown-violet
A14	19	Brown-gray
B14	43	Brown-white
A15	20	Green-black
B15	44	Green-brown
A16	21	Green-red
B16	45	Green-orange
A17	22	Green-blue
B17	46	Green-violet
A18	23(-)	Green-gray
B18	47(-)	Green-white
A19		Yellow-black
B19		Yellow-brown
A20		Yellow-red
B20		Yellow-orange

CABLE-FCN40/4X14/...M/S7-OUT

	Connector, control side	Connector, module side	Conductor color
Connection 1 (byte 0)	A9	10(-)	White
	A10	9(+)	Gray
	A8	8	Violet
	A7	7	Blue
	A6	6	Green
	A5	5	Yellow
	A4	4	Orange
	A3	3	Red
	A2	2	Brown
	A1	1	Black
Connection 2 (byte 1)	A19	10(-)	White
	A20	9(+)	Gray
	A18	8	Violet
	A17	7	Blue
	A16	6	Green
	A15	5	Yellow
	A14	4	Orange
	A13	3	Red
	A12	2	Brown
	A11	1	Black
Connection 3 (byte 2)	B9	10(-)	White
	B10	9(+)	Gray
	B8	8	Violet
	B7	7	Blue
	B6	6	Green
	B5	5	Yellow
	B4	4	Orange
	B3	3	Red
	B2	2	Brown
	B1	1	Black
Connection 4 (byte 3)	B19	10(-)	White
	B20	9(+)	Gray
	B18	8	Violet
	B17	7	Blue
	B16	6	Green
	B15	5	Yellow
	B14	4	Orange
	B13	3	Red
	B12	2	Brown
	B11	1	Black

CABLE-FCN40/4X14/...M/S7-IN

	Connector, control side	Connector, module side	Conductor color
Connection 1 (byte 0)	A9	10(-)	Gray
	A8	8	Violet
	A7	7	Blue
	A6	6	Green
	A5	5	Yellow
	A4	4	Orange
	A3	3	Red
	A2	2	Brown
	A1	1	Black
	Connection 2 (byte 1)	A18	10(-)
A17		8	Violet
A16		7	Blue
A15		6	Green
A14		5	Yellow
A13		4	Orange
A12		3	Red
A11		2	Brown
A10		1	Black
Connection 3 (byte 2)		B9	10(-)
	B8	8	Violet
	B7	7	Blue
	B6	6	Green
	B5	5	Yellow
	B4	4	Orange
	B3	3	Red
	B2	2	Brown
	B1	1	Black
	Connection 4 (byte 3)	B18	10(-)
B17		8	Violet
B16		7	Blue
B15		6	Green
B14		5	Yellow
B13		4	Orange
B12		3	Red
B11		2	Brown
B10		1	Black