



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





7.0" 40-pin TFT Display - 800x480 without Touchscreen

PRODUCT ID: 2353



. Description

This 7.0" TFT screen has lots of pixels, 800x480 to be exact, and an LED backlight. Its great for when you need a lot of space for graphics. These screens are commonly seen in consumer electronics, such as miniature TV's, GPS's, handheld games car displays, etc. A 40-pin connector has 8 red, 8 green, and 8 blue parallel pins, for 24 bit color capability.

This version does not have touchscreen attached It's exactly the same TFT display as PID 2354 but without the resistive touch panel so it is a little less expensive.

This is a "raw pixel-dot-clock" display and does not have an SPI/parallel type controller or any kind of RAM. The display is supposed to be constantly refreshed, at 60Hz, with a pixel clock, V sync, H sync, etc.

There are some high end processors such as that used in the BeagleBone that can natively support such RGB TTL displays. However, it is extremely rare for a small microcontroller to support it, as you need dedicated hardware or a very fast processor such as an FPGA. Not only that, but the backlight requires a 125-150mA constant-current mode boost converter that can go as high as 9V instead of our other small displays that can run the backlight off of 5V

For that reason, we are carrying it as a companion to the Adafruit RA8875 driver board in the store, which is a chip that can handle the huge video RAM and timing requirements, all in the background. That's the best way to interface this display to just about any microcontroller (including Arduino & friends) If you want to control with from an HDMI or DVI output, check out our TFP401 driver board. If you are an advanced electronics enthusiast you can try wiring this directly to your processor, but it we don't have any support or tutorials for that purpose.

. **Technical Details**

- Dimensions: 164mm x 100mm x 4mm / 6.5" x 3.9" x 0.2"