



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts,Customers Priority,Honest Operation,and Considerate Service",our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Chip Beads (2512063007Y0)



Part Number: 2512063007Y0

MULTI- LAYER CHIP BEAD

Part Number System: Example 2512063017Y1

| 25 | 1206 | 301 | 7 | Y | 1 |
|-----------------------|--------------------------|-------------------------------|--|---|--|
| Chip Bead Code | Package Size Code | Impedance Code 300Ω | Packaging Code 6= Bulk Packed 7= Taped and Reeled 7" Reel 8= Taped and Reeled 13" Reel | Material Code Y = Standard Signal Speed Z = High Signal Speed H = GHz Speed | Current Code 0 < 1.0A 1 ≥ 1.0A < 2.0A 3 ≥ 3.0A < 4.0A ETC |

Fair- Rite offers a broad selection of cost effective multi- layer chip beads to suppress conducted EMI signals. Chip beads can be used in an array of devices such as cellular phones, computers, laptops, pagers, etc. The small package sizes accommodate automated placements and allow for a dense packaging of circuit boards.

Chip Beads are available in standard, high and GHz signal speeds.

Packaging Options:

-□ All multi- layer chip beads are supplied taped and reeled, if required bulk packed chip beads can be provided.

The suggested land patterns are in accordance to the latest revision of IPC-7351.

Weight: 0.03 (g)

Package Size: 1206 (3216)

| Dim | mm | mm tol | nominal inch | inch misc. |
|-----|-----|--------|--------------|------------|
| A | 1.1 | ±0.20 | 0.043 | — |
| B | 1.6 | ±0.20 | 0.063 | — |
| C | 3.2 | ±0.20 | 0.126 | — |
| D | 0.7 | ±0.30 | 0.028 | — |

| Reel Information | | | | |
|------------------|-------|----------|-----------|-----------|
| Tape Width | Pitch | Parts 7" | Parts 13" | Parts 14" |
| mm | mm | Reel | Reel | Reel |
| 8 | 4 | 3000 | 10000 | — |

Land Patterns

| V | W | X | Y | Z |
|------------------|------------------|------------------|------------------|---|
| 1.20 (0.047") | 2.80 (0.110") | 1.80 (0.071") | 1.60 (0.063") | — |

Chart Legend

+ Test frequency

| Typical Impedance (Ω) | |
|-----------------------|---------|
| 50 MHz | 21 |
| 100 MHz ⁺ | 30 ±25% |
| 500 MHz | 49 |
| 1000 MHz ⁺ | - |

| Electrical Properties | |
|-------------------------|-----|
| Max DCR (Ω) | 0.1 |
| Max Current (mA) | 800 |

The impedance values listed are typical values. The nominal impedance with a +/- 25% tolerance is specified for the + marked 100 MHz. Chip beads are measured for impedance on the HP 4291A and fixture HP 16192A. Chip beads are 100% tested for impedance and dc resistance.



Fair- Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288
888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • ferrites@fair-rite.com • www.fair-rite.com