imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





- Polyamide hand held enclosure for MCR- and automation engineering
- Ergonomic enclosure shape
- Version with or without display opening
- Prepared for acceptance of keypads/silicone switch mats
- Optional EMC version with internal coating and EMC seal

Technical data

Material:

polyamide

Ingress protection: IP 65 to EN 60529

Surface resistance: 10¹² Ohm, IEC 60093

Flammability:

Colour:

RAL 7021, black grey

Temperature range:

-40°Cto +60°C

Included in delivery

Double-skinned enclosure with top and base unit, each with fixing domes, fastening and enclosure screws. Open version incl. display screen and punshed seal.

Beluga 180/220

Programme range

Enclosuretype	Order No.	Version	Dimensions	Weight
			WxLxH(mm)	(kg)
Beluga 180 O	27.02 02 00	open	106/75 x 187 x 50	0.16
Beluga 180 G	27.02 02 01	closed	106/75 x 187 x 50	0.17
Beluga 220 O	27.02 04 00	open	116/85 x 220 x 51	0.20
Beluga 220 G	27.02 04 01	closed	116/85 x 220 x 51	0.21

Accessories

Hook set without magnet	27.02 00 80
Hook set with magnet	27.02 00 81
Keypad FT 180b, 15 keys, Matrix printed (B 180)	82.10 00 03
Keypad FT 180ge, 12 keys, common connection with insert (B 180)	82.10 00 07
Keypad FT 180e, 15 keys, Matrix with insert (B 180)	82.10 00 04
Keypad FT 220b, 18 keys, Matrix printed (B 220)	82.10 00 05
Keypad FT 220e, 18 keys, Matrix with insert (B 220)	82.10 00 06
Connector (B180)	82.20 00 08
Connector (B220)	82.20 00 09
Display fixing set (B 180)	27.01 06 80
Display fixing set (B 220)	27.02 04 82
Cable gland with bending protection M 16 x 1,5	08.10 01 16
Cable gland with bending protection M 20 x 1,5	08.10 01 20
Hand strap	27.02 00 83
Spare screws	27.02 00 82
Spare display screen set (B 180)	27.01 06 88
Spare display screen set (B 220)	27.02 04 83
Battery compartment (B 180 / 220) without contacts	27.02 00 85
Battery holder for 4 round cells for battery compartment	27.02 00 86
Battery holder for 9 V battery for battery compartment	27.02 00 87
Wall fixing for hook set	27.02 00 84
Enabling switch 2-step, blue	83.50 00 10
Scratch resistant display screen	on request
Push-botton and switches see page 53 - 58	on request




Electromechanical components On request, we offer the enclosures ready equipped with electromechanical components such as emergency stop button, confirm keys, hand wheel, step switch, display.

Compontents mounting options

Component options	Type B180 O	Type B180 G	Type B220 O	Type B220 G
Display max. view area 42 x 65 mm	•			
max. mounting dimensions 56,4 x 74 mm or 54 x 80	mm			
Display max. view area 49 x 78 mm			•	
max. mounting dimensions 71,5 x 84 mm or 70,5 x 8	6 mm			
Emergency stop button	٠	•	•	•
Confirm key	•	•	•	•
Hand wheel		•		•
Step switch		•		•
Joy stick	•		•	
Cable outlet up to M 16	•	•	•	•
Cable outlet up to M 20			•	•
1st board (main board)	•	•	•	•
Other boards	•	•	•	•

Dimensions




Beluga 180/230


Accessories



Membrane keypads for Beluga 180 Standard membrane keypad with 15 keys as printed version or plain. Insertion facility for custom inscription

Туре	Version	Order No.
FT B180 - 15 b	Matrix printed	82.10 00 03
FT B180 - 15 e	Matrix with plug-in-unit	82.10 00 04
	Connector	82.20 00 08









Membrane keypads for Beluga 220 Standard membrane keypad with 18 keys as printed version or plain. Insertion facility for custom inscription

Туре	Version	Order No.
FT B220 - 18 b	Matrix printed	82.10 00 05
FT B220 - 18 e	Matrix with plug-in-unit	82.10 00 06
	Connector	82.20 00 09





Accessories



Membrane keypads for Beluga 180 Standard membrane keypad with 12 keys as plain version. Insertion facility for custom inscription

Туре	Version	Order No.	
FT B180 - 12 ge	common connection with insert	82.10 00 07	
	Distance 1,5 mm to edge		



Hook set consisting of mounted hook and fixing screws

Version	Order No.
without magnet	27.02 00 80
with magnet	27.02 00 81



Display fixing set for variable display mounting

Version for	Order No.
Beluga 180	27.01 06 80
Beluga 220	27.02 04 82



Battery compartment B 180/220 without contacts

Order No. 27.02 00 85

Adhesion by version with magnet

· · · · · · · · · · · · · · · · · · ·		
plate thickness	force	
2 mm	20 N	
5 mm	30 N	

Beluga 180/220

Applications





