

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China










November 2010

# 2KBP005M/3N253 - 2KBP10M/3N259 Bridge Rectifiers

### **Features**

- Surge overload rating: 60 amperes peak.
- · Reliable low cost construction utilizing molded plastic technique.
- UL certified, UL #E111753.



\* The nodules on the package may not be present on the actual parts.

## **Absolute Maximum Ratings** \* $T_a = 25$ °C unless otherwise noted

		Value							
Symbol	Parameter	005M	01M	02M	04M	06M	08M	10M	Units
		253	254	255	256	257	258	259	
V <sub>RRM</sub>	Maximum Repetitive Reverse Voltage	50	100	200	400	600	800	1000	V
V <sub>RMS</sub>	Maximum RMS Bridge Input Voltage	35	70	140	280	420	560	700	V
$V_{R}$	DC Reverse Voltage (Rated V <sub>R</sub> )	50	100	200	400	600	800	1000	V
I <sub>F(AV)</sub>	Average Rectified Forward Current, @ T <sub>A</sub> = 50°C	2.0		Α					
I <sub>FSM</sub>	Non-Repetitive Peak Forward Surge Current 8.3ms Single Half-Sine-Wave	60			Α				
T <sub>STG</sub>	Storage Temperature Range	-55 to +150		°C					
T <sub>J</sub>	Junction Temperature	-55 to +150			°C				

<sup>\*</sup> These ratings are limiting values above which the serviceability of any semiconductor device may by impaired.

### **Thermal Characteristics**

Symbol	Parameter	Value	Units
P <sub>D</sub>	Power Dissipation	4.7	W
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient, * per leg	18	°C/W

<sup>\*</sup> Device mounted on PCB with  $0.47 \times 0.47$ " (12  $\times$  12mm).

# **Electrical Characteristics** $T_a = 25$ °C unless otherwise noted

Symbol	Parameter	Value	Units
V <sub>F</sub>	Forward Voltage, per element @ 3.14A	1.1	V
I <sub>R</sub>	Reverse Current, per element @ Rated $V_R$ $T_A = 25^{\circ}C$ $T_A = 125^{\circ}C$	5.0 500	μ <b>Α</b> μ <b>Α</b>
	I <sup>2</sup> t Rating for Fusing t < 8.35ms	15	A <sup>2</sup> s
C <sub>T</sub>	Total Capacitance, per leg $V_R = 4.0 \text{ V}, f = 1.0 \text{ MHz}$	25	pF

# **Typical Performance Characteristics**

Figure 1. Forward Curve Derating Curve




Figure 3. Reverse Current vs Reverse Voltage




Figure 2. Forward Voltage Characteristics





Figure 4. Non-Repetitive Surge Current







#### TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

 AccuPower™
 F-PFS™

 Auto-SPM™
 FRFET®

 Build it Now™
 Global Power Resource

 CorePLUS™
 Green FPS™

 CorePOWER™
 Green FPS™ e-Series™

 CROSSVOLT™
 Gmax™

 CTL™
 GTO™

CTL™
Current Transfer Logic™
DEUXPEED®
ISOPLANAR™
Dual Cool™
EcoSPARK®
MICROCOUPLER™
EfficientMax™
MicroFET™

ESBC™
MicroPak™
MicroPak™
MicroPak™
MillerDrive™
MillerDrive™
MotionMax™
Motion-SPM™
OptoHiT™
FACT®
FAST®
OPTOLOGIC®
FastvCore™

MicroPak™
MicroPak™
MillerDrive™
Motion-SPM™
OptoHiT™
OPTOLOGIC®
OPTOPLANAR®

FlashWriter®\*
PDP SPM™

PS™

Power-SPM™ PowerTrench® PowerXS™

Programmable Active Droop™

QFĒT<sup>®</sup> QS™

Quiet Series™ RapidConfigure™

Saving our world, 1mW/W/kW at a time™

SignalWise™ SmartMax™ SMART START™ SPM® STEALTH™

SuperFET®
SuperSOT™-3
SuperSOT™-6
SuperSOT™-8
SupreMOS®
SyncFET™
Sync-Lock™

SYSTEM ®\*
GENERAL

The Power Franchise®
the pranchise
franchise
TinyBoost™

TinyBuck™
TinyCalc™
TinyLogic®
TinYOPTO™
TinyPower™
TinyPWM™
TinyWire™
Tripault Detect™
TRUECURRENT™\*\*

SerDes`
UHC®
Ultra FRFET™
UniFET™
VCX™
VisualMax™
XS™

μSerDes™

#### DISCLAIMER

FETBench™

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

#### As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

### **ANTI-COUNTERFEITING POLICY**

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

#### PRODUCT STATUS DEFINITIONS

#### Definition of Terms

Definition of Terms				
Datasheet Identification	Product Status	Definition		
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.		
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.		
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.		
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.		

Rev. I50

<sup>\*</sup> Trademarks of System General Corporation, used under license by Fairchild Semiconductor,