

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China







306C Data Sheet 04.10

306C Pocket Digital Thermometer

Test the TPI advantage



Features:

- Field calibrateable to ±2°F
- Easy-to-read LCD
- Data Hold for hard to reach areas
- Penetration tip
- Auto off
- 3-year limited warranty

APPLICATIONS:

HVACR

- Ambient Air
- Calibrate

Thermostats

- Vents
- Compressor Heads
- Registers

F₀0D

- Grill & Surface Temperatures
- Serving Temperatures

ELECTRICAL

- Motor Temperatures
- •Transformer Temperatures

Compact easy to use thermometer with large display and auto power off.



Comes with A306 protective boot



Specifications:	
Temperature Range	-58°F to 300°F (-50°C to 150°C)
Accuracy	+/-2°F (+/-1°C)
Resolution	0.1°F/°C
Sample Rate	1 reading every 1.5 second
Stem Length	4.9"
Tip Type	Penetration
Water Resistant	N/A
Water Proof	N/A
°C / °F Selectable	Yes
Data Hold	Yes
Auto Off	Yes
Battery Type	LR44