

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



# Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



















## Anaren Integrated Radio 66089 U.FL Antenna Series

The 66089 series antennas are designed for quick connection to Anaren Integrated Radio modules, and have been certified to meet "intentional radiator" requirements for low power non-licensed devices (FCC, IC, and ETSI). The 66089 series antennas are intended for applications where an embedded antenna module is not practical—such a radio module mounted inside a shielded enclosure.

### **Specifications**

#### PERFORMANCE CHARACTERISTICS:

Impedance: 50 ohms Frequency Range: See table 3 dBI Gain: VSWR: 1.7 max Omni directional Radiation:

	Band	Antenna	Center	FCC	
Module	ID	Element	Frequency	(IC)	ETSI
A1101R04C	04	173±1 mm	425 MHz		Χ
A1101R08C	08	86±1 mm	866 MHz		Χ
A1101R09C	09	82±1 mm	915 MHz	Χ	
A25xxE24C	24	2011 202	2.442 GHz	V	V
A25xxR24C	24	30±1 mm	2.442 GHZ	Х	Х
A110LR09C	89	84±1 mm	898 MHz	Χ	Х



This product is not to be used in any implantable medical device or external medical device intended to regulate or monitor biological functions, including but not limited to devices such as pacemakers, defibrillators, cardiac resynchronization devices, pressure sensors, biochemical stimulators and neurostimulators. ANAREN MAKES NO WARRANTY OF FITNESS OR MERCHANTABILITY OF THIS PRODUCT FOR ANY USE OF THIS TYPE. Anaren shall not be responsible for any consequential damages arising from the sale or use of this product for any use of this type. The ultimate user of the

#### **Nomenclature**

66089-XX06

1 Band See "Band ID" in table 2 Lead Length 06 = 6mm 'standard' 30 = 30mm 'extended'

To view the entire available family of AIR Modules & Development options, please visit our website at:

http://www.anaren.com/air



#### Layout





