



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





Clocks for NXP QorIQ and Layerscape CPUs

Selecting clocks for QorIQ designs is straightforward. Once the “Qor” clocking requirements of the NXP QorIQ processors are satisfied (SYS_CCB clock, etc.), product selection proceeds to other required clocks, such as USB or 25M for Ethernet. Then the desired data rates, frequencies and number of SERDES links are factored into the clock selection. IDT offers both integrated and building block approaches to QorIQ timing solutions as shown in the product selector tables.

Clocking Solutions for NXP QorIQ and Layerscape Processors								
"All-in-One" Clock Solutions								
	NXP Clock Modes (only 1 at a time is used)			Other Clocks			SERDES Clock Pairs	
Part Number	SYS_CLK/ DDR_CLK	DIFSYS_CLK	PS_XI	GTX_CLK	USB_CLK (MHz)	Other LVCMOS Outputs (MHz)	Pairs (MHz)	App Jitter Compliance
6V49205	Yes	Yes	Yes (24M Only)	Yes	2 x 12/24	6 x 25 2 x 2.048	6 x 100/125	PCIe Gen1-2, SGMII, sRIO 1x-2x SATA/SATA3G
5P49V5907			Yes		4 x 50 - 167	PCIe Gen1-3, SGMII 1x-2.5x, sRIO 1x-2x SATA/SATA3G, XAUI, XAUI 10G		
5P49V5908			Yes		8 x 50 - 167			
"Building Block" Clock Generators								
Part Number	SYS_CLK/ DDR_CLK	DIFSYS_CLK	PS_XI	GTX_CLK	USB_CLK (MHz)	Other LVCMOS Outputs (MHz)	Pairs (MHz)	App Jitter Compliance
5P30521	Yes	Yes	Yes	Yes	Yes	1 x 32.768KHz	2 x 1 - 500	PCIe Gen1-3
5P30523						1 x REF	4 x 1 - 350	500fs RMS
5P49V69xx							-	-
840S07		No	No		-	-	-	-
MP9855					-	2x 25	-	-
840NT4	-	-	-	-	-	1 x 25 1 x 3.125 1 x 1.5625	-	-
840NT4-01	-	-	-	-	1 x 24	1 x 25 8 x 125	-	-
8T49N222	-	-	-	-	-	-	2 x 7.7 - 1200	300fs RMS
8T49N004	-	-	-	-	-	-	4 x 15.16 - 1250	212fs RMS
8T49N006	-	-	-	-	-	-	6 x 15.16 - 1250	
8T49N008	-	-	-	-	-	-	8 x 15.16 - 1250	
8T49N012	-	-	-	-	-	-	12 x 15.16 - 1250	
8T49NS0312	-	Yes	Yes	-	-	-	12 x 10.9 - 2500	89fs RMS



Clocks for NXP QorIQ and Layerscape CPUs

"Building Block" Non-PLL Fanout Buffers and Multiplexers (< 50fs RMS additive phase jitter)												
Part Number	Inputs (#)	Input Type	Outputs (#)	Output Type	Output Freq (MHz)	Input Freq (MHz)	Core Supply (V)	Output Supply (V)				
5PB1104	1	LVCMOS	4	LVCMOS	0 - 200	0 - 200	1.8, 2.5, 3.3	1.8, 2.5, 3.3				
5PB1106			6									
5PB1108			8									
5PB1110			10									
8312I			12									
8P34S1102I		CML, LVDS, LVPECL	2	LVDS	0 - 1200	0 - 1200	1.8	1.8				
8P34S1106i			6									
8SLVP1102I			2	LVPECL	0 - 2000	0 - 2000	2.5, 3.3	2.5, 3.3				
8SLVP1104I			4									
8530-01		HCSL, HSTL, LVDS, LVPECL, SSTL	16	LVPECL	0 - 500	0 - 500	3.3	3.3				
8SLVP2102I	CML, LVDS, LVPECL	4	0 - 2000		0 - 2000	2.5, 3.3	2.5, 3.3					
8SLVP2104I		8										
8SLVP2106I	LVDS, LVPECL	12										
8SLVP2108I	LVPECL	16										
8T39S04A	3	Xtal, HCSL, HSTL, LVCMOS, LVDS, LVPECL						4	HCSL, LVDS, LVPECL			
8T39S06A								6				
8T39S08A								8				

"Building Block" PCI Express Clock Generators (LP-HCSL outputs)								
Part Number	Input (MHz)	Spread Spectrum Support	Outputs (#)	Operating Frequency (MHz)	Lead Count (#)	Package Size (mm)	Supply Voltage (V)	App Jitter Compliance
9FGV0241	25	Yes	2	100	24	4 x 4	1.8	PCIe Gen1-4
9FGV0441			4		32	5 x 5		
9FGV0641			6		40	5 x 5		
9FGV0841			8		48	6 x 6		
9FGL0241			2		24	4 x 4	3.3	
9FGL0441			4		32	5 x 5		
9FGL0641			6		40	5 x 5		
9FGL0841			8		48	6 x 6		

"Building Block" non-PLL Fanout Buffers and Multiplexers (HCSL inputs and LP-HCSL outputs)								
Part Number	Inputs	Spread Spectrum Support	Outputs (#)	Operating Frequency (MHz)	Lead Count (#)	Package Size (mm)	Supply Voltage (V)	App Jitter Compliance
9DBV0541	1	Yes	5	1 - 200	32	5 x 5	1.8	PCIe Gen1-4
9DBV0741			7		40	5 x 5		
9DBV0941			9		48	6 x 6		
9DMV0141	2		1		16	3 x 3		
9DMV0441			4		24	4 x 4		
9DBL0741	1		7		40	5 x 5	3.3	
9DBL0941			9		48	6 x 6		
9DMV0441			2		4	24		



Clocks for NXP QorIQ and Layerscape CPUs

"Building Block" PCI Express PLL Zero-Delay Buffers (HCSL inputs and LP-HCSL outputs)								
Part Number	Inputs	Spread Spectrum Support	Outputs (#)	Operating Frequency (MHz)	Lead Count (#)	Package Size (mm)	Supply Voltage (V)	App Jitter Compliance
9DBV0241	1	Yes	2	30 - 175	24	4 x 4	1.8	PCIe Gen1-4
9DBV0441			4		32	5 x 5		
9DBV0641			6		40	5 x 5		
9DBV0841			8		48	6 x 6		
9DBL0242			2		24	4 x 4	3.3	
9DBL0442			4		32	5 x 5		
9DBL0641			6		40	5 x 5		
9DBL0841			8		48	6 x 6		

To request samples, download documentation, or learn more visit: idt.com/go/clocks