



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832



Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



**Miniature Fuses
Type A12FA 380V**

super-quick-acting FF
high breaking capacity
Ceramic tube



Standards

none

Approvals



Pre-arcing time/current characteristic (at T_a 23 °C)

Rated current I_n	$n \cdot I_n$	
	$1,5 \cdot I_n$	$2,1 \cdot I_n$
	min.	max.
0,1 – 12,5 A	1 h	1 h

Technical data

Weight 3 g

Order No.	Rated current I_n Rated voltage U_n	Breaking capacity	Voltage drop		Sustained power dissipation		Pre-arcing I^2t		Approvals
			at I_n	max. mV	at $1,5 \cdot I_n$	max. W	at $10 \cdot I_n$	A^2s	
7022.0000	0,100 A / 380 V	150 kA / 380 V AC p.f. / $\cos \varphi \geq 0,2$		2600		1,5		$1,5 \cdot 10^{-3}$	•
7022.0010	0,125 A / 380 V			2300		1,5		$2,9 \cdot 10^{-3}$	•
7022.0020	0,160 A / 380 V			1700		1,4		$5,8 \cdot 10^{-3}$	•
7022.0030	0,200 A / 380 V			1500		1,2		$1,3 \cdot 10^{-2}$	•
7022.0040	0,250 A / 380 V			1500		2,2		$1,9 \cdot 10^{-2}$	•
7022.0050	0,315 A / 380 V			2150		4,1		$2,2 \cdot 10^{-2}$	•
7022.0060	0,400 A / 380 V			2750		2,85		$2,3 \cdot 10^{-2}$	•
7022.0070	0,500 A / 380 V			2850		3,65		$4,1 \cdot 10^{-2}$	•
7022.0080	0,630 A / 380 V			2000		3,2		$1 \cdot 10^{-1}$	•
7022.0090	0,800 A / 380 V			2050		4,15		$1,7 \cdot 10^{-1}$	•
7022.0100	1 A / 380 V			1750		4,45		$4,4 \cdot 10^{-1}$	•
7022.0110	1,25 A / 380 V			740		4,15		$2 \cdot 10^{-1}$	•
7022.0120	1,60 A / 380 V			570		3,05		$5,4 \cdot 10^{-1}$	•
7022.0130	2 A / 380 V			615		4,50		$8,1 \cdot 10^{-1}$	•
7022.0140	2,50 A / 380 V			465		4,35		1,8	•
7022.0150	3,15 A / 380 V			440		5		3,4	•
7022.0160	4 A / 380 V			335		4,8		8,1	•
7022.0170	5 A / 380 V			395		7,7		12	•
7022.0180	6,30 A / 380 V			170		3		6	•
7022.0190	8 A / 380 V			135		3		15	•
7022.0200	10 A / 380 V		155		4,75		20	•	
7022.0210	12,50 A / 380 V		210				15	•	

