imall

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832 Email & Skype: info@chipsmall.com Web: www.chipsmall.com Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China






SINGLE 2 INPUT POSITIVE NAND GATE

Description

The 74AHC1G00 is a single 2-input positive NAND gate with a standard push-pull output. The device is designed for operation with a power supply range of 2.0 V to 5.5 V. The gate performs the positive Boolean function:

$$Y = \overline{A \bullet B}$$
 or $Y = \overline{A} + \overline{B}$

Pin Assignments



Features

- Supply Voltage Range from 2.0V to 5.5V
- ± 8 mA Output Drive at 5.0 V
- CMOS low power consumption
- Schmitt Trigger Action at All Inputs Make the Circuit Tolerant for Slower Input Rise and Fall Time.
- ESD Protection per JESD 22
 - o Exceeds 200-V Machine Model (A115-A)
 - Exceeds 2000-V Human Body Model (A114-A)
 - Exceeds 1000-V Charged Device Model (C101C)
- Latch-Up Exceeds 100mA per JESD 78, Class II
- SOT25 and SOT353: Assembled with "Green" Molding Compound (no Br, Sb)
- Lead Free Finish / RoHS Compliant (Note 1)

Applications

- General Purpose Logic
- Wide array of products such as:
 - PCs, networking, notebooks, netbooks, PDAs
 - o Computer peripherals, hard drives, CD/DVD ROM
 - o TV, DVD, DVR, set top box
 - o Personal Navigation / GPS
 - o MP3 players ,Cameras, Video Recorders

Notes: 1. EU Directive 2002/95/EC (RoHS). All applicable RoHS exemptions applied. Please visit our website at http://www.diodes.com/products/lead_free.html.




SINGLE 2 INPUT POSITIVE NAND GATE

Pin Descriptions

Pin Name	Pin NO.	Description
A	1	Data Input
В	2	Data Input
GND	3	Ground
Y	4	Data Output
V _{CC}	5	Supply Voltage

Logic Diagram



Function Table

Inp	Inputs		
Α	В	Y	
Н	Н	L	
L	Х	Н	
Х	L	Н	

74AHC1G00 Document number: DS35169 Rev. 1- 2



SINGLE 2 INPUT POSITIVE NAND GATE

Absolute Maximum Ratings (Note 2)

Symbol	Description	Rating	Unit
ESD HBM	Human Body Model ESD Protection	2	KV
ESD CDM	Charged Device Model ESD Protection	1	KV
ESD MM	Machine Model ESD Protection	200	V
V _{CC}	Supply Voltage Range	-0.5 to 6.5	V
VI	Input Voltage Range	-0.5 to 6.5	V
Vo	Voltage applied to output in high or low state	-0.5 to V _{CC} +0.5	V
I _{IK}	Input Clamp Current VI<0	-20	mA
I _{OK}	Output Clamp Current (V _O < 0 or V _O > V _{CC})	±20	mA
lo	Continuous output current ($V_O = 0$ to V_{CC})	±25	mA
I _{CC}	Continuous current through V _{CC}	50	mA
I _{GND}	Continuous current through GND	-50	mA
TJ	Operating Junction Temperature	-40 to 150	°C
T _{STG}	Storage Temperature	-65 to 150	°C

Notes: 2. Stresses beyond the absolute maximum may result in immediate failure or reduced reliability. These are stress values and device operation should be within recommend values.

Recommended Operating Conditions (Note 3)

Symbol		Parameter	Min	Мах	Unit
V _{CC}	Operating Voltage		2	5.5	V
		$V_{CC} = 2V$	1.5		
VIH	High-level Input Voltage	$V_{CC} = 3V$	2.1		V
		$V_{CC} = 5.5V$	3.85		
		$V_{CC} = 2V$		0.5	
VIL	Low-level input voltage	$V_{CC} = 3V$		0.9	V
		$V_{CC} = 5.5V$		1.65	
VI	Input Voltage		0	5.5	V
Vo	Output Voltage		0	V _{CC}	V
		$V_{CC} = 2V$		-50	uA
I _{OH}	High-level output current	$V_{CC} = 3.3V \pm 0.3V$		-4	
		$V_{CC} = 5V \pm 0.5V$		-8	- mA
		$V_{CC} = 2V$		50	uA
I _{OL}	Low-level output current	$V_{CC} = 5V \pm 0.5V$		4	
		$V_{CC} = 3V$		8	- mA
A ± / A \ /	Input transition rise or fall	$V_{CC} = 3.3V \pm 0.3 V$		100	
Δt/ΔV	rate	$V_{CC} = 5V \pm 0.5V$		20	ns/V
T _A	Operating free-air temperature		-40	125	°C

Notes: 3. Unused inputs should be held at Vcc or Ground.



SINGLE 2 INPUT POSITIVE NAND GATE

Electrical Characteristics

O what	Demonster	To at Oan ditions	N		25ºC		-40ºC t	o 85ºC	-40ºC to	o 125ºC	1114
Symbol	Parameter	Test Conditions	V _{CC}	Min	Тур.	Max	Min	Max	Min	Max	Unit
			2V	1.9	2		1.9		1.9		
		Ι _{ΟΗ} = -50μΑ	3V	2.9	3		2.9		2.9		
V _{OH}	High Level		4.5V	4.4	4.5		4.4		4.4		V
0.11	Output Voltage	I _{OH} = -4mA	ЗV	2.58			2.48		2.40		
		I _{OH} = -8mA	4.5V	3.94			3.8		3.70		
			2V			0.1		0.1		0.1	
		I _{OL} = 50μΑ	ЗV			0.1		0.1		0.1	
V _{OL}	Low Level		4.5V			0.1		0.1		0.1	V
_	Output Voltage	$I_{OL} = 4mA$	ЗV			0.36		0.44		0.55	
		$I_{OL} = 8mA$	4.5V			0.36		0.44		0.55	
l _l	Input Current	$V_I = 5.5 V \text{ or } GND$	0 to 5.5V			± 0.1		± 1		± 2	μA
I _{CC}	Supply Current	V _I = 5.5V or GND I _O =0	5.5V			1		10		40	μA
CI	Input Capacitance	V _I = V _{CC} – or GND	5.5V		2.0	10		10		10	pF
θ _{JA}	Thermal Resistance	SOT25	(Note 4)		195						°C/W
UJA	Junction-to- Ambient	SOT353	(11018 4)		430						0/00
θ _{JC}		SOT25	(Note 4)		58						°C/W
OIC	Junction-to- Case	SOT353	(11010 4)		155						0/ 00

Notes: 4. Test conditions for SOT25, and SOT353: Device mounted on FR-4 substrate PC board, 2oz copper, with minimum recommended pad layout

Switching Characteristics

V_{cc} = 3.3V ± 0.3 (see Figure 1)

Parameter	From	TO		2	25ºC		-40ºC t	o 85ºC	-40ºC te	o 125ºC	Unit
	(Input)	(OUTPUT)	-	Min	Тур.	Max	Min	Max	Min	Max	
+ .	A or B	V	$C_L=15pF$	0.6	4.5	7.9	0.6	9.5	0.6	10.5	ns
t _{pd}	AULD	Ť	C _L =50pF	0.6	6.5	11.4	0.6	13.0	0.6	14.5	ns

V_{cc} = 5V ± 0.5V (see Figure 1)

Parameter	From	TO			25°C -40°C to			o 85ºC	-40ºC to		Unit
	(Input)	(OUTPUT)	Γ	Min	Тур.	Мах	Min	Max	Min	Max	
+ .	A or B	v	$C_L=15pF$	0.6	3.5	5.5	0.6	6.5	0.6	7.0	ns
lpd	AULP	T	$C_L=50pF$	0.6	4.9	7.5	0.6	8.5	0.6	9.5	ns




SINGLE 2 INPUT POSITIVE NAND GATE

Operating Characteristics


T_A = 25 ^oC

	Parameter	Test Conditions	V _{CC} = 5 V Typ.	Unit
C _{pd}	Power dissipation capacitance	f = 1 MHz No Load	10	pF


Parameter Measurement Information



Vcc	Inj	outs	V _M	CL
VCC	VI	t _r /t _f	▼ IVI	υĽ
3.3V±0.3V	V _{CC}	≤3ns	V _{CC} /2	15pF
5V±0.5V	V _{CC}	≤3ns	V _{CC} /2	15pF
3.3V±0.3V	V _{CC}	≤3ns	V _{CC} /2	50pF
5V±0.5V	V _{CC}	≤3ns	V _{CC} /2	50pF



Voltage Waveform Pulse Duration



Voltage Waveform Propagation Delay Times Inverting and Non Inverting Outputs

Figure 1. Load Circuit and Voltage Waveforms


Notes: A. Includes test lead and test apparatus capacitance.

- B. All pulses are supplied at pulse repetition rate \leq 1 MHz.
- C. Inputs are measured separately one transition per measurement.
- D. t_{PLH} and t_{PHL} are the same as t_{PD}



SINGLE 2 INPUT POSITIVE NAND GATE


Ordering Information



	Davias	Package	Packaging	7" Tape a	and Reel
	Device	Code	(Note 5)	Quantity	Part Number Suffix
B	74AHC1G00W5-7	W5	SOT25	3000/Tape & Reel	-7
P	74AHC1G00SE-7	SE	SOT353	3000/Tape & Reel	-7

Notes: 5. Pad layout as shown on Diodes Inc. suggested pad layout document AP02001, which can be found on our website at http://www.diodes.com/datasheets/ap02001.pdf.

Marking Information




Part Number	Package	Identification Code
74AHC1G00W5	SOT25	YR
74AHC1G00SE	SOT353	YR



SINGLE 2 INPUT POSITIVE NAND GATE


Package Outline Dimensions (All Dimensions in mm)

(1) Package Type: SOT25



	SOT25							
Dim	Min	Max	Тур					
Α	0.35	0.50	0.38					
В	1.50	1.70	1.60					
С	2.70	3.00	2.80					
D	_	_	0.95					
Н	2.90	3.10	3.00					
J	0.013	0.10	0.05					
Κ	1.00	1.30	1.10					
L	0.35	0.55	0.40					
М	0.10	0.20	0.15					
Ν	0.70	0.80	0.75					
α	0°	8°						
All D	imensi	ons in	mm					

(2) Package Type: SOT353



SOT353		
Dim	Min	Max
Α	0.10	0.30
В	1.15	1.35
С	2.00	2.20
D	0.65 Тур	
F	0.40	0.45
Н	1.80	2.20
J	0	0.10
К	0.90	1.00
L	0.25	0.40
М	0.10	0.22
α	0°	8°
All Dimensions in mm		



SINGLE 2 INPUT POSITIVE NAND GATE

IMPORTANT NOTICE

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel.

Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

- A. Life support devices or systems are devices or systems which:
 - 1. are intended to implant into the body, or
 - 2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.
- B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products or systems.

Copyright © 2011, Diodes Incorporated

www.diodes.com