



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!




Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China





900 Series SMA

50 Ohm Cable and PCB Connectors



Product Description

Winchester's Bomar brand 900 Series 50 Ohm SMA Connectors can be used in a wide range of applications including Test and Measurement, Mil-Aero, Satellite, and Wireless Communication Equipment.


Our 900 Series 50 Ohm SMA Connectors are designed in accordance with MIL-STD 348 and feature a .250-36 threaded coupling interface designed for a frequency range of DC to 18 GHz.

Male cable plug connectors are available in straight and right-angle designs for popular flexible and semi-rigid cables.

Printed Circuit Board (PCB) connectors are available in straight and right-angle through-hole solder, and also in our unique E-Snap® Edge-Mount design.



- Threaded coupling ensures connector will not decouple in vibration-intensive applications



- Straight crimp plug center contact features a retention barb which snaps into the insulator to prevent the pin contact from backing out of the connector.



- E-Snap® Edge-Mount connectors provide superior RF performance versus traditional right-angle connects, as a straight contact provides the best transmission path

Specifications

Electrical

Impedance:	50 Ohms
Polarity:	Standard
Frequency (GHz):	
Flexible Cable	0 to 12.5 GHz
Semi-Rigid	0 to 18 GHz
VSWR: Straight	1.15 Max
Right-Angle	1.2 Max
Dielectric	
Withstanding Voltage:	
Flexible	1000 VRMS
Semi-Rigid	1500 VRMS
Contact Resistance:	
Center	≤ 2 mΩ
Outer	≤ 2 mΩ
Insulation Resistance:	5000 mΩ Min
Temperature Range:	-65°C to +165°C

Mechanical

Coupling Mating Torque:	7-15 in-lbs.
Cable Retention:	
Flexible	60 lbs. Min
Semi-Rigid	80 lbs. Min
Center Contact:	Solder / Crimp
Connector Durability:	500 Cycles Min

Material

Insulator Material:	PTFE
Body Material:	Brass
Body Finish:	Nickel or Gold
Contact Material:	Male Brass
	Female BECU
Contact Finish:	Gold
RoHS Compliant:	Yes

Part Numbering

Bomar Part Number	Straight and Right-Angle Cable Plugs	Crimp Tool	Hex Size
910A204M	Straight Plug for RG174, RG316, LMR100	BDHD200	Solder / .128
910A204F	Straight Plug for RG58, RG58A, RG141, LMR195	BDHD200	Solder / .213
910A204P	Straight Plug for RG55, RG142, RG223, RG400	BDHD200	Solder / .213
910A704HV	Straight Plug RG402 (use cable for center contact)	Solder	Solder
910A704B	Straight Plug RG402 Cable (with center contact supplied)	Solder	Solder
910A704A	Straight Plug RG405 Cable (with center contact supplied)	Solder	Solder
913A204M	Right-Angle Plug for RG174, RG316, LMR100	BDND200	Solder / .128
913A204F	Right-Angle Plug for RG58, RG58A, RG141, LMR195	BDHD200	Solder / .213
913A204P	Right-Angle Plug for RG55, RG142, RG223, RG400	BDHD200	Solder / .213
913A704B	Right-Angle Plug for RG402	Solder	Solder
913A704A	Right-Angle Plug for RG405	Solder	Solder

Bomar Part Number	Printed Circuit Board Connectors	PCB Thickness	Packaging
961A514	Vertical, SMA, Jack, 0.155" Solder Tail	0.062"	Single
964A595	Right-Angle, SMA, Jack, 0.155" Solder Tail	0.062"	Single
960A514	Vertical, SMA, Plug, 0.155" Solder Tail	0.062"	Single
963A595	Right-Angle, SMA, Plug, 0.155" Solder Tail	0.062"	Single
961E504	E-Snap® Edge-Mount, SMA, Jack	0.062"	Single
962E504	E-Snap® Edge-Mount, SMA, Plug	0.062"	Single
961E504HF	High Frequency E-Snap® Jack (26.5 GHz)	0.062"	Single



Winchester Electronics
 199 Park Road Extension, Suite 104
 Middlebury, Connecticut 06762
 203.741.5400 Phone
 203.741.5500 Fax
www.winchesterelectronics.com