



Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from,Europe,America and south Asia,supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of “Quality Parts,Customers Priority,Honest Operation,and Considerate Service”,our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip,ALPS,ROHM,Xilinx,Pulse,ON,Everlight and Freescale. Main products comprise IC,Modules,Potentiometer,IC Socket,Relay,Connector.Our parts cover such applications as commercial,industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China



Manual Switches

Mounting Hardware

AML61 Series

FOR STRIP AND MATRIX MOUNT ASSEMBLIES



FEATURES

- Enables subpanel mounting of devices in factory assembled metal cans which are welded together in strips or matrices. Assures accurate alignment and enables pre-wiring.
- L-shaped mounting brackets conform to various panel thicknesses, using spacers.
- Simplifies panel fabrication, since only one large cutout is required.
- Facilitates printed circuit board mounting. Operating force is transmitted to mounting hardware, rather than P.C. board.
- For custom matrices contact the MICRO SWITCH Application Center.
- Mounting dimensions page 64.

AML61 MOUNTING HARDWARE ORDER GUIDE


(For standard strip mount assemblies)

AML61 B		A	5	A
Type	Mounting Bracket Orientation	Number of Cans	Mounting Bracket Location	
Square cans: AML61 B (Plain finish) AML61 J (Black finish)	<div>A</div> <div>E</div>	1 2 3 4 5 6 7 8 9* 10* 11* 12*	<div>0.060</div> <div>A</div> <div>0.020</div> <div>G</div> <div>BRACKET FLUSH TO TOP OF CAN</div> <div>0.045</div> <div>K</div> <div>0.030</div> <div>B</div> <div>0.050</div> <div>L</div> <div>0.060</div> <div>C</div> <div>0.065</div> <div>P</div> <div>0.120</div> <div>E</div> <div>0.085</div> <div>T</div> <div>1.460</div> <div>F</div> <div>U NO BRACKETS</div>	
Rect. cans: AML61 E (Plain finish) AML61 K (Black finish)	<div>B</div> <div>C</div> <div>D</div> <div>1</div>	<div>*A, C, D & E orientation only.</div>		

① To order one rectangular can with mounting brackets on short sides, specify AML61EB1____ or AML61KB1____.

Example: AML61EC5A

Five rectangular cans, plain finish (unpainted), long sides abutting; type A mounting brackets on long sides, located flush with switch or indicator bezel. (Type T bracket brings top of annunciator bezel flush with top of .160 in./4,1 mm panel.)



This strip has Type F brackets for P.C. board mounting.

NON-STANDARD ASSEMBLIES

Use the order form on the following page to specify non-standard AML61 strip or matrix assemblies. You may reproduce it on your office copier, or order pads from the 800 number. Request FO-63558.

Manuals