

Chipsmall Limited consists of a professional team with an average of over 10 year of expertise in the distribution of electronic components. Based in Hongkong, we have already established firm and mutual-benefit business relationships with customers from, Europe, America and south Asia, supplying obsolete and hard-to-find components to meet their specific needs.

With the principle of "Quality Parts, Customers Priority, Honest Operation, and Considerate Service", our business mainly focus on the distribution of electronic components. Line cards we deal with include Microchip, ALPS, ROHM, Xilinx, Pulse, ON, Everlight and Freescale. Main products comprise IC, Modules, Potentiometer, IC Socket, Relay, Connector. Our parts cover such applications as commercial, industrial, and automotives areas.

We are looking forward to setting up business relationship with you and hope to provide you with the best service and solution. Let us make a better world for our industry!



### Contact us

Tel: +86-755-8981 8866 Fax: +86-755-8427 6832

Email & Skype: info@chipsmall.com Web: www.chipsmall.com

Address: A1208, Overseas Decoration Building, #122 Zhenhua RD., Futian, Shenzhen, China









AM-RT4-XXX AM-RT5-XXX **AM-RTQ4-XXX** AM-RT14-XXX

#### **Features**


- Complete RF Transmitter
- CMOS / TTL Input
- No Adjustable Components
- Very Stable Operating Frequency
- Low Current Consumption
- Low Spurious Emissions

#### **Applications**

- Wireless Security Systems
- Car Alarms
- Remote Gate Controls
- Remote Sensing
- Data Capture
- Sensor Reporting

#### **RT4 / RT5**

- Available as 315, 418, 433 MHz
- Range up to 70 metres
- SAW Design
- Available In DIL or SIL Package
- Wide Operating Voltage



#### RTQ4 / RT14

- **High Output Power**
- PLL Design
- Range 100+ metres
- Available as 433, 868 MHz

#### Description

The R F Solutions Ltd. AM hybrid transmitter module provides a complete RF transmitter which can be used to transmit data at up to 4KHz from any standard CMOS/TTL source.

The module is very simple to operate and offers low current consumption (typ. 4 mA). Data can be supplied directly from a microprocessor or encoding device, thus keeping the component count down and ensuring a low hardware cost.

The module exhibits extremely stable electronic characteristics due to the use of 'Thick-Film' hybrid technology, which uses no adjustable components and ensures very reliable operation.

The modules are compatible with R F solutions Ltd. range of AM receivers to provide a complete solution.

#### **Ordering Information**


Part Number	Description
AM-RT4-XXX	DIL AM Transmitter Module XXX MHz
AM-RTQ4-XXX	DIL AM Transmitter Module XXX MHz
AM-RT5-XXX	SIL AM Transmitter Module XXX MHz
AM-RT14-XXX	DIL AM Transmitter Module XXX MHz, SAW Resonator
AM-RT14-XXX-SO	SMT AM Transmitter Module XXX MHz, SAW Resonator


Frequency Availability


**XXX** = 315, 418, 433MHz Other Frequencies available on request RT4 / RT5: XXX = 868MHzRTQ4: Other Frequencies available on request RT14: XXX = 433MHzOther Frequencies available on request


©2008 REG No 277 4001, ENGLAND.


#### **Mechanical Dimensions**











#### **Notes**

Pins on 0.1" pitch

Pin Dimensions: 0.25 x 0.50mm

All measurements in mm

Tolerance: +/- 0.2mm

The component side differs depending on module

#### **Pin Descriptions**


RT4 / RTQ4 / RT14	RT14-SO	RT5	Name	Description
1	1	7	Vcc	Supply Voltage
2	2	6	GND	Ground, Connect to RF earth return path
3	4	2	IN	Data input
4	3	1	ANT	External Antenna

AM-RT4-XXX AM-RT5-XXX AM-RTQ4-XXX AM-RT14-XXX

### **Typical Application**

For further information on this circuit please see datasheet DS600

#### **Transmitter Circuit**



DS013-8

AM-RT4-XXX AM-RT5-XXX AM-RTQ4-XXX AM-RT14-XXX

#### **RT4/RT5: Electrical Characteristics**

Ambient temp = 25 °C unless otherwise stated.

Characteristic	Min.	Тур.	Max.	Dimensions
Supply Voltage	2		14	Vdc
Supply Current (Vcc=5V IN=1kHz)		4		mA
Supply Current (Vcc=5V IN=DC GND)		50		nA
Working Frequency	303.8		433.92	MHz
Frequency Tolerance		+/-100		KHz
RF Output Power into 50Ω (Vcc=5V)		0		dBm
Harmonic Spurious Emissions		-30		dBc
Input Voltage High	2		Vcc	V
Time from Power on to data transmission		10		μSec
Data Rate	50		9,600	bps
Operating Temperature	-25		+80	℃

#### **RTQ4: Electrical Characteristics**

ambient temp = 25 ℃ unless otherwise stated

Characteristic	Min.	Тур.	Max.	Dimensions
Supply Voltage	1.9		5	Vdc
Supply Current (Vcc=5V IN=1kHz)		12		mA
Working Frequency		868.35		MHz
Frequency Tolerance	-35		+35	KHz
RF Output Power into 50Ω (Vcc=4V)	+5	+7		dBm
Harmonic Spurious Emissions		-50		dBc
Input Voltage High	0.7*Vcc			V
Power-Up			1	mSec
Data Rate	50		9,600	bps
Operating Temperature	-25		+80	℃

#### **RT14: Electrical Characteristics**

Ambient temp = 25 ℃ unless otherwise stated.

Characteristic	Min.	Тур.	Max.	Dimensions
Supply Voltage	2		9	Vdc
Supply Current (Vcc=5V IN=1kHz)		8		mA
Working Frequency		433.92		MHz
RF Output Power into 50Ω (Vcc=4V)	+10	+12		dBm
Harmonic Spurious Emissions		-55		dBc
Input Voltage High	2		Vcc	V
Data Rate	50		9,600	Hz
Operating Temperature	-25		+80	$_{\mathbb{C}}$

R. F. Solutions Ltd., Unit 21, Cliffe Industrial Estate, South Street, Lewes, E Sussex, BN8 6JL, England.

Tel +44 (0)1273 898 000. Fax +44 (0)1273 480 661.

Email: sales@rfsolutions.co.uk Web: http://www.rfsolutions.co.uk